

11. REPLACEMENT PARTS LIST

1) Main Board

LTEM	PART NO.	LOCATION	SPECIFICATION	REMARK
1	GM447052J0	C1,C2,C65,C66,C67,C69,C70,C71,C85,C86,C113,C114,C115,C116,C117,C120,C127,C146,C154,C155,C157,C302,C304,C305,C330	CHIP MONO 1608 47P/50V JN MURATA	
2	GM433052J0	C3,C5,C23,C27,C33,C44,C53,C56,C57,C170,C172,C254,C273,C291,C311,C324,C364	CHIP MONO 1608 33P/50V JN MURATA	
3	GM04751870	C6,C135	CHIP MONO 2012 4.7U/10V ZY TATYO YUDEN	
4	GM410423J0	C7,C8,C9,C10,C11,C12,C63,C73,C74,C75,C76,C77,C83,C89,C137,C139,C140,C141,C142,C171,C206,C217,C218,C220,C251,C262,C266,C292,C319,	CHIP MONO 1608 0.1U/16V KX MURATA	
5	GM410518J0	C13,C109,C110,C119,C122,C124,C129,C138,C153,C219,C221,C263,C264,C300,C331,C340	CHIP MONO 1608 1U/10V ZY MURATA	
6	GM02251370	C14,C126,C131	CHIP MONO 2012 2.2U/10V KX TAIYO YUDEN	
7	GM410152J0	C16,C21,C22,C29,C34,C49,C50,C101,C198,C207,C211,C229,C260,C261,C280,C335	CHIP MONO 1608 100P/50V JN MURATA	
8	GM422253J0	C17	CHIP MONO 1608 2200P/50V KX MURATA	
9	GM11060KJ0	C18,C333	CHIP MONO 3216 10U/6.3V K/X5RMURATA	
10	GM447152J0	C19,C88,C125,C130,C163	CHIP MONO 1608 470P/50V JN MURATA	
11	GM910232J0	C20,C24,C28,C48,C60,C68,C81,C84,C91,C97,C104,C106,C161,C166,C175,C205,C208,C247,C274,C285,C339,C341,C342,C343,C356,C298	CHIP MONO 1608 0.001U/25V J/COH MURATA	
12	GM415052J0	C25,C26,C234,C240,C334	CHIP MONO 1608 15P/50V JNMURATA	
13	GM43995BJ0	C35,C203,C213	CHIP MONO 1608 3.9P/50V CNMURATA	
14	GM410353J0	C40,C202,C209,C222,C301	CHIP MONO 1608 0.01U/50V KX MURATA	
15	GM41805270	C46,C47,C99,C23,C180,C237,C315,C317,C318,C350,C358,C359	CHIP MONO 1608 18P/50V JNTAIYO YUDEN	
16	GM40105BJ0	C51,C152,C271,C361	CHIP MONO 1608 1P/50V CNMURATA	
17	GM43395BJ0	C52,C252,C269,C313,C314	CHIP MONO 1608 3.3P/50V CNMURATA	
18	GM418052J0	C54	CHIP MONO 1608 18P/50V JNMURATA	
19	GM922333J0	C64,C332	CHIP MONO1608 .022U/25V KX MURATA	
20	GM422428J0	C80	CHIP MONO 1608 0.22U/16V ZYMURATA	
21	GM11033MJ0	C82	CHIP MONO 3216 0.01U/25V J/COHMURATA	
22	GM415152J0	C87,C173	CHIP MONO 1608 150P/50V JN MURATA	
23	GM427052J0	C90,C151,C232,C345,C346,C347,C348,C353	CHIP MONO 1608 27P/50V JNMURATA	
24	GM412152J0	C95	CHIP MONO 1608 120P/50V JNMURATA	
25	GM40305BJ0	C96,C98	CHIP MONO 1608 2P/50V CNA	
26	GM40605CJ0	C100,C102,C162	CHIP MONO 1608 6P/50V DN MURATA	
27	GM422152J0	C103,C199	CHIP MONO 1608 220P/50V JN MURATA	
28	GM42295BJ0	C144,C204,C215,C281	CHIP MONO 1608 2.2P/50V CN MURATA	
29	GM40595BJ0	C147	CHIP MONO 1608 0.5P/50V CNMURATA	
30	GM40205BJ0	C148,C228,C327	CHIP MONO 1608 2P/50V CNMURATA	
31	GM41005CJ0	C149,C150,C158,C159,C184,C185,C223,C224,C241	CHIP MONO 1608 10P/50V DNMURATA	
32	GM44795BJ0	C156,C253	CHIP MONO 1608 4.7P/50V CN MUR ATA	
33	GM412052J0	C160,C177,C210,C236,C307,C308,C362	CHIP MONO 1608 12P/50V JNMURATA	
34	GM427152J0	C164	CHIP MONO 1608 270P/50V JNMURATA	
35	GM418253J0	C165	CHIP MONO 1608 1800P/50V KXMURATA	
36	GM40905CJ0	C189,C309,C310	CHIP MONO 1608 9P/50V DN MURATA	

LTEM	PART NO.	LOCATION	SPECIFICATION	REMARK
37	GM422052J0	C196,C197,C243,C258,C259,C357	CHIP MONO 1608 22P/50V JNMURATA	
38	GM410052J0	C214,C216	CHIP MONO 1608 10P/50V JN MURATA	
39	GM127252J0	C225	CHIP MONO 3216 0.0027U/50V JNCOG MURATA	
40	GM40805BJ0	C233	CHIP MONO 1608 8P/50V CNMURATA	
41	GM447333J0	C242,C329	CHIP MONO 1608 0.047U/25V KX MURATA	
42	GM40405BJ0	C245,C283	CHIP MONO 1608 4P/50V CNMURATA	
43	GM41295BJ0	C248,C268,C312,C363	CHIP MONO 1608 1.2P/50V CN MURATA	
44	GM433323J0	C255	CHIP MONO 1608 0.033U/16V KXMURATA	
45	GM456052J0	C256	CHIP MONO 1608 56P/50V JN MURATA	
46	GM11061870	C257	CHIP MONO 3216 10U/10V ZY TAIYOYUDEN	
47	GN410725E0	C265	CHIP TAN D 100U/16V M AVXKYOCERA	
48	GM42795BJ0	C287	CHIP MONO 1608 2.7P/50V CNMURATA	
49	GM46895BJ0	C290	CHIP MONO 1608 6.8P/50V CN MURATA	
50	GM415253J0	C306	CHIP MONO 1608 1500P/50V KXMURATA	
51	GM40505BJ0	C323	CHIP MONO 1608 5P/50V CN MURATA	
52	GM447253J0	C328	CHIP MONO 1608 .0047U/50V K MURATA	
53	GM433152J0	C338	CHIP MONO 1608 330P/50V JN MURATA	
54	EJ13008620	D1	DIODE BZX84-C4V3 SOT23 3P PHILIPS	
55	EJ15003160	D5	DIODE SMS7630-020 SOT-143 4P ALPHA	
56	EK920095W0	D6	ZEN DIODE LM4041CIM3-1.2 SOT23NATIONAL	
57	EJ15001240	D7,D8,D9	DIODE IMN10 SMD 6P ROHM	
58	R301007060	J1	CONNECTOR DF12D(3.0)-40DP-0.5V(81) HIROSE	
59	R327000510	J3	SIMLOCK 11.7x7.5x2.0mm	
60	JC101008Y0	J4	ANT-SW IMS 2104.99 IMS	
61	R3010064M0	J5	CARKIT HO1453G1 16P GD588	
62	R3010181F0	J6	BAT.CON.AB3043-A0G1K 4Pin	
63	R3010166M0	J10	VIBRATOR CONNECTOR 1.27mm PITCH 2 PIN SMT	
64	HD000019S0	L1,L18	CORE SMT 27nH 0603 5% KOA	
65	HD000020S0	L3	CORE SMT 47nH 0603 5% KOA	
66	HD000033S0	L4,L80	CORE SMT 82nH 0603 5% KOA	
67	HC10403070	L6,L11	CHIP BEAD 1608 60ohm (PANASONIC)	
68	HD000029S0	L7,L8,L92	CORE SMT 12nH 0603 5% KOA	
69	HD000030S0	L9,L10,L60	CORE SMT 18nH 0603 5% KOA	
70	HD000022S0	L13,L19	CORE SMT 8.2nH 0603 5% KOA	
71	HD000028S0	L15,L24,L25,L47,L81	CORE SMT 10nH 0603 5% KOA	
72	HD000032S0	L17,L44,L69	CORE SMT 56nH 0603 5% KOA	
73	HB100145E0	L20	COIL SMT 82nH 0603 5% COILCRAFT	
74	HD000042S0	L22,L26,L27	CORE SMT 2.7nH 0603 ±0.3nHKOA	
75	HD000024S0	L23,L56,L54,L88,L89	CORE SMT 3.9nH 0603 ±0.3nH KOA	
76	HD000043S0	L28,L29	CORE SMT 150nH 0603 5% KOA	
77	HD000026S0	L30,L84,L68	CORE SMT 4.7nH 0603 ±0.3nH KOA	
78	HD000027S0	L32,L35	CORE SMT 5.6nH 0603 ±0.3nHKOA	
79	HD000041S0	L36,L37	CORE SMT 2.2nH 0603 ±0.3nHKOA	
80	HD000018S0	L38,L39,L91	CORE SMT 22nH 0603 5% KOA	
81	HD000040S0	L49	CORE SMT 1.8nH 0603 ±0.3nHKOA	
82	HD000016S0	L58	CORE SMT 6.8nH 0603 5% KOA	
83	HD000044S0	L59	CORE SMT 1.2nH 0603 ±0.3nHKOA	
84	HD000031S0	L61,L62	CORE SMT 39nH 0603 5% KOA	

11. REPLACEMENT PARTS LIST

LTEM	PART NO.	LOCATION	SPECIFICATION	REMARK
85	HD000021S0	L63,L64,L65,L79	CORE SMT 68nH 0603 5% KOA	
86	HB100142E0	L67	COIL SMT 5.45nH 0906 5% COILCRAFT	
87	EG950001T0	Q1	MOSFET-P-SCH SI6923DQ TSSOP 8P VISHAY	
88	EA95853040	Q4	TR NPN UMH10N SC-88 6P ROHM	
89	EA95000440	Q5,Q20,Q28	TR NPN UMX1N UM6 6P ROHM	
90	EA95000740	Q10	TR NPN 2SC2411K SMT 3P ROHM	
91	EG92000430	Q13	MOSFET-P BSS84P SOT-23 3P SIEMENS	
92	EB95000840	Q15	TR PNP UMB10N SC-88 6P ROHM	
93	EA95001340	Q19	TR NPN/PNP UMD9N SC-88 6P ROHM	
94	EG920005T0	Q21,Q22	MOSFET-P SI2301DS SOT23 3P VI SHAY	
95	EB95000740	Q26,Q33	TR PNP 2SA1576A UMT3 3P ROHM	
96	EA95001240	Q27	TR NPN UMH11N SC-88 6P ROHM	
97	EB95000940	Q29	TR PNP UMA3N SC-88A 5P ROHM	
98	EF92000130	Q30	MOSFET-N BSS138 SOT23 3P SIEMENS	
99	EB95001040	Q31	TR PNP DTA123JUA SC-70 3P ROHM	
100	EG920011A0	Q34	FET P FDN338P SOT-23 FAIRCHILD	
101	FN01100300	R1,R2,R10,R102,R107,R118,R122,R156,R160,R185, R200,R239,R254,R255,R298,R303, R304,R314,R318	CHIP RES 1/10W 1% 100K 1608	
102	FM01000000	R3,R16,R27,R30,R31,R36, R37,R44,R45,R47,R52, R66,R78,R81,R94, R110,R117,R183,R184,R186,R188, R192,R193,R194,R199,R205,R223,R238,R242,R265, R266, R275,R276,R277,R282,R293,R308,R312,R313, R321,R322,R326,R330	CHIP RES 1/10W 5% 0ohm 1608	
103	FN01510100	R4,R155	CHIP RES 1/10W 1% 5.1Kohm 1608	
104	FN01270100	R5	CHIP RES 1/10W 1% 2.7K 1608	
105	FM01002000	R7,R56,R57,R101, R106	CHIP RES 1/10W 5% 2ohm 1608	
106	FN01100100	R8,R228,R229,R286,R287,R258,R261,R339	CHIP RES 1/10W 1% 1K 1608	
107	FM01051900	R12,R25,R54,R224	CHIP RES 1/10W 5% 5.1ohm 1608	
108	FN01510000	R17	CHIP RES 1/10W 1% 510ohm 1608	
109	FN01220100	R22,R26,R306,R327	CHIP RES 1/10W 1% 2.2K 1608	
110	FN01022000	R24	CHIP RES 1/10W 1% 22ohm 1608	
111	FN01100000	R38,R59,R60	CHIP RES 1/10W 1% 100ohm 1608	
112	FN01051000	R40,R41,R42,R43,R89,R90,R91,R92,R154,R341, R342,R343	CHIP RES 1/10W 1% 51ohm 1608	
113	FN01100200	R46,R95,R99,R103,R105,R125,R138,R173,R175, R212,R244,R249,R253,R280,R281, R299	CHIP RES 1/10W 1% 10K 1608	
114	FN01150200	R51,R58,R178,R182,R291,R307	CHIP RES 1% 15K 1608 1/10W	
115	FN01220300	R53,R219,R302,R335,R336	CHIP RES 1/10W 1% 220K 1608	
116	FN01300100	R55	CHIP RES 1/10W 1% 3K 1608	
117	FN01560300	R65,R148,R334	CHIP RES 1/10W 1% 560K 1608	
118	FN01120000	R67,R72,R323	CHIP RES 1/10W 1% 120ohm 1608	
119	FN01120100	R69	CHIP RES 1/10W 1% 1.2K 1608	
120	FN01180100	R74,R75	CHIP RES 1/10W 1% 1.8K 1608	
121	FN01180200	R76,R144,R245	CHIP RES 1/10W 1% 18K 1608	
122	FN01010000	R77,R132,R165	CHIP RES 1/10W 1% 10ohm 1608	
123	FN01300000	R79,R80	CHIP RES 1/10W 1% 300ohm 1608	
124	FN01560200	R85,R180,181	CHIP RES 1/10W 1% 56Kohm 1608	
125	FN01330200	R98	CHIP RES 1/10W 1% 33K 1608	
126	FN01270200	R100,R119	CHIP RES 1/10W 1% 27K 1608	

LTEM	PART NO.	LOCATION	SPECIFICATION	REMARK
127	FN01100400	R121,R123,R124,R248	CHIP RES 1/10W 1% 1M 1608	
128	FN01056000	R126	CHIP RES 1/10W 1% 56ohm 1608	
129	FM01033900	R128	CHIP RES 1/10W 5% 3.3ohm 1608	
130	FN01120300	R129	CHIP RES 1/10W 1% 120K 1608	
131	FN01120200	R131,R189	CHIP RES 1/10W 1% 12K 1608	
132	FN01470200	R130,R259	CHIP RES 1/10W 1% 47K 1608	
133	FN01047000	R133,R166,R169,R174, R294,R296,R297	CHIP RES 1/10W 1% 47ohm 1608	
134	FN01390100	R139	CHIP RES 1/10W 1% 3K9 1608	
135	FN01820200	R176,R177	CHIP RES 1/10W 1% 82K 1608	
136	FM01022900	R206	CHIP RES 1/10W 5% 2.2ohm 1608	
137	FN01330100	R215,R262	CHIP RES 1/10W 1% 3K3 1608	
138	FN01560000	R247	CHIP RES 1/10W 1% 560ohm 1608	
139	FN01330000	R252	CHIP RES 1/10W 1% 330ohm 1608	
140	FN01680200	R256,R292,R310	CHIP RES 1/10W 1% 68K 1608	
141	FN01220000	R257	CHIP RES 1/10W 1% 220ohm 1608	
142	FN01220200	R260	CHIP RES 1/10W 1% 22K 1608	
143	FN01470100	R278,R289,R290	CHIP RES 1/10W 4.7Kohm 1% 1608	
144	FM01075900	R279	CHIP RES 1/10W 5% 7.5ohm 1608	
145	FN01470000	R305	CHIP RES 1/10W 1% 470ohm 1608	
146	FM01027200	R315	CHIP RES 1/10W 5% 2.7K 1608	
147	FN01330300	R324,R325	CHIP RES 1/10W 1% 330K 1608	
148	FM01082900	R338	CHIP RES 1/10W 5% 8.2ohm 1608	
149	FN01200100	R344	CHIP RES 1/10W 1% 2K 1608	
150	CF21019BD0	U1	DSP 1689 TQFP 100P LUCENT	
151	DA00900Y40	U3,U43	AMPLIFIER UPC2771TB SMD 6P NE	
152	HA03203450	U4,U6	FILTER B4697 SMD 8P SIEMENS	
153	HA032036U0	U8	FILTER LDB15C101A1800 SMD 6P MURATA	
154	DA00998YT0	U9	AMPLIFIER RF2173 SMD 16PRFMD	
155	JZ010058Z0	U10	RX SAW B4684 SS-38S1(A) 6P SIEMENS	
156	DE03471YT0	U11	SIMPOWER LTC1555CGN SSOP 16P LINEAR	
157	BG049079S0	U12	FLASH TE28F160C3B90 TSOP 48PINTEL	
158	BB076059Y0	U14	SRAM BS62LV2000STC-70 STSOP32P	
159	CA12003DD0	U15	CPU CPP-2 V3.4 TQFP 100P LUCENT	
160	CG01006YS0	U19	IC-RF W3000 TSSOP 14P LUCENT	
161	HA03203550	U20,U44	FILTER B4692 SMD 8P SIEMENS	
162	DA00980YA0	U21	OP AMP OPA343 SOT-23 5P BURRBROWN	
163	HA03203350	U22	FILTER B4635 SMD 6P SIEMENS	
164	HA032032U0	U23	FILTER LMC36-07A0501B SMD 10P MURATA	
165	DZ70610YR0	U24,U25	REGULATOR AME8802JEEV SOT-23 5P ANALOG	
166	DZ70810YS0	U26	REGULATOR TC1185-2.85VCT SOT-23 5P TELCOM	
167	DZ70620YE0	U27	REGULATOR ILC7081AIM5 2.85VSOT-23A IMPALA	
168	EN460006Y0	U29	VCO-PCN UCVE3X191A SMD 8P ALPS	
169	EN460007Y0	U30	VCO-GSM UCVE3X190A SMD 8P ALPS	
170	CG01007YS0	U31	IC-RF W3020 TQFPT 64P LUCENT	
171	DA00950YT0	U32	AMPLIFIER RF2140 SMD 16P RFMD	
172	HA03203850	U33	FILTER B4210 SMD 9P SIEMENS	
173	EN40000120	U35	TCXO 13MHz END3352B SMD 4P NDK	

11. REPLACEMENT PARTS LIST

LTEM	PART NO.	LOCATION	SPECIFICATION	REMARK
174	AR10140310	U38	IC TC74VHC14FT TSSOP 14PTOSHIBA	
175	AR11320310	U39	IC TC74VHC132FT TSSOP 14PTOSHIBA	
176	DE03520Y80	U41	L-VOLT DET RN5VT29 SOT23 5P RICOH	
177	EN460008Y0	U42	VCO-IF UCVE1X114A-540MHz SMD	
178	JZ040002Z0	U45	FILTER-RF B4686 SMD 6P SIEMENS	
179	JZ040008Z0	U46	FILTER-RF B4693 SMD 8P SIEMENS	
180	AR10245310	U48	IC TC74VHC245FT TSSOP 20PTOSHIBA	
181	HA03203750	U50	FILTER B4836 SMD 12P SIEMENS	
182	DE04008YP0	U53	INVERTER TC7SH04FU SSOP 5PTOSHIBA	
183	JC101010T0	U54	SW-ELECTRON MAX4541EUA 8 μ MAX8P MAXIM	
184	AR10273310	U58	IC TC74VHC273FT TSSOP 20PTOSHIBA	
185	DZ80321YJ0	U59	REGULATOR TK71629SCLH SOT-23 5P TOKO	
186	EM432702Y0	X1	CRYSTAL 32.768KHz MC-206 SMD4P EPSON	
187	R3255003E0	ANTENNA	SPRING PLATE ANTENNA GD268M	
188	KG101703T0	NA	BOARD A758M 100x39mm	

2) Keyboard

LTEM	PART NO.	LOCATION	SPECIFICATION	REMARK
1	HJ02004760	BZ1	BUZZER SMT-8103C SMD SAMBU	
2	GM410423J0	C901,C915,C916,C925	CHIP MONO 1608 0.1U/16V KX MURATA	
3	GM410152J0	C902,C920	CHIP MONO 1608 100P/50V JN MURATA	
4	GM03351870	C903,C904,C905,C906	CHIP MONO 2012 3.3U/10V ZY TAIYO YUDEN	
5	GM410518J0	C907,C908,C909,C910,C911	CHIP MONO 1608 1U/10V ZY MURATA	
6	GM610152J0	C912,C913,C914	CHIP MONO 1005 100P/50V JN MURATA	
7	GM410052J0	C917	CHIP MONO 1608 10P/50V JN MURATA	
8	GM447052J0	C918,C919,C921,C922,C923	CHIP MONO 1608 47P/50V JN MURATA	
9	EJ15001340	D902	DIODE 1SS355 UMD2 P ROHM	
10	EL000359F0	D908,D909,D910,D911	LED LNJ310M6URA GREEN EVERLIGH	
11	EL000358F0	D912,D913,D914,D915, D918,D919	LED LNJ306G5URA GREEN SMD EVERLIGHT	
12	R301006860	J901	CONNECTOR DF12A(3.0)-40DS-0.5V (81) HIROSE	
13	HC10401240	L1,L2	CHIP BEAD BK 1608 HM121 TAIYO YUDEN	
14	EA95000740	Q901	TR NPN 2SC2411K SMT 3P ROHM	
15	EA95847020	Q902,Q903	TR NPN BC847BW SOT-323 3P IPS	
16	AR10574310	U901	IC 74VHC574FT(EL) TSSOP 20P TOSHIBA	
17	EJ15001240	U902,U903	DIODE IMN10 SMD 6P ROHM	
18	EJ15001640	U904	DIODE DA204U UMT3 P ROHM	
19	FM01010300	R901	CHIP RES 1/10W 5% 10K 1608	
20	FN21100200	R903,R904,R905	CHIP RES 1/16W 1% 10K 1005	
21	FM01020000	R907,R908	CHIP RES 1/10W 5% 20ohm 1608	
22	FM01022200	R909	CHIP RES 1/10W 5% 2.2K 1608	
23	FM21022100	R911	CHIP RES 1/16W 5% 220ohm 1005	
24	FP21104BC0	R912	CHIP ARRAY 1/16W 5% 100K 10 1608 RALEC	
25	FM21047200	R915	CHIP RES 1/16W 5% 4.7K 1005	
26	FM01010200	R916	CHIP RES 1/10W 5% 1K 1608	
27	FN01100300	R917,R918	CHIP RES 1/10W 1% 100K 1608	
28	FF900005B0	VR1,VR2	VARISTOR VA-A1608-5R5JJT SMD (CERATECH)	
29	KG101403X0	NA	BOARD A758K 100x39mm	

3) Mechanical/Electrical/Packing Parts

Item	Part No.	Specification	Remark
1	R393000930	Antenna (Black)	
2	R3870068A0	LCD Lens (In-Mold Grey)	
3	R395003660	Adhesive Tape for LCD Lens	
4	R3920024J0	Keypad (Silver White P+R)	
5	R401000260	Metal Dome for Keypad	
6	R2710150B0	Upper Case - Pearl White	
	R2710209B0	Upper Case - Dark Silver	
	R2710213B0	Upper Case - Blue	
7	R2720125B0	Lower Case (Dark Grey)	
8	R015403200	Rubber Cap (Dark Grey)	
9	R286002030	Shielding Cover	
10	R2820015B0	Button for Battery Eject	
11	R3250009V0	Button Spring for Battery Eject	
12	HJ00117460	Receiver	
13	HJ110029M0	Microphone	
14	JG100012C0	LCD Module	
15	R3970005C0	Nonwoven for Receiver	
16	R022051800	Backup Battery	
17	R4000004V0	Vibrator	
18	R382004090	Mylar	
19	R3850027H0	SIM Card Plate	
20	R382005080	Isolate Plate - Small for Screw Type M2x8L	
21	R382004880	Isolate Plate - Large for Lower Case	
22	HJ02004760	Buzzer	
23	R3010064M0	Carkit System Connector	
24	R3220026Q0	Screws - M2x8L	
25	R3220051Q0	Screws - M1.6x5.5L	
26	R3630029E0	Sponge for Receiver	
27	R3630065E0	Sponge for Buzzer	
28	R3630049G0	Sponge for Vibrator	
29	R3630069E0	Sponge for LCM	
30	R3630073E0	Sponge for Backup Battery	
31	R0274039X0	Pulp Modeling	

4) STANDARD ACCESSORIES

Item	Part No.	Specification
1	JB040042A0	Battery Pack - 600mAh Li-Ion
2	JB100083E0	Switching Travel Charger - Europe Version (Round Pin)

5) OPTIONAL ACCESSORIES

Item	Part No.	Specification
1		Headset
2		Cigar Lighter Charger
3		Mock up (Dummy)
4		Simple Handsfree Car Kit
5		Cable (for S/W Upgrading)
6		Cable (for RF Testing)