

PARTS LIST

CAUTION

- The parts identified by the \triangle symbol are important for the safety . Whenever replacing these parts, be sure to use specified ones to secure the safety .
- The parts not indicated in this Parts List and those which are filled with lines --- in the Parts No. columns will not be supplied .
- P. W. Board Ass'y will not be supplied, but those which are filled with the Parts No. in the Parts No. columns will be supplied .

ABBREVIATIONS OF RESISTORS, CAPACITORS

RESISTOR

RC.....	CARBON RESISTOR
MG R.....	METAL GLAZED RESISTOR

CAPACITORS

CC.....	CERAMIC CAPACITOR
CE.....	ALUMI ELECTROLYTIC CAPACITOR
CP.....	POLYESTER CAPACITOR
CPP.....	POLYPROPYLENE CAPACITOR
CPL.....	PLASTIC CAPACITOR
CMP.....	METAL POLYESTER CAPACITOR
CMPL.....	METAL PLASTIC CAPACITOR
CMPP.....	METAL POLYPROPYLENE CAPACITOR

CONTENTS

■ USING P.W. BOARD	33
■ MECHANICAL REPLACEMENT PARTS LIST	34
■ MECHANICAL EXPLODED VIEW [I]	35
■ MECHANICAL EXPLODED VIEW [II]	36
■ ELECTRICAL REPLACEMENT PARTS LIST	37
■ PACKING & ACCESSORY REPLACEMENT PARTS LIST	47


USING P.W. BOARD

P.W.B ASS'Y	Model
POWER PCB ASS'Y	X-A5C2042020
OPERATION PCB ASS'Y	X-A5C2042030
CRT PCB ASS'Y	X-A5C2042110
DVD PCB ASS'Y	X-A5C2042130
AV PCB ASS'Y	X-A5C2042250


MECHANICAL REPLACEMENT PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
101	X-A5C2042720	CABINET,FRONT ASSY	
102	X-761WPA0252	COVER,PCB ASS'Y	
103	X-7230007426	SHEET,IC	
104	X-7230007461	SHEET,IC	
105	X-761WPA0250	HOLDER,FFC	
106	X-761WSA0093	ANGLE,DECK	
107	X-8995034000	CORD CLIP UL CO.	
108	X-7235380003	BRAND,BADGE	
109	X-761WPA0249	HOLDER,FBT	
110	X-769WPA0018	GUIDE,CONNECTOR(FFC)	
112	X-702WPA0807	DOOR	
113	X-713WPA0144	GLASS,LED	
114	X-713WPA0145	GUIDE,REMOCON	
115	X-7230007285	SHEET,INDICATER	
116	X-7230007286	SHEET,INDICATER(JACK)	
117	X-702WPA0960	CABINET,BACK	
118	X-702WSA0125	PLATE,BOTTOM	
119	X-702WSA0144	SHIELD,TOP	
120	X-7230007529	SHEET,JACK	
121	X-7260000332	SHEET,CAUTION	
122	X-752WSA0297	SHIELD,JACK	
123	X-712WPB0119	PLATE,TRAY-FRONT	
124	X-7225380016	SHEET,RATING	
125	X-7235630001	SHEET,DVD	
126	X-735WPA0516	BUTTON,CLEAR	
127	X-741WUA0021	SPRING,EARTH	
128	X-735WPA0543	BUTTON,CHANNEL	
129	X-735WPD0732	BUTTON,FRAME	
130	X-735WPE0011	BUTTON,COVER	
131	X-735WPE0014	BUTTON,CAP(STOP)	
132	X-735WPE0015	BUTTON,CAP(OPEN)	
133	X-800WQ00056	FELT SHEET	
134	X-800WQ00039	FELT SHEET	
135	X-800WQ00041	FELT SHEET	
136	X-7220001107	SHEET,HWC	
137	X-7220001119	SHEET,CSA WARNING	
138	X-7230006818	SHEET,CAUTION	
139	X-7260000339	SHEET,CRT NO.	
140	X-741WUA0001	SPRING,EARTH	
141	X-762WPA0011	HOLDER,CRT WIRE	
142	X-890LA20000	NC LATCH(LA-2)	
143	X-899HV3T000	HOLDER,ANODE WIRE	
201	X-8121J50B54	SCREW,TAPPING(B0) GW20	5x28
202	X-8117540A64	SCREW,TAPPING(B0) TRUSS	4x16
203	X-8117540804	SCREW,TAPPING(B0) TRUSS	4x8
204	X-8109I30A04	SCREW,TAP TITE(B) WH7	3x10
205	X-8109I30804	SCREW,TAP TITE(B) WH7	3x8
206	X-8109230804	SCREW,TAP TITE(B) BIND	3x8
207	X-8109230704	SCREW,TAP TITE(B) R BIND	3x7
208	X-8109630604	SCREW,TAP TITE(B) BRAZIER	3x6
209	X-8110630A04	SCREW,TAP TITE(P) BRAZIER	3x10
210	X-8110226804	SCREW,TAP TITE(P) BIND	2.6x8
211	X-8107630804	SCREW,TAP TITE(S) BRAZIER	3x8
212	X-8110630804	SCREW,TAP TITE(P) BRAZIER	3x8

MECHANICAL EXPLODED VIEW [I]



MECHANICAL EXPLODED VIEW [II]



ELECTRICAL REPLACEMENT PARTS LIST

POWER PCB ASS'Y

△ Symbol.No.	Part No.	Part Name	Description
PCB020	X-A5C2042020	POWER PCB ASS'Y	VPB157A

RESISTORS

△ R3800	X-R4X5T6302F	R,METAL	3KΩ 1/6W
R3801	QRE141J-222Y	RC	2.2KΩ 1/4W
R3802	X-R002T2563J	RC	56KΩ 1/2W
△ R3803	X-R002T2155J	RC	1.5MΩ 1/2W
R3804	QRE141J-331Y	RC	330Ω 1/4W
R3805	QRE141J-102Y	RC	1KΩ 1/4W
△ R3806	X-R0G3K2275K	RC	2.7MΩ 1/2W
R3807	QRE141J-103Y	RC	10KΩ 1/4W
R3808	QRE141J-103Y	RC	10KΩ 1/4W
△ R3812	X-R3X181331J	R,METAL OXIDE	330Ω 1W
R3813	QRE141J-101Y	RC	100Ω 1/4W
R3816	QRE141J-271Y	RC	270Ω 1/4W
△ R3817	X-R5Y2CE010J	R,CEMENT	1Ω 7W
R3819	QRE141J-101Y	RC	100Ω 1/4W
△ R3821	X-R3X181R15J	R,METAL OXIDE	0.15Ω 1W
R3825	QRE121J-100Y	RC	10Ω 1/2W
R3826	QRE141J-125Y	RC	1.2MΩ 1/4W
R3827	QRE141J-125Y	RC	1.2MΩ 1/4W
△ R3828	X-R63581R22J	R,FUSE	0.22Ω 1W
R3829	QRE141J-101Y	RC	100Ω 1/4W
R3830	QRE141J-102Y	RC	1KΩ 1/4W
R3831	QRE141J-101Y	RC	100Ω 1/4W
R3832	QRE121J-102Y	RC	1KΩ 1/2W
R3833	QRE141J-331Y	RC	330Ω 1/4W

VARIABLE RESISTORS

VR3800	X-V1K63Q2BTE	VOLUME,SEMI FIXED	NVG6TLTAB471
--------	--------------	-------------------	--------------

CAPACITORS

C3800	X-CHGTB0413K	CC	0.001μF	50V	B
△ C3801	X-P2472B224M	CMP	0.22μF	275V	PHE840
△ C3802	X-CD39E0M13M	CC	0.001μF	250V	
△ C3803	X-CD39E0M13M	CC	0.001μF	250V	
△ C3804	X-P2472B104M	CMP	0.1μF	275V	PHE840
C3805	QCBB1HK-103Y	CC	0.01μF	50V	B
C3806	QCBB1HK-103Y	CC	0.01μF	50V	B
C3807	X-P232T1473J	CMP	0.047μF	100V	MMTV
C3807	X-P235W1473J	CMP	0.047μF	100V	MKT
C3808	X-E5EZU3470M	CE	47μF	25V	
△ C3810	X-C0JBB0713K	CC	0.001μF	2KV	B
C3811	X-C03L0R7E3K	CC	0.0015μF	2KV	R
△ C3812	X-C0JBB0713K	CC	0.001μF	2KV	B
C3814	X-CHGTB0413K	CC	0.001μF	50V	B
△ C3815	X-E51CGC471M	CE	470μF	200V	
△ C3815	X-E52DGC471M	CE	470μF	200V	
△ C3816	X-CD39E0mH3M	CC	0.0022μF	250V	
△ C3818	X-E5EZ02102M	CE	1000μF	16V	
△ C3820	X-E5EZU8100M	CE	10μF	100V	
△ C3822	X-E5EZF2222M	CE	2200μF	16V	
△ C3823	X-E5EZF3102M	CE	1000μF	25V	
C3824	X-C0PLRR7Q2K	CC	470pF	2KV	RR
C3824	X-C03L0R7Q2K	CC	470pF	2KV	R
△ C3826	X-E62NFC221M	CE	220μF	200V	
△ C3827	X-E5EZF2222M	CE	2200μF	16V	

DIODES

D3801	X-D97U05R61B	ZENER	MTZJ5.6BT-77
D3802	X-D1VT001330	SILICON	1SS133T-77
D3804	X-D97U01801B	ZENER	MTZJ18BT-77
D3806	X-D1VT001330	SILICON	1SS133T-77
D3807	X-D2WXXN49370	SILICON	1N4937
△ D3808	X-D2WTRM11C0	SILICON	RM11C-EIC
△ D3809	X-D2WTRM11C0	SILICON	RM11C-EIC
D3810	X-D97U01801B	ZENER	MTZJ18BT-77
△ D3815	X-D2WTRM11C0	SILICON	RM11C-EIC
△ D3816	X-D2WTRM11C0	SILICON	RM11C-EIC
△ D3817	X-D2LKB340L0	SCHOTTKY	SB340L-6737
△ D3818	X-D2WXXN49370	SILICON	1N4937
△ D3819	X-D28T21DQN9	SCHOTTKY	21DQ09N-TA2B1
△ D3820	X-D2WXB290S0	SILICON	SB290S
△ D3821	X-D2WXR2A0M0	SILICON	RU2AM-EIC
D3822	X-D1VT001330	SILICON	1SS133T-77
△ D3823	X-D2WXB290S0	SILICON	SB290S
△ D3824	X-D2WXB290S0	SILICON	SB290S

△ Symbol.No.	Part No.	Part Name	Description
D3825	X-D97U01101B	ZENER	MTZJ11BT-77
D3826	X-D1VT001330	SILICON	1SS133T-77
D3827	X-D1VT001330	SILICON	1SS133T-77
D3828	X-D97U03R91B	ZENER	MTZJ3.9BT-77
D3829	X-D1VT001330	SILICON	1SS133T-77
△ D3830	X-D28T21DQN9	SCHOTTKY	21DQ09N-TA2B1
D3831	X-D97U05R11B	ZENER	MTZJ5.1BT-77

ICS

△ IC3800	X-0002E00610	PHOTO COUPLER	LTV-817M-VB
----------	--------------	---------------	-------------

TRANSISTORS

Q3800	X-TCATC31980	SILICON	KTC3198-AT(Y,GR)
Q3801	X-TCATC31980	SILICON	KTC3198-AT(Y,GR)
△ Q3802	X-TCAT032034	SILICON	KTC3203_YAT
△ Q3803	X-T220033260	FET	2SK3326(2)

COILS

△ L3801	X-029T000105	COIL,LINE FILTER	2R2A752F28
L3803	X-02A6B2E0A1	CORE,FERRITE	HF70T22"10"14

TRANSFORMERS

△ T3800	X-481350824	TRANSFORMER,SWITCHING	81350824
---------	-------------	-----------------------	----------

CONNECTORS

△ CP3800	X-069S420110	CONNECTOR PCB SIDE	A1561WV2-2P
CP3802	X-069R260589	CONNECTOR PCB SIDE	52147-0610
CP3803	X-069R2A0589	CONNECTOR PCB SIDE	52147-1010
PH3800	X-069D01001A	CONNECTOR PCB SIDE	003P-2100

OTHERS

B3800	X-024HT03563	CORE,BEADS	W4BRH3.5X6X1.0X2
B3801	X-024HT03553	CORE,BEADS	W5RH3.5X5X1.0
△ BD3800	X-120R414903	CORD AC BUSH	0R414903
EL001	X-124120301A	EYE LET	XRY20X30BD
EL002	X-124116281A	EYE LET	XRY16X28BD
△ F3800	X-081PC05004	FUSE	51MS050LCC
FH3800	X-06710T0006	HOLDER,FUSE	EYF-52BC
FH3801	X-06710T0006	HOLDER,FUSE	EYF-52BC
△ RY3800	X-0560V20115	RELAY	ALKS321
△ TH3800	X-DF5EL3R0A0	DEGAUSS ELEMENT	ZPB45BL3R0A

OPERATION PCB ASS'Y

△ Symbol.No.	Part No.	Part Name	Description
PCB030	X-A5C2042030	OPERATION PCB ASS'Y	TEBB03A

RESISTORS

R751	QRE141J-821Y	RC	820Ω 1/4W
R752	QRE141J-102Y	RC	1KΩ 1/4W
R753	QRE141J-560Y	RC	56Ω 1/4W
R754	QRE141J-152Y	RC	1.5KΩ 1/4W
R755	QRE141J-272Y	RC	2.7KΩ 1/4W
R756	QRE141J-682Y	RC	6.8KΩ 1/4W
R757	QRE141J-271Y	RC	270Ω 1/4W

CAPACITORS

C751	QEKJ1CM-476Z	CE	47μF 16V
------	--------------	----	----------

DIODES

D751	X-21721150	LED	SLR-342VCT32
D752	X-D97U06R81B	ZENER	MTZJ6.8BT-77

△ Symbol.No.	Part No.	Part Name	Description
TRANSISTORS			
Q751	X-TNATX05001	COMPOUND	KRC114MAT
SWITCHES			
SW751	X-0504101T34	TACT	EVQ21505R
SW751	X-0504201T31	TACT	SKHVBED010
SW752	X-0504101T34	TACT	EVQ21505R
SW752	X-0504201T31	TACT	SKHVBED010
SW753	X-0504101T34	TACT	EVQ21505R
SW753	X-0504201T31	TACT	SKHVBED010
SW754	X-0504101T34	TACT	EVQ21505R
SW754	X-0504201T31	TACT	SKHVBED010
SW755	X-0504101T34	TACT	EVQ21505R
SW755	X-0504201T31	TACT	SKHVBED010
SW756	X-0504101T34	TACT	EVQ21505R
SW756	X-0504201T31	TACT	SKHVBED010
CONNECTORS			
CD751	X-122S062101	CORD JUMPER	2S062101
CP751	X-069J760019	CONNECTOR PCB SIDE	IMSA-9604S-06Z13
OTHERS			
OS751	X-077Q000019	REMOTE RECEIVER	PIC-28143TC5
CRT PCB ASS'Y			
△ Symbol.No.	Part No.	Part Name	Description
PCB110	X-A5C2042110	CRT PCB ASS'Y	TCB402A
RESISTORS			
R801	NRSA02J-221X	MG R	220Ω 1/10W
R802	X-R001T4272J	RC	2.7KΩ 1/4W
△ R803	X-R3X18A123J	R,METAL OXIDE	12KΩ 2W
R804	X-R001T4272J	RC	2.7KΩ 1/4W
△ R805	X-R3X18A123J	R,METAL OXIDE	12KΩ 2W
R806	X-R001T4272J	RC	2.7KΩ 1/4W
△ R807	X-R3X18A123J	R,METAL OXIDE	12KΩ 2W
R808	NRSA02J-221X	MG R	220Ω 1/10W
R809	NRSA02J-182X	MG R	1.8KΩ 1/10W
R810	NRSA02J-221X	MG R	220Ω 1/10W
R811	NRSA02J-182X	MG R	1.8KΩ 1/10W
R812	NRSA02J-561X	MG R	560Ω 1/10W
R813	NRSA02J-331X	MG R	330Ω 1/10W
R814	NRSA02J-182X	MG R	1.8KΩ 1/10W
R815	NRSA02J-331X	MG R	330Ω 1/10W
R816	NRSA02J-331X	MG R	330Ω 1/10W
R817	NRSA02J-561X	MG R	560Ω 1/10W
R818	NRSA02J-561X	MG R	560Ω 1/10W
CAPACITORS			
C801	X-CS0KSL412K	CC	100pF 50V SL
C802	X-C0JBB0713K	CC	0.001μF 2KV B
C803	NCB21HK-102X	CC	0.001μF 50V B
C809	NDC21HJ-391X	CC	390pF 50V CH
C810	NDC21HJ-271X	CC	270pF 50V CH
C811	NDC21HJ-271X	CC	270pF 50V CH
DIODES			
D801	X-D1VT001330	SILICON	1SS133T-77
D802	X-D1VT001330	SILICON	1SS133T-77
D803	X-D1VT001330	SILICON	1SS133T-77

△ Symbol.No.	Part No.	Part Name	Description
TRANSISTORS			
△ Q801	X-TCYT1740S0	SILICON	2SC1740SPTP
△ Q802	X-TCYT1740S0	SILICON	2SC1740SPTP
△ Q803	X-TCYT1740S0	SILICON	2SC1740SPTP
△ Q804	X-TCA0042170	SILICON	KTC4217(O,Y)
△ Q805	X-TCA0042170	SILICON	KTC4217(O,Y)
△ Q806	X-TCA0042170	SILICON	KTC4217(O,Y)
COILS			
L801	X-021673151K	COIL	150μH
L802	X-021673151K	COIL	150μH
L803	X-021673151K	COIL	150μH
L804	X-021673151K	COIL	150μH
OTHERS			
CP801	X-069S320010	CONNECTOR PCB SIDE	A2361WV2-2P
CP802B	X-067U005049	WIRE HOLDER	B2013H02-5P
CP803B	X-067U004029	WIRE HOLDER	B2013H02-4P
CP805	X-069S320010	CONNECTOR PCB SIDE	A2361WV2-2P
△ J801	X-066C130017	SOCKET,CATHODE RAY TUBE	CVT3275-5101
DVD PCB ASS'Y			
△ Symbol.No.	Part No.	Part Name	Description
PCB130	X-A5C2042130	DVD PCB ASS'Y	VMB261A
RESISTORS			
R1001	NRSA63J-103X	MG R	10KΩ 1/16W
R1002	NRSA63J-103X	MG R	10KΩ 1/16W
R1003	NRSA63J-104X	MG R	100KΩ 1/16W
R1004	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1005	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1008	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1009	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1010	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1011	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1012	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1014	NRSA63J-103X	MG R	10KΩ 1/16W
R1015	NRSA63J-103X	MG R	10KΩ 1/16W
R1016	NRSA63J-103X	MG R	10KΩ 1/16W
R1017	NRSA63J-330X	MG R	33Ω 1/16W
R1018	NRSA63J-103X	MG R	10KΩ 1/16W
R1019	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1020	NRSA63J-103X	MG R	10KΩ 1/16W
R1021	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1023	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1024	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1026	NRSA63J-473X	MG R	47KΩ 1/16W
R1027	NRSA63J-473X	MG R	47KΩ 1/16W
R1030	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1031	NRSA63J-103X	MG R	10KΩ 1/16W
R1032	NRSA63J-103X	MG R	10KΩ 1/16W
R1034	NRSA63J-103X	MG R	10KΩ 1/16W
R1036	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1037	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1038	NRSA63J-103X	MG R	10KΩ 1/16W
R1039	NRSA63J-103X	MG R	10KΩ 1/16W
R1040	NRSA63J-103X	MG R	10KΩ 1/16W
R1041	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1046	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1047	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1048	NRSA63J-103X	MG R	10KΩ 1/16W
R1049	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1050	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1051	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1053	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1054	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1055	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1066	NRSA63J-103X	MG R	10KΩ 1/16W
R1067	NRSA63J-472X	MG R	4.7KΩ 1/16W
R1068	NRSA63J-472X	MG R	4.7KΩ 1/16W

△ Symbol.No. Part No. Part Name Description

RESISTORS

R1069	NRSA63J-330X	MG R	33Ω 1/16W
R1070	NRSA63J-330X	MG R	33Ω 1/16W
R1071	NRSA63J-330X	MG R	33Ω 1/16W
R1072	NRSA63J-330X	MG R	33Ω 1/16W
R1073	NRSA63J-330X	MG R	33Ω 1/16W
R1074	NRSA63J-472X	MG R	4.7KΩ 1/16W
R2001	NRSA63J-104X	MG R	100KΩ 1/16W
R2002	NRSA63J-333X	MG R	33KΩ 1/16W
R2006	NRSA63J-102X	MG R	1KΩ 1/16W
R2007	NRSA63J-102X	MG R	1KΩ 1/16W
R2008	NRSA63J-102X	MG R	1KΩ 1/16W
R2009	NRSA63J-102X	MG R	1KΩ 1/16W
R2010	NRSA63J-102X	MG R	1KΩ 1/16W
R2011	NRSA63J-102X	MG R	1KΩ 1/16W
R2012	NRSA63J-103X	MG R	10KΩ 1/16W
R2013	NRSA63J-103X	MG R	10KΩ 1/16W
R2014	NRSA63J-153X	MG R	15KΩ 1/16W
R2016	NRSA63J-103X	MG R	10KΩ 1/16W
R2017	NRSA63J-103X	MG R	10KΩ 1/16W
R2020	NRSA63J-221X	MG R	220Ω 1/16W
R2021	NRSA63J-221X	MG R	220Ω 1/16W
R2022	NRSA63J-221X	MG R	220Ω 1/16W
R2023	NRSA63J-221X	MG R	220Ω 1/16W
R2024	NRSA63J-221X	MG R	220Ω 1/16W
R2025	NRSA63J-103X	MG R	10KΩ 1/16W
R2026	NRSA63J-103X	MG R	10KΩ 1/16W
R2027	NRSA63J-103X	MG R	10KΩ 1/16W
R2028	NRSA63J-220X	MG R	22Ω 1/16W
R2029	NRSA63J-103X	MG R	10KΩ 1/16W
R2030	NRSA63J-562X	MG R	5.6KΩ 1/16W
R2031	NRSA63J-103X	MG R	10KΩ 1/16W
R2033	NRSA63J-221X	MG R	220Ω 1/16W
R2035	NRSA63J-273X	MG R	27KΩ 1/16W
R2036	NRSA63J-103X	MG R	10KΩ 1/16W
R2037	NRSA63J-220X	MG R	22Ω 1/16W
R2038	NRSA63J-103X	MG R	10KΩ 1/16W
R2039	NRSA63J-103X	MG R	10KΩ 1/16W
R2041	NRSA63J-105X	MG R	1MΩ 1/16W
R2042	NRSA63J-122X	MG R	1.2KΩ 1/16W
R2043	NRSA63J-182X	MG R	1.8KΩ 1/16W
R2044	NRSA63J-223X	MG R	22KΩ 1/16W
R2045	NRSA63J-223X	MG R	22KΩ 1/16W
R2046	NRSA63J-151X	MG R	150Ω 1/16W
R2052	NRSA63J-122X	MG R	1.2KΩ 1/16W
R2054	NRSA63J-681X	MG R	680Ω 1/16W
R2064	NRSA63J-221X	MG R	220Ω 1/16W
R2301	NRSA63J-103X	MG R	10KΩ 1/16W
R2302	NRSA63J-103X	MG R	10KΩ 1/16W
R2303	NRSA63J-103X	MG R	10KΩ 1/16W
R2304	NRSA63J-103X	MG R	10KΩ 1/16W
R2305	NRSA63J-103X	MG R	10KΩ 1/16W
R2306	NRSA63J-223X	MG R	22KΩ 1/16W
R2307	NRSA63J-103X	MG R	10KΩ 1/16W
R2308	NRSA63J-153X	MG R	15KΩ 1/16W
R2309	NRSA63J-101X	MG R	100Ω 1/16W
R2310	NRSA63J-103X	MG R	10KΩ 1/16W
R2311	NRSA63J-101X	MG R	100Ω 1/16W
R2312	NRSA63J-101X	MG R	100Ω 1/16W
R2313	NRSA63J-103X	MG R	10KΩ 1/16W
R2314	NRSA63J-123X	MG R	12KΩ 1/16W
R2315	NRSA63J-223X	MG R	22KΩ 1/16W
R2316	NRSA63J-103X	MG R	10KΩ 1/16W
R2317	NRSA63J-562X	MG R	5.6KΩ 1/16W
R2318	NRSA63J-103X	MG R	10KΩ 1/16W
R2319	NRSA63J-103X	MG R	10KΩ 1/16W
R2320	NRSA63J-103X	MG R	10KΩ 1/16W
R2321	NRSA63J-153X	MG R	15KΩ 1/16W
R2322	NRSA63J-103X	MG R	10KΩ 1/16W
R2323	NRSA63J-105X	MG R	1MΩ 1/16W
R2324	NRSA63J-102X	MG R	1KΩ 1/16W
R2603	NRSA63J-103X	MG R	10KΩ 1/16W
R2604	NRSA63J-102X	MG R	1KΩ 1/16W
R2605	NRSA63J-102X	MG R	1KΩ 1/16W
R2606	NRSA63J-823X	MG R	82KΩ 1/16W
R2607	NRSA63J-823X	MG R	82KΩ 1/16W
R2608	NRSA63J-220X	MG R	22Ω 1/16W
R2609	NRSA63J-220X	MG R	22Ω 1/16W
R2610	NRSA63J-220X	MG R	22Ω 1/16W
R2611	NRSA63J-220X	MG R	22Ω 1/16W
R2614	NRSA63J-103X	MG R	10KΩ 1/16W
R2615	NRSA63J-123X	MG R	12KΩ 1/16W

△ Symbol.No. Part No. Part Name Description

RESISTORS

R2617	NRSA63J-102X	MG R	1KΩ 1/16W
R2618	NRSA63J-102X	MG R	1KΩ 1/16W
R2619	NRSA63J-2R2X	MG R	2.2Ω 1/16W
R2620	NRSA63J-561X	MG R	560Ω 1/16W
R2621	NRSA63J-102X	MG R	1KΩ 1/16W
R2622	NRSA63J-273X	MG R	27KΩ 1/16W
R2623	NRSA63J-471X	MG R	470Ω 1/16W
R2625	NRSA63J-103X	MG R	10KΩ 1/16W
R2626	NRSA63J-273X	MG R	27KΩ 1/16W
R2627	NRSA63J-331X	MG R	330Ω 1/16W
R2628	NRSA63J-331X	MG R	330Ω 1/16W
R2629	NRSA63J-273X	MG R	27KΩ 1/16W
R2630	NRSA63J-331X	MG R	330Ω 1/16W
R2631	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2632	NRSA63J-682X	MG R	6.8KΩ 1/16W
R2633	NRSA63J-563X	MG R	56KΩ 1/16W
R2634	NRSA63J-331X	MG R	330Ω 1/16W
R2638	NRSA63J-151X	MG R	150Ω 1/16W
R2639	NRSA63J-683X	MG R	68KΩ 1/16W
R2640	NRSA63J-331X	MG R	330Ω 1/16W
R2642	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2643	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2644	NRSA63J-331X	MG R	330Ω 1/16W
R2645	NRSA63J-223X	MG R	22KΩ 1/16W
R2646	NRSA63J-473X	MG R	47KΩ 1/16W
R2647	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2649	NRSA63J-473X	MG R	47KΩ 1/16W
R2650	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2651	NRSA63J-331X	MG R	330Ω 1/16W
R2652	NRSA63J-331X	MG R	330Ω 1/16W
R2653	NRSA63J-473X	MG R	47KΩ 1/16W
R2654	NRSA63J-473X	MG R	47KΩ 1/16W
R2655	NRSA63J-333X	MG R	33KΩ 1/16W
R2656	NRSA63J-473X	MG R	47KΩ 1/16W
R2657	NRSA63J-331X	MG R	330Ω 1/16W
R2658	NRSA63J-333X	MG R	33KΩ 1/16W
R2659	NRSA63J-104X	MG R	100KΩ 1/16W
R2660	NRSA63J-223X	MG R	22KΩ 1/16W
R2661	NRSA63J-273X	MG R	27KΩ 1/16W
R2662	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2663	NRSA63J-103X	MG R	10KΩ 1/16W
R2664	NRSA63J-223X	MG R	22KΩ 1/16W
R2665	NRSA63J-223X	MG R	22KΩ 1/16W
R2666	NRSA63J-223X	MG R	22KΩ 1/16W
R2667	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2668	NRSA63J-223X	MG R	22KΩ 1/16W
R2669	NRSA63J-104X	MG R	100KΩ 1/16W
R2670	NRSA63J-222X	MG R	2.2KΩ 1/16W
R2671	NRSA63J-103X	MG R	10KΩ 1/16W
R2672	NRSA63J-104X	MG R	100KΩ 1/16W
R2673	NRSA63J-103X	MG R	10KΩ 1/16W
R2674	NRSA63J-103X	MG R	10KΩ 1/16W
R2675	NRSA63J-103X	MG R	10KΩ 1/16W
R4001	NRSA63J-103X	MG R	10KΩ 1/16W
R4002	NRSA63J-103X	MG R	10KΩ 1/16W
R4003	NRSA63J-103X	MG R	10KΩ 1/16W
R4004	NRSA63J-103X	MG R	10KΩ 1/16W
R4005	NRSA63J-101X	MG R	100Ω 1/16W
R4006	NRSA63J-103X	MG R	10KΩ 1/16W
R4007	NRSA63J-103X	MG R	10KΩ 1/16W
R4008	X-R803R9391F	RC	390Ω 1/16W
R4009	NRSA63J-220X	MG R	22Ω 1/16W
R4010	NRSA63J-101X	MG R	100Ω 1/16W
R4011	NRSA63J-101X	MG R	100Ω 1/16W
R4012	NRSA63J-472X	MG R	4.7KΩ 1/16W
R4015	NRSA63J-330X	MG R	33Ω 1/16W
R4016	NRSA63J-101X	MG R	100Ω 1/16W
R4017	NRSA63J-101X	MG R	100Ω 1/16W
R4018	NRSA63J-101X	MG R	100Ω 1/16W
R4019	NRSA63J-103X	MG R	10KΩ 1/16W
R4021	NRSA63J-105X	MG R	1MΩ 1/16W
R4023	NRSA63J-472X	MG R	4.7KΩ 1/16W
R4024	NRSA63J-472X	MG R	4.7KΩ 1/16W
R4025	NRSA63J-472X	MG R	4.7KΩ 1/16W
R4026	NRSA63J-472X	MG R	4.7KΩ 1/16W
R4027	NRSA63J-100X	MG R	10Ω 1/16W
R4028	X-R803R9511F	RC	510Ω 1/16W
R4029	X-R803R9102F	RC	1KΩ 1/16W
R4030	NRSA63J-102X	MG R	1KΩ 1/16W
R8501	X-R803R9750F	RC	75Ω 1/16W
R8502	X-R803R9750F	RC	75Ω 1/16W

△ Symbol.No.	Part No.	Part Name	Description
RESISTORS			
R8503	X-R803R9750F	RC	75Ω 1/16W
R8504	X-R803R9750F	RC	75Ω 1/16W
R8506	NRSA63J-222X	MG R	2.2KΩ 1/16W
R8507	NRSA63J-222X	MG R	2.2KΩ 1/16W
R8508	NRSA63J-222X	MG R	2.2KΩ 1/16W
R8515	X-R803R9750F	RC	75Ω 1/16W
R8516	NRSA63J-681X	MG R	680Ω 1/16W
R8520	NRSA63J-102X	MG R	1KΩ 1/16W
R8522	NRSA63J-104X	MG R	100KΩ 1/16W
R8523	NRSA63J-104X	MG R	100KΩ 1/16W

CAPACITORS			
C1001	NCB31EZ-104X	CC	0.1μF 25V F
C1002	NDC31HJ-180X	CC	18pF 50V CH
C1003	NDC31HJ-180X	CC	18pF 50V CH
C1004	X-E62FU0151M	CE	150μF 6.3V
C1005	NCB31EZ-104X	CC	0.1μF 25V F
C1006	NCB31EZ-104X	CC	0.1μF 25V F
C1007	X-E62FU0151M	CE	150μF 6.3V
C1008	NCB31EZ-104X	CC	0.1μF 25V F
C1009	NCB31EZ-104X	CC	0.1μF 25V F
C1011	NCB31EZ-104X	CC	0.1μF 25V F
C1012	X-E524U2470D	CE	47μF 16V
C1013	NCB31EZ-104X	CC	0.1μF 25V F
C1014	NCB31EZ-104X	CC	0.1μF 25V F
C1015	NCB31EZ-104X	CC	0.1μF 25V F
C1016	NDC31HJ-101X	CC	100pF 50V CH
C1017	NDC31HJ-101X	CC	100pF 50V CH
C1018	NCB21CK-105X	CC	1μF 16V B
C1019	NCB31EZ-104X	CC	0.1μF 25V F
C1020	NDC31HJ-220X	CC	22pF 50V CH
C1021	NCB31EZ-104X	CC	0.1μF 25V F
C2002	NCB31CK-104X	CC	0.1μF 16V B
C2003	NCB31HK-102X	CC	0.001μF 50V B
C2006	NCB31HK-102X	CC	0.001μF 50V B
C2009	NCB31CK-104X	CC	0.1μF 16V B
C2010	X-E62FU0151M	CE	150μF 6.3V
C2011	NCB31HK-102X	CC	0.001μF 50V B
C2014	NCB31HK-102X	CC	0.001μF 50V B
C2015	NCB31HK-102X	CC	0.001μF 50V B
C2016	NCB31HK-102X	CC	0.001μF 50V B
C2017	NDC31HJ-471X	CC	470pF 50V CH
C2018	NDC31HJ-471X	CC	470pF 50V CH
C2019	NCB31CK-104X	CC	0.1μF 16V B
C2020	NCB31HK-102X	CC	0.001μF 50V B
C2021	NCB31CK-104X	CC	0.1μF 16V B
C2023	X-E62FU0151M	CE	150μF 6.3V
C2024	NCB31CK-104X	CC	0.1μF 16V B
C2030	NCB31CK-104X	CC	0.1μF 16V B
C2031	NCB31CK-104X	CC	0.1μF 16V B
C2032	NCB31CK-104X	CC	0.1μF 16V B
C2033	X-E62FU0151M	CE	150μF 6.3V
C2034	NCB31HK-103X	CC	0.01μF 50V B
C2035	NCB31CK-104X	CC	0.1μF 16V B
C2036	NCB31CK-104X	CC	0.1μF 16V B
C2037	NCB31CK-104X	CC	0.1μF 16V B
C2038	NCB31CK-104X	CC	0.1μF 16V B
C2039	NDC31HJ-150X	CC	15pF 50V CH
C2040	NDC31HJ-150X	CC	15pF 50V CH
C2041	NCB31CK-104X	CC	0.1μF 16V B
C2043	NDC31HJ-151X	CC	150pF 50V CH
C2045	X-E62FU0151M	CE	150μF 6.3V
C2046	X-E62FU0151M	CE	150μF 6.3V
C2048	NCB31CK-104X	CC	0.1μF 16V B
C2049	NCB31CK-104X	CC	0.1μF 16V B
C2050	X-E62FU0151M	CE	150μF 6.3V
C2051	X-E62FU0151M	CE	150μF 6.3V
C2052	NCB31CK-104X	CC	0.1μF 16V B
C2053	X-E62FU0151M	CE	150μF 6.3V
C2301	NCB31CK-104X	CC	0.1μF 16V B
C2303	NCB31CK-104X	CC	0.1μF 16V B
C2304	NCB31CK-104X	CC	0.1μF 16V B
C2305	NCB31CK-104X	CC	0.1μF 16V B
C2306	NCB31CK-104X	CC	0.1μF 16V B
C2307	NCB31HK-222X	CC	0.0022μF 50V B
C2308	NCB31CK-104X	CC	0.1μF 16V B
C2309	X-E524U1101D	CE	100μF 10V
C2310	NCB31CK-104X	CC	0.1μF 16V B
C2315	NCB31CK-104X	CC	0.1μF 16V B

△ Symbol.No.	Part No.	Part Name	Description
CAPACITORS			
C2601	X-E524U2470D	CE	47μF 16V
C2602	X-E524U2470D	CE	47μF 16V
C2605	NDC31HJ-820X	CC	82pF 50V CH
C2608	NCB31CK-104X	CC	0.1μF 16V B
C2609	NCB31HK-102X	CC	0.001μF 50V B
C2610	NCB31HK-102X	CC	0.001μF 50V B
C2611	X-E524U2100D	CE	10μF 16V
C2612	X-E524U2100D	CE	10μF 16V
C2613	NDC31HJ-470X	CC	47pF 50V CH
C2614	NCB31CK-104X	CC	0.1μF 16V B
C2615	NDC31HJ-390X	CC	39pF 50V CH
C2616	NDC31HJ-560X	CC	56pF 50V CH
C2617	NDC31HJ-151X	CC	150pF 50V CH
C2618	X-E62FU0151M	CE	150μF 6.3V
C2619	NDC31HJ-151X	CC	150pF 50V CH
C2620	X-E524U5010D	CE	1μF 50V
C2621	NDC31HJ-151X	CC	150pF 50V CH
C2622	NDC31HJ-151X	CC	150pF 50V CH
C2623	NDC31HJ-330X	CC	33pF 50V CH
C2625	NCB31CK-104X	CC	0.1μF 16V B
C2626	NDC31HJ-680X	CC	68pF 50V CH
C2627	NDC31HJ-221X	CC	220pF 50V CH
C2629	NDC31HJ-561X	CC	560pF 50V CH
C2631	NDC31HJ-330X	CC	33pF 50V CH
C2633	NDC31HJ-470X	CC	47pF 50V CH
C2634	NDC31HJ-101X	CC	100pF 50V CH
C2635	X-E524U2470D	CE	47μF 16V
C2636	NDC31HJ-820X	CC	82pF 50V CH
C2637	NDC31HJ-560X	CC	56pF 50V CH
C2639	NDC31HJ-221X	CC	220pF 50V CH
C2640	NCB31HK-472X	CC	0.0047μF 50V B
C2641	NDC31HJ-330X	CC	33pF 50V CH
C2642	NDC31HJ-220X	CC	22pF 50V CH
C2643	NDC31HJ-471X	CC	470pF 50V CH
C2644	NDC31HJ-180X	CC	18pF 50V CH
C2645	NDC31HJ-151X	CC	150pF 50V CH
C2646	NDC31HJ-221X	CC	220pF 50V CH
C2647	NDC31HJ-470X	CC	47pF 50V CH
C2648	NCB31CK-104X	CC	0.1μF 16V B
C2649	NCB31CK-104X	CC	0.1μF 16V B
C2650	NCB31CK-104X	CC	0.1μF 16V B
C2651	NCB31CK-104X	CC	0.1μF 16V B
C2652	X-E524U0470D	CE	47μF 6.3V
C2653	NCB31CK-104X	CC	0.1μF 16V B
C2654	X-E524U0470D	CE	47μF 6.3V
C2655	X-E524U0470D	CE	47μF 6.3V
C2656	NCB31CK-104X	CC	0.1μF 16V B
C2658	NCB31CK-104X	CC	0.1μF 16V B
C2659	NCB31CK-104X	CC	0.1μF 16V B
C4001	NCB31EZ-104X	CC	0.1μF 25V F
C4002	NCB31EZ-104X	CC	0.1μF 25V F
C4003	NCB31EZ-104X	CC	0.1μF 25V F
C4004	NCB31EZ-104X	CC	0.1μF 25V F
C4005	NCB31EZ-104X	CC	0.1μF 25V F
C4006	NCB31EZ-104X	CC	0.1μF 25V F
C4007	NCB31EZ-104X	CC	0.1μF 25V F
C4008	NCB31EZ-104X	CC	0.1μF 25V F
C4009	NCB31EZ-104X	CC	0.1μF 25V F
C4010	NCB31EZ-104X	CC	0.1μF 25V F
C4011	NCB31EZ-104X	CC	0.1μF 25V F
C4012	X-CS0PCH430C	CC	3pF 50V CH
C4013	X-CS0PCH430C	CC	3pF 50V CH
C4014	NCB31EZ-104X	CC	0.1μF 25V F
C4015	NCB31EZ-104X	CC	0.1μF 25V F
C4016	NCB31EZ-104X	CC	0.1μF 25V F
C4017	X-E62FU0151M	CE	150μF 6.3V
C4018	NCB31EZ-104X	CC	0.1μF 25V F
C4019	NCB31EZ-104X	CC	0.1μF 25V F
C4020	X-E62FU0151M	CE	150μF 6.3V
C4022	NCB31EZ-104X	CC	0.1μF 25V F
C4023	X-E62FU0151M	CE	150μF 6.3V
C4024	NCB31EZ-104X	CC	0.1μF 25V F
C4025	X-E524U0470D	CE	47μF 6.3V
C4026	NCB31EZ-104X	CC	0.1μF 25V F
C4027	NCB31EZ-104X	CC	0.1μF 25V F
C4028	NCB31EZ-104X	CC	0.1μF 25V F
C4029	X-E524U0470D	CE	47μF 6.3V
C4030	NCB31EZ-104X	CC	0.1μF 25V F
C4031	NCB31EZ-104X	CC	0.1μF 25V F
C4032	NCB31EZ-104X	CC	0.1μF 25V F
C4033	NCB31EZ-104X	CC	0.1μF 25V F

△ Symbol.No.	Part No.	Part Name	Description
CAPACITORS			
C4034	NCB31EZ-104X	CC	0.1μF 25V F
C4035	NCB31EZ-104X	CC	0.1μF 25V F
C4036	NCB31EZ-104X	CC	0.1μF 25V F
C4037	NCB31EZ-104X	CC	0.1μF 25V F
C4038	NCB31EZ-104X	CC	0.1μF 25V F
C4039	NCB31EZ-104X	CC	0.1μF 25V F
C4040	NCB31EZ-104X	CC	0.1μF 25V F
C4041	X-E524U1101D	CE	100μF 10V
C4043	X-E524U1101D	CE	100μF 10V
C4044	NCB31EZ-104X	CC	0.1μF 25V F
C4045	X-E524U1101D	CE	100μF 10V
C8502	NDC31HJ-271X	CC	270pF 50V CH
C8503	X-E524U2100D	CE	10μF 16V
C8504	NDC31HJ-271X	CC	270pF 50V CH
C8505	NDC31HJ-271X	CC	270pF 50V CH
C8506	NCB31EZ-104X	CC	0.1μF 25V F
C8508	NDC31HJ-220X	CC	22pF 50V CH
C8509	NDC31HJ-220X	CC	22pF 50V CH
C8510	NDC31HJ-220X	CC	22pF 50V CH
C8512	NDC31HJ-331X	CC	330pF 50V CH
C8513	NDC31HJ-331X	CC	330pF 50V CH
C8514	NDC31HJ-331X	CC	330pF 50V CH
C8518	NCB21CK-105X	CC	1μF 16V B
C8520	NCB31EZ-104X	CC	0.1μF 25V F
C8523	X-E524U1101D	CE	100μF 10V
C8524	NCB31EZ-104X	CC	0.1μF 25V F
C8525	X-E62FU1121M	CE	120μF 10V
C8526	X-E62FU1121M	CE	120μF 10V
C8529	NCF21CZ-225X	CC	2.2μF 16V F
C8530	NCF21CZ-225X	CC	2.2μF 16V F
C8534	X-E524U1101D	CE	100μF 10V
C8535	NCB31EZ-104X	CC	0.1μF 25V F
C8536	X-E524U0220D	CE	22μF 6.3V
C8537	X-E524U0220D	CE	22μF 6.3V
C8538	NCB31EZ-104X	CC	0.1μF 25V F

DIODES

D1001	X-DDRL41480	SILICON	MCL4148
D2601	X-DDARDS1210	SILICON	KDS121RTK
D2602	X-DDARDS1200	SILICON	KDS120RTK
D8504	X-DD5R002260	SILICON	1SS226(TE85L)
D8505	X-DD5R002260	SILICON	1SS226(TE85L)
D8506	X-DD5R002260	SILICON	1SS226(TE85L)

ICS

IC1001	X-ICQF067050	IC	ZR36705
IC1006	X-I5HJ004BF0	IC	S-24C04BFJ-TB
IC2001	X-I53F086610	IC	LC78661W
IC2002	X-I59J0258B3	IC	MSM5416258B-30
IC2301	X-I03F065600	IC	LA6560
IC2601	X-I07F04066F	IC	BU4066BCF
IC2602	X-I03FR97020	IC	LA9702WVL
IC4001	X-ICQF067320	IC	ZR36732
IC4002	X-I59J0160FB	IC	MSM56V16160F-8
IC4005	X-ICMJ0800A7	IC	SST39VF800A-70-4C-EK
IC4006	X-I0GF9XZ010	IC	PQ070XZ01ZP
IC8503	X-I17F017480	IC	PCM1748E
IC8504	X-I5CF040520	IC	SN74LV4052APW

TRANSISTORS

Q2301	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2302	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q2303	X-TNAAB05003	COMPOUND	KRC1025RRTK
Q2304	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q2601	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2603	X-T67J1036K0	SILICON	2SA1036KT146
Q2604	X-T67J1036K0	SILICON	2SA1036KT146
Q2605	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q2606	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2607	X-T27T030180	FET	2SK3018
Q2608	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2609	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2610	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2611	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q2612	X-T27T030180	FET	2SK3018
Q2613	X-T27T030180	FET	2SK3018

△ Symbol.No.	Part No.	Part Name	Description
TRANSISTORS			
Q2614	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2615	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q2616	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q8502	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q8503	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q8504	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q8506	X-TS5M000037	COMPOUND	HN1C03F_B(TE85L)

COILS

L1001	X-02167F2R2J	COIL	2.2μH
L8502	X-0216S71R8J	COIL	1.8μH
L8503	X-0216S71R8J	COIL	1.8μH
L8504	X-0216S71R8J	COIL	1.8μH
L8505	X-02167F150J	COIL	15μH
L8507	X-02AHB9A972	CORE,FERRITE	W5T29X7.5X19

CONNECTORS

CP2301	X-069EV83020	CONNECTOR PCB SIDE	00_6232_008_102
CP2302	X-069S250639	CONNECTOR PCB SIDE	A2001WR2-5P
CP2601	X-069EYOT040	CONNECTOR PCB SIDE	08_6210_024_340_800
CP8502	X-069J710029	CONNECTOR PCB SIDE	IMS-A-9604S-18Z14

OTHERS

B1001	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B1002	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2001	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2002	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2003	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2601	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2602	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2604	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2605	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B2606	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B4001	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B4002	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B4003	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B4004	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B8501	X-024HC31022	CORE,BEADS	FCM2012H-102T04
B8502	X-024HC31022	CORE,BEADS	FCM2012H-102T04
CD8501	X-06CU2D3001	CORD CONNECTOR	CU2D3001
CD8502	X-06CU262501	CORD CONNECTOR	CU262501
X1001	X-100CT01210	CRYSTAL	HC-49/U
X2001	X-100CT01604	CRYSTAL	HC-49/U-S
X4001	X-100WT02706	CRYSTAL	HC-49/U-S

AV PCB ASS'Y

△ Symbol.No.	Part No.	Part Name	Description
PCB250	X-A5C2042250	AV PCB ASS'Y	TMB543A

RESISTORS

R001	NRSA02J-750X	MG R	75Ω 1/10W
R003	NRSA02J-101X	MG R	100Ω 1/10W
R004	NRSA02J-101X	MG R	100Ω 1/10W
R005	NRSA02J-153X	MG R	15KΩ 1/10W
R006	NRSA02J-124X	MG R	120KΩ 1/10W
R101	NRSA02J-103X	MG R	10KΩ 1/10W
R103	NRSA02J-103X	MG R	10KΩ 1/10W
R109	NRSA02J-472X	MG R	4.7KΩ 1/10W
R110	NRSA02J-472X	MG R	4.7KΩ 1/10W
R114	NRSA02J-472X	MG R	4.7KΩ 1/10W
R115	NRSA02J-472X	MG R	4.7KΩ 1/10W
R119	NRSA02J-103X	MG R	10KΩ 1/10W
R120	NRSA02J-472X	MG R	4.7KΩ 1/10W
R122	NRSA02J-103X	MG R	10KΩ 1/10W
R123	NRSA02J-103X	MG R	10KΩ 1/10W

△ Symbol.No. Part No. Part Name Description

RESISTORS

R125	NRSA02J-332X	MG R	3.3KΩ	1/10W
R126	NRSA02J-472X	MG R	4.7KΩ	1/10W
R129	NRSA02J-103X	MG R	10KΩ	1/10W
R130	NRSA02J-472X	MG R	4.7KΩ	1/10W
R132	NRSA02J-103X	MG R	10KΩ	1/10W
R133	NRSA02J-821X	MG R	820Ω	1/10W
R134	NRSA02J-102X	MG R	1KΩ	1/10W
R135	NRSA02J-821X	MG R	820Ω	1/10W
R136	NRSA02J-102X	MG R	1KΩ	1/10W
R138	NRSA02J-152X	MG R	1.5KΩ	1/10W
R140	NRSA02J-101X	MG R	100Ω	1/10W
R141	NRSA02J-472X	MG R	4.7KΩ	1/10W
R142	NRSA02J-472X	MG R	4.7KΩ	1/10W
R143	NRSA02J-101X	MG R	100Ω	1/10W
R144	NRSA02J-472X	MG R	4.7KΩ	1/10W
R145	NRSA02J-472X	MG R	4.7KΩ	1/10W
R147	NRSA02J-101X	MG R	100Ω	1/10W
R148	NRSA02J-102X	MG R	1KΩ	1/10W
R149	NRSA02J-102X	MG R	1KΩ	1/10W
R157	NRSA02J-102X	MG R	1KΩ	1/10W
R159	NRSA02J-333X	MG R	33KΩ	1/10W
R160	NRSA02J-222X	MG R	2.2KΩ	1/10W
R161	QRE141J-103Y	RC	10KΩ	1/4W
R162	NRSA02J-153X	MG R	15KΩ	1/10W
R174	QRE141J-101Y	RC	100Ω	1/4W
R177	NRSA02J-683X	MG R	68KΩ	1/10W
R178	NRSA02J-472X	MG R	4.7KΩ	1/10W
R190	QRE141J-472Y	RC	4.7KΩ	1/4W
R202	NRSA02J-332X	MG R	3.3KΩ	1/10W
R203	NRSA02J-391X	MG R	390Ω	1/10W
R204	NRSA02J-332X	MG R	3.3KΩ	1/10W
R205	NRSA02J-103X	MG R	10KΩ	1/10W
R208	NRSA02J-331X	MG R	330Ω	1/10W
R210	NRSA02J-102X	MG R	1KΩ	1/10W
R211	NRSA02J-222X	MG R	2.2KΩ	1/10W
R212	NRSA02J-472X	MG R	4.7KΩ	1/10W
R213	NRSA02J-682X	MG R	6.8KΩ	1/10W
R214	NRSA02J-222X	MG R	2.2KΩ	1/10W
R215	QRE141J-122Y	RC	1.2KΩ	1/4W
R216	QRE141J-221Y	RC	220Ω	1/4W
R217	NRSA02J-102X	MG R	1KΩ	1/10W
R218	NRSA02J-681X	MG R	680Ω	1/10W
R219	NRSA02J-820X	MG R	82Ω	1/10W
R220	NRSA02J-101X	MG R	100Ω	1/10W
R221	QRE121J-221Y	RC	220Ω	1/2W
R222	NRSA02J-471X	MG R	470Ω	1/10W
R226	NRSA02J-561X	MG R	560Ω	1/10W
R227	NRSA02J-330X	MG R	33Ω	1/10W
R230	NRSA02J-124X	MG R	120KΩ	1/10W
R231	QRE141J-682Y	RC	6.8KΩ	1/4W
R232	X-R00104154J	RC	150KΩ	1/4W
R301	NRSA02J-822X	MG R	8.2KΩ	1/10W
R302	NRSA02J-683X	MG R	68KΩ	1/10W
R303	NRSA02J-822X	MG R	8.2KΩ	1/10W
R304	NRSA02J-223X	MG R	22KΩ	1/10W
R306	NRSA02J-223X	MG R	22KΩ	1/10W
R308	NRSA02J-472X	MG R	4.7KΩ	1/10W
R309	NRSA02J-472X	MG R	4.7KΩ	1/10W
R310	NRSA02J-182X	MG R	1.8KΩ	1/10W
R311	NRSA02J-104X	MG R	100KΩ	1/10W
R312	NRSA02J-182X	MG R	1.8KΩ	1/10W
R313	NRSA02J-391X	MG R	390Ω	1/10W
R314	NRSA02J-101X	MG R	100Ω	1/10W
R315	NRSA02J-101X	MG R	100Ω	1/10W
R318	QRE141J-101Y	RC	100Ω	1/4W
R319	QRE141J-101Y	RC	100Ω	1/4W
R320	NRSA02J-104X	MG R	100KΩ	1/10W
R323	NRSA02J-473X	MG R	47KΩ	1/10W
R325	NRSA02J-391X	MG R	390Ω	1/10W
R326	NRSA02J-101X	MG R	100Ω	1/10W
R337	QRE121J-121Y	RC	120Ω	1/2W
R342	QRE121J-121Y	RC	120Ω	1/2W
R346	NRSA02J-683X	MG R	68KΩ	1/10W
△ R401	X-R002T2331J	RC	330Ω	1/2W
△ R402	X-R3X28A271J	R,METAL OXIDE	270Ω	2W
R404	QRE121J-563Y	RC	56KΩ	1/2W
R405	QRE121J-563Y	RC	56KΩ	1/2W
R406	QRE141J-473Y	RC	47KΩ	1/4W
R407	QRE121J-102Y	RC	1KΩ	1/2W
△ R408	X-R3X28AR47J	R,METAL OXIDE	0.47Ω	2W
R409	QRE141J-223Y	RC	22KΩ	1/4W

△ Symbol.No. Part No. Part Name Description

RESISTORS

R410	QRE141J-562Y	RC	5.6KΩ	1/4W
R411	X-R4X5T6103F	R,METAL	10KΩ	1/6W
R412	NRSA02J-822X	MG R	8.2KΩ	1/10W
R413	X-R4X5T6273F	R,METAL	27KΩ	1/6W
R414	X-R4X5T6821F	R,METAL	820Ω	1/6W
R415	QRE121J-1R8Y	RC	1.8Ω	1/2W
R416	X-R4X5T6473F	R,METAL	47KΩ	1/6W
R417	QRE121J-391Y	RC	390Ω	1/2W
△ R418	QRE121J-1R5Y	RC	1.5Ω	1/2W
R419	QRE121J-391Y	RC	390Ω	1/2W
R420	NRSA02J-222X	MG R	2.2KΩ	1/10W
R421	QRE121J-152Y	RC	1.5KΩ	1/2W
R423	QRE141J-123Y	RC	12KΩ	1/4W
R424	QRE141J-122Y	RC	1.2KΩ	1/4W
△ R425	X-R002T2331J	RC	330Ω	1/2W
R428	NRSA02J-103X	MG R	10KΩ	1/10W
R430	QRE121J-562Y	RC	5.6KΩ	1/2W
R431	NRSA02J-103X	MG R	10KΩ	1/10W
△ R442	X-R801R7223F	RC	22KΩ	1/10W
△ R444	X-R801R7562F	RC	5.6KΩ	1/10W
R445	QRE141J-153Y	RC	15KΩ	1/4W
△ R447	X-R65582680J	R,FUSE	68Ω	1/2W
△ R448	X-R3X181102J	R,METAL OXIDE	1KΩ	1W
△ R450	X-R6558A3R9J	R,FUSE	3.9Ω	2W
R453	QRE121J-823Y	RC	82KΩ	1/2W
R456	QRE121J-471Y	RC	470Ω	1/2W
R460	QRE141J-101Y	RC	100Ω	1/4W
R463	QRE121J-471Y	RC	470Ω	1/2W
R464	QRE121J-471Y	RC	470Ω	1/2W
R490	QRE141J-563Y	RC	56KΩ	1/4W
R601	QRE141J-221Y	RC	220Ω	1/4W
R602	NRSA02J-221X	MG R	220Ω	1/10W
R604	NRSA02J-560X	MG R	56Ω	1/10W
R605	NRSA02J-682X	MG R	6.8KΩ	1/10W
R607	NRSA02J-101X	MG R	100Ω	1/10W
R608	NRSA02J-101X	MG R	100Ω	1/10W
R609	NRSA02J-101X	MG R	100Ω	1/10W
R611	NRSA02J-184X	MG R	180KΩ	1/10W
R612	NRSA02J-272X	MG R	2.7KΩ	1/10W
R613	NRSA02J-272X	MG R	2.7KΩ	1/10W
R614	NRSA02J-272X	MG R	2.7KΩ	1/10W
R618	NRSA02J-102X	MG R	1KΩ	1/10W
R619	NRSA02J-332X	MG R	3.3KΩ	1/10W
R620	NRSA02J-471X	MG R	470Ω	1/10W
R623	QRE141J-222Y	RC	2.2KΩ	1/4W
R624	QRE141J-271Y	RC	270Ω	1/4W
R625	NRSA02J-561X	MG R	560Ω	1/10W
R626	NRSA02J-102X	MG R	1KΩ	1/10W
R627	NRSA02J-124X	MG R	120KΩ	1/10W
R629	QRE141J-101Y	RC	100Ω	1/4W
R630	QRE141J-472Y	RC	4.7KΩ	1/4W
R631	QRE141J-101Y	RC	100Ω	1/4W
R632	QRE141J-103Y	RC	10KΩ	1/4W
R634	NRSA02J-154X	MG R	150KΩ	1/10W
R635	NRSA02J-331X	MG R	330Ω	1/10W
R637	NRSA02J-103X	MG R	10KΩ	1/10W
R638	NRSA02J-222X	MG R	2.2KΩ	1/10W
R639	NRSA02J-333X	MG R	33KΩ	1/10W
R640	NRSA02J-185X	MG R	1.8MΩ	1/10W
R643	NRSA02J-102X	MG R	1KΩ	1/10W
R908	QRE141J-471Y	RC	470Ω	1/4W
R909	QRE141J-471Y	RC	470Ω	1/4W
R910	NRSA02J-224X	MG R	220KΩ	1/10W
R911	NRSA02J-101X	MG R	100Ω	1/10W
R912	NRSA02J-101X	MG R	100Ω	1/10W
R913	NRSA02J-275X	MG R	2.7MΩ	1/10W
R1501	NRSA02J-331X	MG R	330Ω	1/10W
R1502	NRSA02J-682X	MG R	6.8KΩ	1/10W
R1503	NRSA02J-332X	MG R	3.3KΩ	1/10W
R1504	NRSA02J-102X	MG R	1KΩ	1/10W
R1505	NRSA02J-101X	MG R	100Ω	1/10W
R1506	NRSA02J-821X	MG R	820Ω	1/10W
R1507	NRSA02J-102X	MG R	1KΩ	1/10W
R1508	NRSA02J-122X	MG R	1.2KΩ	1/10W
R1509	NRSA02J-561X	MG R	560Ω	1/10W
R1510	NRSA02J-563X	MG R	56KΩ	1/10W
R1511	NRSA02J-273X	MG R	27KΩ	1/10W
R1512	NRSA02J-331X	MG R	330Ω	1/10W
R1513	NRSA02J-102X	MG R	1KΩ	1/10W
R3000	NRSA02J-101X	MG R	100Ω	1/10W
R3001	NRSA02J-101X	MG R	100Ω	1/10W

△ Symbol.No. Part No. Part Name Description

RESISTORS

R3002	NRSA02J-103X	MG R	10KΩ	1/10W
R3003	QRE141J-102Y	RC	1KΩ	1/4W
R3004	NRSA02J-331X	MG R	330Ω	1/10W
R3005	QRE121J-101Y	RC	100Ω	1/2W
R3006	NRSA02J-561X	MG R	560Ω	1/10W
R3007	NRSA02J-101X	MG R	100Ω	1/10W
R3008	NRSA02J-101X	MG R	100Ω	1/10W
R3009	NRSA02J-391X	MG R	390Ω	1/10W
R3011	X-R00104822J	RC	8.2KΩ	1/4W
R3012	QRE141J-101Y	RC	100Ω	1/4W
R3013	NRSA02J-820X	MG R	82Ω	1/10W
R3014	X-R801R7821F	RC	820Ω	1/10W
R3015	X-R801R7152F	RC	1.5KΩ	1/10W
R4201	NRSA02J-103X	MG R	10KΩ	1/10W
R4202	NRSA02J-103X	MG R	10KΩ	1/10W
R4203	NRSA02J-471X	MG R	470Ω	1/10W
R4205	QRE141J-100Y	RC	10Ω	1/4W
R4206	NRSA02J-471X	MG R	470Ω	1/10W
R4208	NRSA02J-103X	MG R	10KΩ	1/10W
R4209	NRSA02J-100X	MG R	10Ω	1/10W
R4210	NRSA02J-100X	MG R	10Ω	1/10W
R4211	NRSA02J-104X	MG R	100KΩ	1/10W
R4212	NRSA02J-104X	MG R	100KΩ	1/10W
R4213	NRSA02J-103X	MG R	10KΩ	1/10W
R4214	QRE141J-103Y	RC	10KΩ	1/4W
R4216	NRSA02J-121X	MG R	120Ω	1/10W
R4218	NRSA02J-102X	MG R	1KΩ	1/10W
R4219	NRSA02J-102X	MG R	1KΩ	1/10W
R4220	QRE141J-101Y	RC	100Ω	1/4W
R4221	NRSA02J-560X	MG R	56Ω	1/10W
R4223	NRSA02J-103X	MG R	10KΩ	1/10W
R4224	NRSA02J-103X	MG R	10KΩ	1/10W
R4225	NRSA02J-222X	MG R	2.2KΩ	1/10W
R4226	NRSA02J-222X	MG R	2.2KΩ	1/10W
R4227	NRSA02J-103X	MG R	10KΩ	1/10W
R4228	NRSA02J-123X	MG R	12KΩ	1/10W
R4229	NRSA02J-123X	MG R	12KΩ	1/10W
R4230	NRSA02J-102X	MG R	1KΩ	1/10W
R4231	NRSA02J-822X	MG R	8.2KΩ	1/10W
R4232	NRSA02J-822X	MG R	8.2KΩ	1/10W
R4233	NRSA02J-102X	MG R	1KΩ	1/10W
R4234	NRSA02J-471X	MG R	470Ω	1/10W
R4235	NRSA02J-471X	MG R	470Ω	1/10W
R4236	NRSA02J-103X	MG R	10KΩ	1/10W
R4237	NRSA02J-103X	MG R	10KΩ	1/10W
R4238	NRSA02J-332X	MG R	3.3KΩ	1/10W
R4239	NRSA02J-102X	MG R	1KΩ	1/10W
R4240	NRSA02J-102X	MG R	1KΩ	1/10W
R4241	NRSA02J-121X	MG R	120Ω	1/10W
R4242	NRSA02J-121X	MG R	120Ω	1/10W
R4243	NRSA02J-103X	MG R	10KΩ	1/10W
R4246	NRSA02J-223X	MG R	22KΩ	1/10W
R4247	NRSA02J-101X	MG R	100Ω	1/10W
R4248	NRSA02J-123X	MG R	12KΩ	1/10W
R4249	QRE121J-331Y	RC	330Ω	1/2W
R4250	QRE141J-680Y	RC	68Ω	1/4W
R4251	QRE141J-101Y	RC	100Ω	1/4W
R4252	QRE141J-101Y	RC	100Ω	1/4W
R4253	QRE141J-101Y	RC	100Ω	1/4W
R4254	NRSA02J-101X	MG R	100Ω	1/10W
R4255	NRSA02J-101X	MG R	100Ω	1/10W
R4256	NRSA02J-101X	MG R	100Ω	1/10W
R4257	QRE141J-101Y	RC	100Ω	1/4W
R4259	QRE141J-101Y	RC	100Ω	1/4W
R4262	QRE141J-101Y	RC	100Ω	1/4W
R4263	NRSA02J-823X	MG R	82KΩ	1/10W
R4264	NRSA02J-823X	MG R	82KΩ	1/10W
R4265	NRSA02J-823X	MG R	82KΩ	1/10W
R4266	NRSA02J-104X	MG R	100KΩ	1/10W
R4267	NRSA02J-823X	MG R	82KΩ	1/10W
R4268	NRSA02J-823X	MG R	82KΩ	1/10W
R4269	NRSA02J-823X	MG R	82KΩ	1/10W
R4270	NRSA02J-104X	MG R	100KΩ	1/10W
R4271	QRE141J-101Y	RC	100Ω	1/4W
R4274	NRSA02J-102X	MG R	1KΩ	1/10W
R4275	NRSA02J-102X	MG R	1KΩ	1/10W
R4276	X-R00204750J	RC	75Ω	1/4W
R4278	NRSA02J-101X	MG R	100Ω	1/10W
R4279	NRSA02J-101X	MG R	100Ω	1/10W
R4280	NRSA02J-750X	MG R	75Ω	1/10W
R4281	NRSA02J-102X	MG R	1KΩ	1/10W
R4282	NRSA02J-102X	MG R	1KΩ	1/10W

△ Symbol.No. Part No. Part Name Description

VARIABLE RESISTORS

VR402 X-V1K6313BTE VOLUME,SEMI FIXED NVG6TLTAB102

CAPACITORS

C001	X-P232W0223J	CMPL	0.022μF	50V	MMTS
C002	QETN0JM-477Z	CE	470μF	6.3V	
C003	NDC21HJ-101X	CC	100pF	50V	CH
C004	NDC21HJ-101X	CC	100pF	50V	CH
C005	QEKJ1HM-335Z	CE	3.3μF	50V	
C006	QEKJ0JM-476Z	CE	47μF	6.3V	
C101	QEKJ0JM-336Z	CE	33μF	6.3V	
C102	NCB21HK-103X	CC	0.01μF	50V	B
C103	QEKJ0JM-227Z	CE	220μF	6.3V	
C104	NCB21EK-104X	CC	0.1μF	25V	B
C106	NCB21EK-104X	CC	0.1μF	25V	B
C107	NCB21EK-104X	CC	0.1μF	25V	B
C108	NCB21EK-104X	CC	0.1μF	25V	B
C109	NCB21HK-223X	CC	0.022μF	50V	B
C111	NDC21HJ-271X	CC	270pF	50V	CH
C117	NCB21HK-103X	CC	0.01μF	50V	B
C119	QEKJ0JM-107Z	CE	100μF	6.3V	
C123	NCB21HK-122X	CC	0.0012μF	50V	B
C124	NCF21HZ-104X	CC	0.1μF	50V	F
C127	NCB21HK-822X	CC	0.0082μF	50V	B
C128	NCB21HK-103X	CC	0.01μF	50V	B
C130	NCF21HZ-104X	CC	0.1μF	50V	F
C131	NCF21HZ-104X	CC	0.1μF	50V	F
C132	NCF21HZ-104X	CC	0.1μF	50V	F
C135	NCF21HZ-104X	CC	0.1μF	50V	F
C201	NCB21HK-103X	CC	0.01μF	50V	B
C202	NCB21HK-103X	CC	0.01μF	50V	B
C203	NCB21HK-222X	CC	0.0022μF	50V	B
C204	NCB21HK-103X	CC	0.01μF	50V	B
C205	QETN1AM-107Z	CE	100μF	10V	
C206	NDC21HJ-391X	CC	390pF	50V	CH
C207	QEKJ1CM-106Z	CE	10μF	16V	
C208	NCB21HK-103X	CC	0.01μF	50V	B
C209	QEKJ1HM-224Z	CE	0.22μF	50V	
C210	QETN1CM-107Z	CE	100μF	16V	
C213	QEKJ1CM-106Z	CE	10μF	16V	
C215	NDC21HJ-330X	CC	33pF	50V	CH
C216	X-CS0RCH450C	CC	5pF	50V	CH
C217	X-CS0RCH450C	CC	5pF	50V	CH
C218	NCB21HK-103X	CC	0.01μF	50V	B
C219	QEKJ1CM-106Z	CE	10μF	16V	
C220	NCB21HK-103X	CC	0.01μF	50V	B
C221	QEKJ1HM-474Z	CE	0.47μF	50V	
C222	NCB21HK-103X	CC	0.01μF	50V	B
C224	NDC21HJ-150X	CC	15pF	50V	CH
C226	NCB21CK-105X	CC	1μF	16V	B
C227	QETN1CM-476Z	CE	47μF	16V	
C301	QETN1CM-107Z	CE	100μF	16V	
C302	QEKJ1CM-106Z	CE	10μF	16V	
C303	QEKJ1CM-476Z	CE	47μF	16V	
C304	NCB21EK-104X	CC	0.1μF	25V	B
C305	QETN1CM-107Z	CE	100μF	16V	
C307	NCB21HK-333X	CC	0.033μF	50V	B
C308	QETN1HM-106Z	CE	10μF	50V	
C309	QEKJ1CM-106Z	CE	10μF	16V	
C311	NCB21HK-333X	CC	0.033μF	50V	B
C312	QETN1EM-336Z	CE	33μF	25V	
C313	X-E02LT2102M	CE	1000μF	16V	
C314	NCB21HK-333X	CC	0.033μF	50V	B
C315	NCB21HK-223X	CC	0.022μF	50V	B
C316	NCB21HK-223X	CC	0.022μF	50V	B
C317	NCB21CK-474X	CC	0.47μF	16V	B
C318	NCB21CK-474X	CC	0.47μF	16V	B
C319	QEKJ1CM-106Z	CE	10μF	16V	
C320	X-P232T0104J	CMPL	0.1μF	50V	MMTV
C321	NDC21HJ-101X	CC	100pF	50V	CH
C322	NCB21HK-102X	CC	0.001μF	50V	B
C323	NCB21EK-104X	CC	0.1μF	25V	B
C324	NDC21HJ-101X	CC	100pF	50V	CH
C325	QEKJ1CM-476Z	CE	47μF	16V	
C326	NCB21HK-223X	CC	0.022μF	50V	B
C327	QEKJ1CM-106Z	CE	10μF	16V	
C348	NCB21HK-333X	CC	0.033μF	50V	B
C349	NDC21HJ-471X	CC	470pF	50V	CH
C350	NDC21HJ-471X	CC	470pF	50V	CH
C351	NDC21HJ-471X	CC	470pF	50V	CH

△ Symbol.No.	Part No.	Part Name	Description
CAPACITORS			
C352	NDC21HJ-471X	CC	470pF 50V CH
C356	NDC21HJ-331X	CC	330pF 50V CH
C401	X-E5EZTD100M	CE	10μF 250V
C402	X-E02LT2471M	CE	470μF 16V
C403	X-E02LT2470M	CE	47μF 16V
C404	X-E5EZU5010M	CE	1μF 50V
C405	X-E5EZU5R47M	CE	0.47μF 50V
C406	X-E5EZU4101M	CE	100μF 35V
△ C407	X-E5EZF3222M	CE	2200μF 25V
C409	X-E5EZU4101M	CE	100μF 35V
C410	QEKJ1CM-106Z	CE	10μF 16V
C411	X-P235W1224J	CMP	0.22μF 100V MKT
C417	X-P235W1103J	CMP	0.01μF 100V MKT
C418	QETN1HM-226Z	CE	22μF 50V
△ C421	X-E5EZT4471M	CE	470μF 35V
C422	X-E5EZTD2R2M	CE	2.2μF 250V
C423	X-P4J7F394J	CMPP	0.39μF 250V PMS
△ C428	X-P4N8FJ123H	CMPP	0.012μF 1.25KV
C429	X-C0JTB05H3K	CC	0.0022μF 500V B
C430	X-C0JTB0513K	CC	0.001μF 500V B
△ C431	X-E0ELFD220M	CE	22μF 250V
C432	X-P235W1104J	CMP	0.1μF 100V MKT
△ C433	X-E02LU5220M	CE	22μF 50V
C435	NDC21HJ-561X	CC	560pF 50V CH
C439	X-C0JTSLS51J	CC	56pF 500V SL
C450	X-C03L0R713K	CC	0.001μF 2KV R
C602	QETN1CM-107Z	CE	100μF 16V
C603	NCB21EK-224X	CC	0.22μF 25V B
C604	NCF21HZ-104X	CC	0.1μF 50V F
C605	X-CS0RCH411D	CC	10pF 50V CH
C606	NCB21HK-222X	CC	0.0022μF 50V B
C607	QEKJ1HM-105Z	CE	1μF 50V
C608	QEKJ1HM-105Z	CE	1μF 50V
C609	QEKJ1HM-015Z	CE	0.1μF 50V
C610	NCB21HK-153X	CC	0.015μF 50V B
C612	NCB21HK-103X	CC	0.01μF 50V B
C613	NCF21HZ-104X	CC	0.1μF 50V F
C614	QETN0JM-477Z	CE	470μF 6.3V
C616	NCF21HZ-104X	CC	0.1μF 50V F
C617	NCB21EK-104X	CC	0.1μF 25V B
C618	QEKJ1HM-105Z	CE	1μF 50V
C619	NCB21EK-104X	CC	0.1μF 25V B
C620	QETN1AM-107Z	CE	100μF 10V
C621	X-P232T0474J	CMPL	0.47μF 50V MMTV
C622	NCB21EK-104X	CC	0.1μF 25V B
C624	NCB21EK-104X	CC	0.1μF 25V B
C625	QEKJ1HM-225Z	CE	2.2μF 50V
C626	NCB21EK-104X	CC	0.1μF 25V B
C629	NCB21HK-103X	CC	0.01μF 50V B
C630	QEKJ1AM-107Z	CE	100μF 10V
C631	NCB21EK-104X	CC	0.1μF 25V B
C632	NDC21HJ-121X	CC	120pF 50V CH
C634	QETN1CM-476Z	CE	47μF 16V
C635	NCB21EK-104X	CC	0.1μF 25V B
C636	NCB21HK-103X	CC	0.01μF 50V B
C639	X-E00NU2100M	CE	10μF 16V V
C641	QEKJ1CM-106Z	CE	10μF 16V
C642	NCF21EZ-104X	CC	0.1μF 25V F
C644	QCFB1HZ-105Y	CC	1μF 50V F
C645	X-E00NU42R2M	CE	2.2μF 35V V
C647	NCB21HK-473X	CC	0.047μF 50V B
C649	X-E0EL054R7M	CE	4.7μF 50V
C907	QEKJ1HM-475Z	CE	4.7μF 50V
C920	NCB21EK-104X	CC	0.1μF 25V B
C921	QEKJ1HM-475Z	CE	4.7μF 50V
C922	NCB21EK-104X	CC	0.1μF 25V B
C923	NCB21EK-104X	CC	0.1μF 25V B
C924	NCB21EK-104X	CC	0.1μF 25V B
C925	QEKJ1HM-475Z	CE	4.7μF 50V
C926	QEKJ1HM-475Z	CE	4.7μF 50V
C927	NDC21HJ-151X	CC	150pF 50V CH
C928	QEKJ1CM-106Z	CE	10μF 16V
C929	NCB21EK-104X	CC	0.1μF 25V B
C930	NDC21HJ-151X	CC	150pF 50V CH
C931	QEKJ0JM-107Z	CE	100μF 6.3V
C932	QEKJ1HM-334Z	CE	0.33μF 50V
C933	NCB21HK-473X	CC	0.047μF 50V B
C934	NCB21HK-223X	CC	0.022μF 50V B
C935	NCB21EK-104X	CC	0.1μF 25V B
C936	QEKJ1HM-335Z	CE	3.3μF 50V
C937	NCB21EK-104X	CC	0.1μF 25V B

△ Symbol.No.	Part No.	Part Name	Description
CAPACITORS			
C938	NCB21EK-104X	CC	0.1μF 25V B
C939	NCB21EK-104X	CC	0.1μF 25V B
C1501	NDC21HJ-560X	CC	56pF 50V CH
C1502	NCB21EK-104X	CC	0.1μF 25V B
C1504	NCB21HK-103X	CC	0.01μF 50V B
C1505	NCB21HK-103X	CC	0.01μF 50V B
C1506	NDC21HJ-270X	CC	27pF 50V CH
C1507	NCB21HK-103X	CC	0.01μF 50V B
C1508	NCB21HK-103X	CC	0.01μF 50V B
C1509	NCB21HK-103X	CC	0.01μF 50V B
C1510	NCB21HK-103X	CC	0.01μF 50V B
C1511	NCB21CK-474X	CC	0.47μF 16V B
C1512	NCB21HK-103X	CC	0.01μF 50V B
C1513	NDC21HJ-181X	CC	180pF 50V CH
C1514	NDC21HJ-560X	CC	56pF 50V CH
C1515	NDC21HJ-101X	CC	100pF 50V CH
C1516	QETN1CM-476Z	CE	47μF 16V
C1517	NCB21HK-103X	CC	0.01μF 50V B
C1518	QETN0JM-227Z	CE	220μF 6.3V
C1519	NCB21HK-103X	CC	0.01μF 50V B
C1520	NCB21EK-104X	CC	0.1μF 25V B
C1521	QETN1HM-335Z	CE	3.3μF 50V
C1523	NDC21HJ-390X	CC	39pF 50V CH
C1524	NDC21HJ-560X	CC	56pF 50V CH
C3003	NCF21HZ-104X	CC	0.1μF 50V F
C3005	NCF21HZ-104X	CC	0.1μF 50V F
C3007	NCF21HZ-104X	CC	0.1μF 50V F
C3009	NDC21HJ-471X	CC	470pF 50V CH
C3010	NDC21HJ-471X	CC	470pF 50V CH
C3011	QETN0JM-477Z	CE	470μF 6.3V
C3012	QETN1AM-477Z	CE	470μF 10V
C3013	QETN0JM-107Z	CE	100μF 6.3V
C3014	QETN0JM-477Z	CE	470μF 6.3V
C3015	X-E5EZT2471M	CE	470μF 16V
C3016	X-E5EZT2471M	CE	470μF 16V
C3018	X-E02LT2471M	CE	470μF 16V
C3019	QEKJ1CM-106Z	CE	10μF 16V
△ C3020	X-E5EZT0102M	CE	1000μF 6.3V
C3022	QETN1VM-226Z	CE	22μF 35V
C3024	NDC21HJ-101X	CC	100pF 50V CH
C3025	QETN0JM-477Z	CE	470μF 6.3V
C3026	X-CHGTCH4Q0K	CC	4.7pF 50V CH
C3028	QETN0JM-477Z	CE	470μF 6.3V
C4201	NCB21HK-471X	CC	470pF 50V B
C4202	NCB21HK-471X	CC	470pF 50V B
C4203	QEKJ1CM-107Z	CE	100μF 16V
C4204	QEKJ0JM-476Z	CE	47μF 6.3V
C4205	NCB21HK-223X	CC	0.022μF 50V B
C4206	QEKJ1HM-225Z	CE	2.2μF 50V
C4207	QEKJ1HM-225Z	CE	2.2μF 50V
C4208	QEKJ1CM-106Z	CE	10μF 16V
C4209	NDC21HJ-101X	CC	100pF 50V CH
C4210	NDC21HJ-821X	CC	820pF 50V CH
C4211	QEKJ1CM-106Z	CE	10μF 16V
C4212	NDC21HJ-821X	CC	820pF 50V CH
C4213	QEKJ1CM-106Z	CE	10μF 16V
C4214	QEKJ1AM-336Z	CE	33μF 10V
C4215	NCB21EK-104X	CC	0.1μF 25V B
C4216	NCB21EK-104X	CC	0.1μF 25V B
C4217	QEKJ1CM-107Z	CE	100μF 16V
C4219	QEKJ1HM-475Z	CE	4.7μF 50V
C4220	NCB21HK-152X	CC	0.0015μF 50V B
C4222	NCB21HK-152X	CC	0.0015μF 50V B
C4223	NCB21HK-103X	CC	0.01μF 50V B
C4224	NDC21HJ-101X	CC	100pF 50V CH
C4225	NDC21HJ-101X	CC	100pF 50V CH
C4226	NDC21HJ-101X	CC	100pF 50V CH
C4227	QEKJ1CM-226Z	CE	22μF 16V
C4228	QEKJ1HM-225Z	CE	2.2μF 50V
C4229	QEKJ1HM-225Z	CE	2.2μF 50V
C4230	QEKJ1HM-225Z	CE	2.2μF 50V
C4231	QEKJ1CM-226Z	CE	22μF 16V
C4232	QEKJ1CM-226Z	CE	22μF 16V
C4233	NDC21HJ-221X	CC	220pF 50V CH
C4234	QEKJ1HM-475Z	CE	4.7μF 50V
C4237	NCB21HK-471X	CC	470pF 50V B
C4238	NCF21HZ-104X	CC	0.1μF 50V F
C4239	NCB21HK-471X	CC	470pF 50V B
C4240	X-E02LT0102M	CE	1000μF 6.3V
C4241	QETN1CM-107Z	CE	100μF 16V
C4242	QEKJ1HM-475Z	CE	4.7μF 50V

△ Symbol.No.	Part No.	Part Name	Description
CAPACITORS			
C4243	QEKJ1HM-475Z	CE	4.7μF 50V
C4244	QEKJ1HM-225Z	CE	2.2μF 50V
C4245	NCB21HK-222X	CC	0.0022μF 50V B
C4246	NCB21EK-104X	CC	0.1μF 25V B
C4247	NCB21HK-222X	CC	0.0022μF 50V B
C4249	NDC21HJ-101X	CC	100pF 50V CH
C4250	QEKJ1CM-106Z	CE	10μF 16V
C4251	QEKJ1CM-106Z	CE	10μF 16V
C4252	QEKJ1CM-106Z	CE	10μF 16V
C4253	QETN1HM-106Z	CE	10μF 50V
C4255	QEKJ1CM-107Z	CE	100μF 16V
C4256	QEKJ0JM-227Z	CE	220μF 6.3V
C4259	NCB21EK-104X	CC	0.1μF 25V B
C4261	QEKJ1HM-225Z	CE	2.2μF 50V
C4262	QEKJ1HM-225Z	CE	2.2μF 50V B
C4263	NCB21EK-104X	CC	0.1μF 25V B
C4264	QEKJ1HM-225Z	CE	2.2μF 50V
C4265	NDC21HJ-101X	CC	100pF 50V CH
C4267	QEKJ1HM-225Z	CE	2.2μF 50V
C4268	QEKJ1HM-225Z	CE	2.2μF 50V
C4269	QEKJ1HM-225Z	CE	2.2μF 50V
C4270	NCB21EK-104X	CC	0.1μF 25V B
C4271	NCB21HK-222X	CC	0.0022μF 50V B
C4272	NCB21HK-222X	CC	0.0022μF 50V B
C4274	NDC21HJ-471X	CC	470pF 50V CH
C4275	NDC21HJ-471X	CC	470pF 50V CH
C4276	X-E02LT5100M	CE	10μF 50V
C4277	X-E02LT5100M	CE	10μF 50V

DIODES			
D101	X-D1VT001330	SILICON	1SS133T-77
D104	X-D97U06R81B	ZENER	MTZJ6.8BT-77
D105	X-D1V0001330	SILICON	1SS133
D202	X-D1VT001330	SILICON	1SS133T-77
D401	X-D2WT011E10	SILICON	11E1-EIC
D403	X-D97U03301B	ZENER	MTZJ33BT-77
D404	X-D97U03301B	ZENER	MTZJ33BT-77
D405	X-D1VT001330	SILICON	1SS133T-77
D406	X-D1VT001330	SILICON	1SS133T-77
D408	X-D97U03301B	ZENER	MTZJ33BT-77
△ D409	X-D1VT001330	SILICON	1SS133T-77
D410	X-D97U06R81B	ZENER	MTZJ6.8BT-77
△ D411	X-D2WXN49370	SILICON	1N4937
△ D412	X-D2LTPG06J0	SILICON	RMPG06J-G3
△ D413	X-D2WXN49370	SILICON	1N4937
D414	X-D2WT011E10	SILICON	11E1-EIC
D415	X-D28TELS6N6	RECTIFIER	10ELSGN-TA1B2
D416	X-D97U05R11B	ZENER	MTZJ5.1BT-77
D601	X-D1VT001330	SILICON	1SS133T-77
D602	X-D1VT001330	SILICON	1SS133T-77
D603	X-D1VT001330	SILICON	1SS133T-77
D606	X-D97U06R81B	ZENER	MTZJ6.8BT-77
D607	X-D97U06R81B	ZENER	MTZJ6.8BT-77
D608	X-D97U06R81B	ZENER	MTZJ6.8BT-77
D612	X-D2WT11ES10	SILICON	11ES1-EIC
D613	X-D1VT001330	SILICON	1SS133T-77
D614	X-D1VT001330	SILICON	1SS133T-77
D615	X-D1VT001330	SILICON	1SS133T-77
D3000	X-D1VT001330	SILICON	1SS133T-77
D3002	X-D2WT011E10	SILICON	11E1-EIC
D3003	X-D97U01201B	ZENER	MTZJ12BT-77
D3004	X-D97U09R11B	ZENER	MTZJ9.1BT-77
D3005	X-D1VT001330	SILICON	1SS133T-77
D3006	X-D2WT011E10	SILICON	11E1-EIC
D3007	X-D97006R81B	ZENER	MTZJ6.8B
D4213	X-D1VT001330	SILICON	1SS133T-77

ICS			
IC101	X-I55D06070B	IC	OEC6070B
IC103	X-I9UF032450	IC	PST3245NR
IC199	X-A5C2041255	IC	S-24C08ADPA-01
IC301	X-I06F062420	IC	M62420FP
△ IC302	X-I0FSP75220	IC	AN7522
△ IC401	X-I03TD80400	IC	LA78040
IC601	X-I05DC12530	IC	TB1253N
IC602	X-I03F071510	IC	LA7151M-TLM
IC902	X-I01FF58290	IC	AN5829S
IC1501	X-I05FE90A45	IC	TC90A45F

ICS			
△ IC3000	X-I1KA98R050	IC	KIA78R05PI
△ IC3001	X-I1KA98R09A	IC	KIA78R09API
△ IC3002	X-I1KA98R050	IC	KIA78R05PI
△ IC3003	X-I1KA98R050	IC	KIA78R05PI
IC3004	X-I1KA98R050	IC	KIA78R05PI
IC4201	X-I0QF045800	IC	NJM4580M
IC4202	X-I5CF040530	IC	CD4053BNSR
IC4203	X-I0UD013110	IC	MM1311AD

TRANSISTORS			
Q103	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q104	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q105	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q109	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q202	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q203	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q204	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q205	X-T8AA03881S	SILICON	KTC3881S-RTK
Q301	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
△ Q401	X-TA3T016240	SILICON	2SA1624-AA
Q403	X-TNAAJ05003	COMPOUND	KRC111SRTK
Q404	X-TAATA12660	SILICON	KTA1266-AT(Y,GR)
△ Q405	X-TCAT03227Y	SILICON	KTC3227_YAT
△ Q406	X-TDUF024990	SILICON	2SD2499
Q601	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q603	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q608	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q609	X-TPAAB05001	COMPOUND	KRA102SRTK
Q1501	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q1502	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q1503	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q3000	X-TB3T011310	SILICON	2SB1131(S,T)-AE
Q3001	X-TNAA05003	COMPOUND	KRC102SRTK
Q3002	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
△ Q3003	X-TB30011430	SILICON	2SB1143(S,T,U)
Q3004	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q3005	X-TCAT03209Y	SILICON	KTC3209_YAT
Q4201	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4202	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q4203	X-TNAAD05001	COMPOUND	KRC104SRTK
Q4204	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4205	X-TPAAB05001	COMPOUND	KRA102SRTK
Q4206	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4207	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4208	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4209	X-TNAAC05002	COMPOUND	KRC103SRTK
Q4210	X-TPAA05001	COMPOUND	KRA101SRTK
Q4211	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4212	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4213	X-TNAAC05002	COMPOUND	KRC103SRTK
Q4214	X-TCAA3875SY	SILICON	KTC3875S_Y_RTK
Q4215	X-TAAA1504SY	SILICON	KTA1504S_Y_RTK
Q4217	X-TNAAD05001	COMPOUND	KRC104SRTK

COILS			
L001	X-02167F101J	COIL	100μH
L201	X-021LA6180K	COIL	18μH
L202	X-02167F101J	COIL	100μH
L203	X-02167F101J	COIL	100μH
L204	X-021LA6R22M	COIL	0.22μH
L205	X-021LA6120K	COIL	12μH
L207	X-021LA63R3K	COIL	3.3μH
L302	X-02167F101J	COIL	100μH
L303	X-02167F101J	COIL	100μH
L401	X-021679472K	COIL	4.7mH
△ L402	X-022100027A	COIL,LINEARITY	ELH5L4113
L602	X-02167F101J	COIL	100μH
L603	X-02167D221K	COIL	220μH
L605	X-10380R1501	DELAY EQ	380R1501
L606	X-021LA6101K	COIL	100μH
L902	X-02167F101J	COIL	100μH
L1501	X-02167F150J	COIL	15μH
L1502	X-02167F150J	COIL	15μH
L1503	X-021673821K	COIL	820μH
L1504	X-02167F151J	COIL	150μH
L4201	X-02167D472K	COIL	4.7mH
L4202	X-021673101K	COIL	100μH
L4203	X-02167F101J	COIL	100μH

△ Symbol.No.	Part No.	Part Name	Description
COILS			
L4204	X-02167F101J	COIL	100μH
L4205	X-02167F101J	COIL	100μH
TRANSFORMERS			
△ FB401	X-043220056F	TRANSFORMER,FLYBACK	3220056F
T401	X-045013003J	TRANS,HORIZONTAL DRIVE	ETH14Y47AY
JACKS			
△ J301	X-060J131015	HEADPHONE JACK	MSJ-2000
J4201	X-060J401082	RCA JACK	MSP-251V-05PBSN
J4202	X-060J411018	RCA JACK	MSP-213V1-432PBSN
J4203	X-060J431019	RCA JACK	MSP-213V2-432PBSN
J4204	X-060J421023	RCA JACK	MSP-281V3-A
J4205	X-060J401080	RCA JACK	MSP-281V1-B
J4206	X-060J401079	RCA JACK	MSP-281V4-B
SWITCHES			
SW117	X-0504101T34	TACT	EVQ21505R
SW118	X-0504101T34	TACT	EVQ21505R
SW119	X-0504101T34	TACT	EVQ21505R
SW120	X-0504101T34	TACT	EVQ21505R
CONNECTORS			
CP101	X-069X170379	CONNECTOR PCB SIDE	07JQ-ST
CP104	X-069J760029	CONNECTOR PCB SIDE	IMSA-9604S-06Z14
CP301	X-069W120029	CONNECTOR PCB SIDE	TID-X02P-M1
CP302	X-069W120029	CONNECTOR PCB SIDE	TID-X02P-M1
△ CP401	X-069S450089	CONNECTOR PCB SIDE	A1561WV2-A5P
CP402	X-067U006049	WIRE HOLDER	B2013H02-6P
CP8001	X-069S2D0629	CONNECTOR PCB SIDE	A2001WV2-13P
CP8002	X-069J710029	CONNECTOR PCB SIDE	IMSA-9604S-18Z14
CP802A	X-067U005049	WIRE HOLDER	B2013H02-5P
CP803A	X-067U004029	WIRE HOLDER	B2013H02-4P
CP8004	X-067U010049	WIRE HOLDER	B2013H02-10P
CP8005	X-069S260629	CONNECTOR PCB SIDE	A2001WV2-6P
OTHERS			
B301	X-024HT03564	CORE,BEADS	W4BRH3.5X6X1
B4201	X-024HT03564	CORE,BEADS	W4BRH3.5X6X1
CD402	X-WDL6016038	FLAT CABLE AWM2468 A	WG266C BLACK 160MM
CD802	X-WCL6850038	FLAT CABLE AWM2468 A	WG265C GRAY 500MM
CD803	X-WBL6032038	FLAT CABEL AWM2468 A	WG264C BLACK 320MM
CD8004	X-WHL6016038	FLAT CABLE AWM2468 A	WG2610C BLACK 160MM
CF201	X-1011T4R517	FILTER,CERAMIC	EFCT4R5MW5
CF202	X-1011T4R504	FILTER,CERAMIC	EFCT4R5YS5A
CF203	X-1029045R7G	FILTER,SAW	TSF5229P3
CF204	X-1012T04702	FILTER,CERAMIC TRAP	MKT47.3MC110P-TF
CUS251	X-800WFAA006	CUSHION A	
CUS252	X-800WFAA008	CUSHION C	
EL003	X-124120301A	EYE LET	XRY20X30BD
EL004	X-124116281A	EYE LET	XRY16X28BD
△ TU001	X-0145K00061	TUNER,VHF-UHF	TECC1040PG38B
X101	X-1002T01606	CERAMIC OSCILLATOR	CSTLS16M0X53-A0
X601	X-100CT3R505	CRYSTAL	HC-49/C


MISCELLANEOUS

△ Symbol.No.	Part No.	Part Name	Description
COILS			
△ L3800	X-028R200024	COIL,DEGAUSS	8R200024
OTHERS			
CD301	X-06CU123801	CORD CONNECTOR	CU123801
CD302	X-06CU123801	CORD CONNECTOR	CU123801
CD801	X-06CU823001	CORD CONNECTOR	CU823001
CD805	X-06CU823001	CORD CONNECTOR	CU823001
CD2301	X-122H081007	CORD JUMPER	2H081007
CD2302	X-06CU251002	CORD CONNECTOR	CU251002
CD2601	X-122H002102	CORD JUMPER	2H002102
CD8002	X-122H010102	CORD JUMPER	2H010102
DK4001	X-169G00014A	DECK CD	DVD-KDR717SK
△ SP351	X-070C546004	SPEAKER	SG04H02BRA
△ SP352	X-070C546004	SPEAKER	SG04H02BRA
△ V801	X-981210441	CRT W/DY	A51LXR195X80

REMOTE CONTROL UNIT PARTS LIST(RM-C394G)

△ Ref.No.	Part No.	Part Name	Description
	UR52EC1286C	BATTERY COVER	

PACKING



ACCESSORY REPLACEMENT PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
1	X-076G0EE010	TRANSMITTER	RM-C394G
2	X-791WHA0085	LAMIFILM,BAG	
3	X-792WHA0315	PACKAGE, TOP	
4	X-792WHA0316	PACKAGE,BOTTOM	
5	X-793WCD1426	GIFT BOX	
7	X-JB5KD500	POLYBAG,INSTRUCTION(RED CAUTION)	
8	X-J5C20401	INSTRUCTION BOOK	
9	X-J5500112	GUARANTEE CARD	
10	X-J5500115	SERVICE STATION LIST	
11	X-J5500117	REGISTRATION CARD	
12	X-J5501202	GUARANTEE CARD	