

PARTS LIST

[XV-SA600BK / XV-SA602SL]

* All printed circuit boards and its assemblies are not available as service parts.

Area Suffix	
J	----- U.S.A.
C	----- Canada


- Contents -

Exploded view of general assembly and parts list	-----	3-2
DVD Traverse mechanism assembly and parts list	-----	3-5
DVD Loading mechanism assembly and parts list	-----	3-7
Electrical parts list	-----	3-9
Packing materials and accessories parts list	-----	3-18

Exploded view of general assembly and parts list

Block No.

M	1	M	M
---	---	---	---



■ Parts list (General assembly) 1/2

Block No. M1MM

△	Item	Parts number	Parts name	Q'ty	Description	Area
	01	GN10018-009A	FRONT PANEL	1		60c,60j
		GN10018-010A	FRONT PANEL	1		62c,62j
	02	GN40006-001A	JVC MARK	1		60c,60j
		GN40006-002A	JVC MARK	1		62c,62j
	03	GN20010-017A	WINDOW SCREEN	1		
	04	LE40759-001A	FL SCREEN	1		
	05	LE30900-001A	INDICATOR	1		
	06	GN20011-001A	PUSH BUTTON	1		60c,60j
		GN20011-002A	PUSH BUTTON	1		62c,62j
	07	QYSBSF2608Z	T.SCREW	2		
	08	GN20012-003A	PUSH BUTTON	1		60c,60j
		GN20012-004A	PUSH BUTTON	1		62c,62j
	09	QYSBSF2608Z	T.SCREW	3		
	10	QYSDSG3008M	SCREW	1		60c,60j
		QYSDSG3008N	T.SCREW	1		62c,62j
	11	LE30951-001A	FOOT	2		60c,60j
		LE30951-002A	FOOT	2		62c,62j
	12	QYSBSG3010Z	T.SCREW	4		
	13	E75896-001	FELT SPACER	2		
	14	GN10016-001A	CHASSIS BASE	1		
	15	E47227-029	FOOT	2		
	16	QYSBSG3010Z	T.SCREW	2		
	17	LE40768-002A	PROTECT SHEET	1		
	18	QYSBSGG3008E	T.SCREW	4		
	19	QUQB12-1710AM	FFC WIRE	1		
	20	LE30968-001A	FASTENER	2		
	21	-----	DVD TRAVERSE ME	1		
	22	LV41659-201A	INSULATOR	4		
	23	LV41424-001A	SPECIAL SCREW	4		
	24	-----	1DISC LAODING B	1		
	25	LV10582-001A	TRAY LONG TYPE	1		
	26	LV20913-002A	CLAMPER BASE	1		
	27	LV32417-001A	CLAMPER	1		
	28	LV42089-002A	YOKE	1		
	29	LV42930-003A	MAGNET	1		
	30	LV41741-001A	SPECIAL SCREW	1		
	31	QYSBSF2008Z	SCREW	4		
	32	QUQ110-0610AJ	FFC WIRE	1		
	33	QYSBSG3010E	T.SCREW	3		
	34	QQR1259-001	FERRITE CORE	1		
	35	VYSA1R3-003	SPACER	1		
	36	GN20018-098A	REAR PANEL	1		60c,60j
		GN20018-0A1A	REAR PANEL	1		62c,62j
	37	QYSBSGY3008M	SPECIAL SCREW	1		
	38	QYSBSGY3008M	SPECIAL SCREW	1		
	39	QYSBSGY3008M	SPECIAL SCREW	1		
	40	QYSBSGY3008M	SPECIAL SCREW	3		
	41	QYSBSGY3008M	SPECIAL SCREW	1		

Extention of area column

60j : XV-SA600BK ver.J

60c : XV-SA600BK ver.C

62j : XV-SA602SL ver.J

62c : XV-SA602SL ver.C

■ Parts list (General assembly) 2/2

Block No. M1MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
⚠	42	QYSBSGY3008M	SPECIAL SCREW	2		
	43	QYSBSGY3008M	SPECIAL SCREW	1		
	44	QYSBSGY3008M	SPECIAL SCREW	1		
	45	QYSBSGY3008M	SPECIAL SCREW	1		
	46	QMF51U1-1R6-J8	FUSE	1		
	47	LE20541-001A/S/	METAL COVER	1		60c,60j
		LE20541-002A/S/	METAL COVER	1		62c,62j
	48	QYSBSGG3008E	T.SCREW	3		
	49	E406308-003	SPECIAL SCREW	2		60c,60j
		E406308-004	SPECIAL SCREW	2		62c,62j
	50	GN20013-003A	FITTING	1		60c,60j
		GN20013-004A	FITTING	1		62c,62j
	51	LE40758-001A	MARK	1		60c,60j
		LE40758-002A	MARK	1		62c,62j
	55	LE20540-002A	FL HOLDER	1		

Extention of area column

60j : XV-SA600BK ver.J

60c : XV-SA600BK ver.C

62j : XV-SA602SL ver.J


62c : XV-SA602SL ver.C

DVD Traverse mechanism assembly and parts list

Block No. **M 2 M M**

Grease

- ★ EBS0006-013B
- ▲ PG-641
- CFD-4007ZY2



■ Parts list (DVD Traverse mechanism assembly)


Block No. M2MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
	1	LE20520-002A	MECHA BASE	1		
	2	LE20516-001A	SPINDLE BASE	1		
	3	QYSDST2605M	TAPPING SCREW	3		
	4	LE30909-001A	HOLDER	1		
	5	QAR0165-001	FEED MOTOR	1		
	6	LV41510-001A	FEED GEAR	1		
	7	QYSPSPU2040M	SCREW	2		
	8	LV41512-001A	FEED GEAR	1		
	9	LV41517-003A	LEAD SCREW	1		
	10	LV41511-002A	FEED GEAR	1		
	11	LE40742-001A	TORSION SPRING	1		
	12	QYSDSF2005Z	SCREW	1		
	13	QYSDST2605M	TAPPING SCREW	2		
	14	LE20517-001A	HOLDER	1		
	15	LE40744-001A	SPRING	1		
	16	LV41121-002A	SLIDE SHAFT	2		
	17	QYSDST2605M	TAPPING SCREW	1		
	18	QAL0342-001	OPTICAL PICK-UP	1		
	19	LE20519-001A	ACTUATOR	1		
	20	LE30886-001A	SPRING	1		
	21	QYSPSFU1740Z	SCREW	2		
	22	LE30888-003A	SPRING	1		
	23	QYSPSGU1430Z	SCREW	1		
	24	LE40743-001A	SPRING	1		
	25	LE40774-001A	PLATE	1		
	26	QYSDST2606Z	SCREW	1		
	27	QAL0284-001	F.P.C.WIRE ASSY	1		
	28	QAR0162-001	SPINDLE MOTOR	1		
	29	QYSPSPU1760Z	SCREW	3		
	30	QYYASPF2608N	SCREW	3		

DVD Loading mechanism assembly and parts list

Block No. M3MM

Grease	
★	UD-24H2
▲	EM-30L
■	CFD-4007ZY2



■ Parts list (DVD Loading mechanism assembly)

Block No. M3MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
	1	LV10454-007A	LOADING BASE	1		
	2	QAR0164-001	MOTOR	1		
	3	LV42087-001A	MOTOR PULLEY	1		
	4	QYSPSPU1730Z	SCREW	1		
	5	VKZ4777-003	MINI SCREW	1		
	6	LV42209-001A	BELT	1		
	7	LV42084-002A	PULLEYGEAR	1		
	8	LV42085-002A	MIDDLE GEAR	1		
	9	LV42086-001A	IDLE GEAR	1		
	10	LV32514-002A	SLIDE CAM	1		
	11	LV42348-001A	GEAR BRACKET	1		
	12	VKZ4777-003	SCREW	1		
	13	LV20912-002A	ELEVATOR	1		
	14	QUQ110-0610AJ	FFC WIRE	1		

■ Electrical parts list (Loading motor board)

Block No. 04

⚠	Item	Parts number	Parts name	Remarks	Area
	CN 1	QGF1016F3-06	CONNECTOR		
	S 1	QSW0910-002	SWITCH		
	S 2	QSW0910-002	SWITCH		

■ Electrical parts list (Servo control board)

Block No. 01

△	Item	Parts number	Parts name	Remarks	Area	△	Item	Parts number	Parts name	Remarks	Area
	C 105	NEA70JM-476X	E.CAPACITOR				C 315	NCB31HK-471X	C CAPACITOR		
	C 106	NEA70JM-476X	E.CAPACITOR				C 316	NCB31HK-271X	C CAPACITOR		
	C 109	NCB31CK-104X	C CAPACITOR				C 317	NCB31HJ-121X	C CAPACITOR		
	C 110	NCS31HJ-221X	C.CAPA. C.M				C 318	NCB31CK-104X	C CAPACITOR		
	C 111	NCB31CK-104X	C CAPACITOR				C 319	NCB31HK-102X	C CAPACITOR		
	C 112	NCB31CK-104X	C CAPACITOR				C 320	NCB31HK-102X	C CAPACITOR		
	C 113	NEA70JM-226X	E CAPACITOR				C 321	NCB31HK-102X	C CAPACITOR		
	C 115	NCB31CK-104X	C CAPACITOR				C 322	NCB31HK-562X	C CAPACITOR		
	C 116	NCB31CK-104X	C CAPACITOR				C 323	NCB31HK-102X	C CAPACITOR		
	C 117	NCB31CK-473X	C CAPACITOR				C 324	NCB31CK-104X	C CAPACITOR		
	C 118	NCB31CK-273X	C CAPACITOR				C 325	NCS31HJ-470X	C.CAPA. C.M		
	C 119	NCB31HK-561X	C CAPACITOR				C 326	NCB31CK-183X	C CAPACITOR		
	C 120	NCB31HK-561X	C CAPACITOR				C 327	NCB31HK-102X	C CAPACITOR		
	C 121	NCB31CK-104X	C CAPACITOR				C 328	NCB31CK-104X	C CAPACITOR		
	C 122	NCS31HJ-120X	C.CAPA. C.M				C 329	NCB31CK-103X	C CAPACITOR		
	C 123	NCB31CK-104X	C CAPACITOR				C 330	NCB31CK-104X	C CAPACITOR		
	C 124	NCS31HJ-470X	C.CAPA. C.M				C 331	NCB31CK-103X	C CAPACITOR		
	C 125	NCB31HK-271X	C CAPACITOR				C 332	NCB21CK-105X	C CAPACITOR		
	C 126	NCB31CK-104X	C CAPACITOR				C 333	NCB31CK-104X	C CAPACITOR		
	C 127	NCB31CK-104X	C CAPACITOR				C 334	NCB31CK-104X	C CAPACITOR		
	C 128	NCB31CK-104X	C CAPACITOR				C 337	NCB31CK-104X	C CAPACITOR		
	C 129	NCB31HK-472X	C CAPACITOR				C 338	NCB31CK-104X	C CAPACITOR		
	C 135	NEA70JM-476X	E.CAPACITOR				C 339	NCB31CK-104X	C CAPACITOR		
	C 137	NEA70GM-476X	E.CAPA. C.M.				C 340	NCB31CK-104X	C CAPACITOR		
	C 138	NCB31CK-104X	C CAPACITOR				C 341	NCB31CK-104X	C CAPACITOR		
	C 139	NCB31CK-104X	C CAPACITOR				C 342	NCB31CK-104X	C CAPACITOR		
	C 141	NCB31CK-104X	C CAPACITOR				C 343	NCB31CK-104X	C CAPACITOR		
	C 142	NCB31CK-104X	C CAPACITOR				C 344	NCB31CK-104X	C CAPACITOR		
	C 143	NCB31CK-104X	C CAPACITOR				C 345	NCB31CK-104X	C CAPACITOR		
	C 144	NCB31CK-103X	C CAPACITOR				C 346	NCB31CK-104X	C CAPACITOR		
	C 146	NCB31CK-104X	C CAPACITOR				C 347	NCB31CK-104X	C CAPACITOR		
	C 201	NEA70JM-226X	E CAPACITOR				C 348	NCB31CK-104X	C CAPACITOR		
	C 203	NCB31CK-104X	C CAPACITOR				C 349	NCB31CK-104X	C CAPACITOR		
	C 204	NCB31CK-104X	C CAPACITOR				C 350	NCB31CK-104X	C CAPACITOR		
	C 205	NCS31HJ-121X	C CAPACITOR				C 401	NEA70GM-476X	E.CAPA. C.M.		
	C 207	NCB31HK-391X	C CAPACITOR				C 402	NCB31CK-104X	C CAPACITOR		
	C 208	NCB31HK-391X	C CAPACITOR				C 403	NCB31CK-104X	C CAPACITOR		
	C 211	NCB31HK-223X	C CAPACITOR				C 404	NCB31CK-104X	C CAPACITOR		
	C 212	NCB31CK-103X	C CAPACITOR				C 405	NCB31CK-104X	C CAPACITOR		
	C 216	NCB30JK-105X	C CAPACITOR				C 406	NCB31CK-104X	C CAPACITOR		
	C 217	NCB31CK-104X	C CAPACITOR				C 407	NCB31CK-104X	C CAPACITOR		
	C 218	NCB30JK-105X	C CAPACITOR				C 450	NCB31CK-104X	C CAPACITOR		
	C 251	NCB31CK-104X	C CAPACITOR				C 501	NCB31CK-104X	C CAPACITOR		
	C 252	NEA71AM-336X	E CAPACITOR				C 506	NDC31HJ-150X	C CAPACITOR		
	C 253	NCB31CK-104X	C CAPACITOR				C 507	NDC31HJ-180X	C.CAPACITOR		
	C 255	NCB31CK-153X	C CAPACITOR				C 511	NEA70GM-476X	E.CAPA. C.M.		
	C 256	NCB31CK-104X	C CAPACITOR				C 512	NCB31CK-104X	C CAPACITOR		
	C 257	NCB31CK-104X	C CAPACITOR				C 514	NCB31CK-104X	C CAPACITOR		
	C 258	NCB31CK-104X	C CAPACITOR				C 515	NCB31CK-104X	C CAPACITOR		
	C 259	NCB31CK-104X	C CAPACITOR				C 516	NCB31CK-104X	C CAPACITOR		
	C 260	NCB31CK-104X	C CAPACITOR				C 517	NCB31CK-104X	C CAPACITOR		
	C 261	NCB31CK-104X	C CAPACITOR				C 518	NCB31CK-104X	C CAPACITOR		
	C 262	NCB31CK-104X	C CAPACITOR				C 519	NCB31CK-104X	C CAPACITOR		
	C 263	NCB31CK-104X	C CAPACITOR				C 520	NCB31CK-104X	C CAPACITOR		
	C 264	NCB31CK-103X	C CAPACITOR				C 523	NCB31CK-104X	C CAPACITOR		
	C 301	NCB31CK-104X	C CAPACITOR				C 524	NEA70GM-476X	E.CAPA. C.M.		
	C 302	NCB31CK-104X	C CAPACITOR				C 527	NEA70GM-476X	E.CAPA. C.M.		
	C 303	NCB31CK-104X	C CAPACITOR				C 528	NCB31CK-104X	C CAPACITOR		
	C 304	NEA70GM-107X	E CAPACITOR				C 529	NCB31CK-104X	C CAPACITOR		
	C 306	NEA70GM-107X	E CAPACITOR				C 531	NCB31CK-104X	C CAPACITOR		
	C 308	NEA70GM-107X	E CAPACITOR				C 532	NCB31CK-104X	C CAPACITOR		
	C 310	NCB31CK-104X	C CAPACITOR				C 533	NCB31CK-104X	C CAPACITOR		
	C 311	NCB31HK-561X	C CAPACITOR				C 534	NCB31CK-104X	C CAPACITOR		
	C 312	NCB31HK-561X	C CAPACITOR				C 535	NCB31CK-104X	C CAPACITOR		
	C 313	NCB31HK-561X	C CAPACITOR				C 536	NCB31CK-104X	C CAPACITOR		
	C 314	NCB31HK-331X	C CAPACITOR				C 539	NCB31CK-104X	C CAPACITOR		

■ Electrical parts list (Servo control board)

Block No. 01

△	Item	Parts number	Parts name	Remarks	Area
	C 540	NCB31CK-104X	C CAPACITOR		
	C 541	NCB31CK-104X	C CAPACITOR		
	C 542	NCB31CK-104X	C CAPACITOR		
	C 543	NCB31CK-104X	C CAPACITOR		
	C 544	NCB31CK-104X	C CAPACITOR		
	C 545	NCB31CK-104X	C CAPACITOR		
	C 547	NCB31CK-104X	C CAPACITOR		
	C 548	NCB31CK-104X	C CAPACITOR		
	C 549	NEA70GM-476X	E.CAPA. C.M.		
	C 550	NCB31CK-104X	C CAPACITOR		
	C 554	NCB31CK-104X	C CAPACITOR		
	C 555	NCB31CK-104X	C CAPACITOR		
	C 557	NCB31CK-104X	C CAPACITOR		
	C 558	NCB11CK-105X	C CAPACITOR		
	C 569	NCB31CK-104X	C CAPACITOR		
	C 571	NEA70GM-476X	E.CAPA. C.M.		
	C 572	NCB31CK-104X	C CAPACITOR		
	C 573	NEA70GM-227X	E.CAPA. C.M.		
	C 578	NCB31CK-104X	C CAPACITOR		
	C 580	NEA70GM-476X	E.CAPA. C.M.		
	C 581	NEA70GM-227X	E.CAPA. C.M.		
	C 582	NEA70GM-476X	E.CAPA. C.M.		
	C 601	NEA70GM-476X	E.CAPA. C.M.		
	C 602	NEA70GM-476X	E.CAPA. C.M.		
	C 619	NCB31CK-104X	C CAPACITOR		
	C 801	NCS31HJ-680X	C.CAPA. C.M.		
	C 802	NCS31HJ-680X	C.CAPA. C.M.		
	C 803	NCS31HJ-120X	C.CAPA. C.M.		
	C 804	NCS31HJ-102X	C CAPACITOR		
	C 805	NCS31HJ-820X	C CAPACITOR		
	C 806	NCS31HJ-221X	C.CAPA. C.M.		
	C 807	NCS31HJ-180X	C CAPACITOR		
	C 808	NCS31HJ-181X	C CAPACITOR		
	C 809	NCB31HK-392X	C CAPACITOR		
	C 810	NCB31CK-183X	C CAPACITOR		
	C 902	NCB31CK-104X	C CAPACITOR		
	C 904	NCB31CK-104X	C CAPACITOR		
	C 906	NCB31CK-104X	C CAPACITOR		
	C 908	NCB31CK-104X	C CAPACITOR		
	C 992	NCB31CK-104X	C CAPACITOR		
	C 993	NCB31CK-104X	C CAPACITOR		
	C 994	NCB31CK-104X	C CAPACITOR		
	C 995	NCB31CK-104X	C CAPACITOR		
	C 996	NCB31CK-104X	C CAPACITOR		
	C 997	NCB31CK-104X	C CAPACITOR		
	C 998	NCB31CK-104X	C CAPACITOR		
	CN101	QGF0522F1-30W	FFC CONNECTOR	PU	
	CN201	QGF1016F2-15W	CONNECTOR	SP&STP	
	CN202	QGF1016F2-06W	CONNECTOR	LOADER	
	CN502	QGB2027L1-26X	CONNECTOR	SYSTEM	
	CN503	QGB2027L1-26X	CONNECTOR	VIDEO	
	D 101	RB521S-30	DIODE		
	IC101	AN8703FH-V	IC		
	IC201	BA5983FM-X	IC		
	IC251	BA6664FM-X	LSI		
	IC301	MN103S26EGA	IC		
	IC451	S-93C66AFJ-X	IC		
	IC501	NDV8611VWA	IC		
	IC505	K4S643232E-TC60	IC		
	IC509	SST39VF160-9CEK	IC (FLASH)	LSB	
	IC510	S-93C66AFJ-X	IC		
	IC511	LM1117MP1.8-X	IC		
	IC512	74LCX373MTC-X	IC(DIGITAL)		
	IC513	74LCX373MTC-X	IC(DIGITAL)		
	IC522	74LCX32MTC-X	IC(DIGITAL)		
	IC523	NC7SZ125P5-X	IC(DIGITAL)		

△	Item	Parts number	Parts name	Remarks	Area
	K 101	NQR0007-002X	FERRITE BEADS		
	K 301	NQR0007-002X	FERRITE BEADS		
	K 302	NQR0007-002X	FERRITE BEADS		
	K 303	NQR0007-002X	FERRITE BEADS		
	K 304	NQR0007-002X	FERRITE BEADS		
	K 401	NQR0007-002X	FERRITE BEADS		
	K 501	NQR0007-002X	FERRITE BEADS		
	K 504	NQR0007-002X	FERRITE BEADS		
	K 507	NQR0007-002X	FERRITE BEADS		
	K 508	NQR0007-002X	FERRITE BEADS		
	K 509	NQR0007-002X	FERRITE BEADS		
	K 510	NQR0007-002X	FERRITE BEADS		
	K 513	NQR0007-002X	FERRITE BEADS		
	K 515	NQR0007-002X	FERRITE BEADS		
	K 518	NQR0007-002X	FERRITE BEADS		
	K 519	NQR0007-002X	FERRITE BEADS		
	K 520	NQR0007-002X	FERRITE BEADS		
	K 556	NRSA63J-0R0X	MG RESISTOR		
	K 557	NRSA63J-0R0X	MG RESISTOR		
	K 558	NRSA63J-0R0X	MG RESISTOR		
	K 559	NRSA63J-0R0X	MG RESISTOR		
	K 560	NQR0007-002X	FERRITE BEADS		
	K 561	NQR0007-002X	FERRITE BEADS		
	K 562	NQR0007-002X	FERRITE BEADS		
	K 563	NQR0007-002X	FERRITE BEADS		
	K 564	NQR0007-002X	FERRITE BEADS		
	K 565	NQR0007-002X	FERRITE BEADS		
	K 566	NRSA02J-0R0X	MG RESISTOR		
	K 567	NQR0007-002X	FERRITE BEADS		
	K 568	NQR0007-002X	FERRITE BEADS		
	K 569	NQR0007-002X	FERRITE BEADS		
	K 570	NQR0007-002X	FERRITE BEADS		
	K 571	NQR0007-002X	FERRITE BEADS		
	K 572	NQR0007-002X	FERRITE BEADS		
	K 573	NQR0007-002X	FERRITE BEADS		
	K 574	NQR0007-002X	FERRITE BEADS		
	K 575	NQR0007-002X	FERRITE BEADS		
	K 576	NQR0007-002X	FERRITE BEADS		
	K 577	NQR0007-002X	FERRITE BEADS		
	K 578	NQR0007-002X	FERRITE BEADS		
	K 579	NQR0007-002X	FERRITE BEADS		
	K 582	NQR0007-002X	FERRITE BEADS		
	K 586	NQR0007-002X	FERRITE BEADS		
	L 501	NQL044K-100X	INDUCTOR		
	Q 101	KTA1001/Y/-X	TRANSISTOR		
	Q 102	KTA1001/Y/-X	TRANSISTOR		
	Q 103	DTA144EE-X	DIGI TRANSISTOR		
	Q 501	2SB1424/QR/-X	TRANSISTOR		
	Q 502	2SC2412K/RS/-X	CHIP TRANSISTOR		
	Q 801	2SC4617/R/-X	TRANSISTOR		
	Q 802	2SA1774/R/-X	TRANSISTOR		
	Q 803	2SC4617/R/-X	TRANSISTOR		
	Q 804	2SC4617/R/-X	TRANSISTOR		
	Q 805	2SC4617/R/-X	TRANSISTOR		
	Q 806	2SC4617/R/-X	TRANSISTOR		
	Q 807	DTC114EE-X	TRANSISTOR		
	Q 808	2SC4617/R/-X	TRANSISTOR		
	R 101	NRSA63J-333X	MG RESISTOR		
	R 102	NRSA63J-223X	MG RESISTOR		
	R 103	NRSA63J-223X	MG RESISTOR		
	R 104	NRS125J-270X	MG RESISTOR		
	R 105	NRS125J-270X	MG RESISTOR		
	R 106	NRSA63J-273X	MG RESISTOR		
	R 107	NRSA63J-273X	MG RESISTOR		
	R 108	NRSA63J-222X	MG RESISTOR		
	R 109	NRSA63J-182X	MG RESISTOR		

■ Electrical parts list (Servo control board)

Block No. 01

△	Item	Parts number	Parts name	Remarks	Area	△	Item	Parts number	Parts name	Remarks	Area
	R 110	NRSA63J-333X	MG RESISTOR				R 329	NRSA63J-473X	MG RESISTOR		
	R 111	NRVA63D-243X	RES. C.M				R 332	NRSA63J-102X	MG RESISTOR		
	R 112	NRSA63J-822X	MG RESISTOR				R 333	NRSA63J-183X	MG RESISTOR		
	R 113	NRSA63J-103X	MG RESISTOR				R 334	NRSA63J-102X	MG RESISTOR		
	R 114	NRSA63J-0R0X	MG RESISTOR				R 336	NRSA63J-273X	MG RESISTOR		
	R 115	NRSA63J-0R0X	MG RESISTOR				R 337	NRSA63J-273X	MG RESISTOR		
	R 116	NRSA63J-0R0X	MG RESISTOR				R 338	NRSA63J-472X	MG RESISTOR		
	R 117	NRSA63J-0R0X	MG RESISTOR				R 339	NRSA63J-472X	MG RESISTOR		
	R 119	NRSA63J-2R2X	MG RESISTOR				R 340	NRSA63J-103X	MG RESISTOR		
	R 120	NRSA63J-2R2X	MG RESISTOR				R 341	NRSA63J-562X	MG RESISTOR		
	R 125	NRSA63J-105X	MG RESISTOR				R 402	NRSA63J-472X	MG RESISTOR		
	R 126	NRSA63J-105X	MG RESISTOR				R 403	NRSA63J-0R0X	MG RESISTOR		
	R 127	NRSA63J-222X	MG RESISTOR				R 405	NRSA63J-0R0X	MG RESISTOR		
	R 128	NRS125J-1R0X	MG RESISTOR				R 411	NRSA63J-472X	MG RESISTOR		
	R 129	NRS125J-1R0X	MG RESISTOR				R 413	NRSA63J-472X	MG RESISTOR		
	R 130	NRSA63J-182X	MG RESISTOR				R 414	NRSA63J-472X	MG RESISTOR		
	R 201	NRSA63J-470X	MG RESISTOR				R 421	NRSA63J-0R0X	MG RESISTOR		
	R 202	NRS125J-1R0X	MG RESISTOR				R 422	NRSA63J-472X	MG RESISTOR		
	R 203	NRSA63J-0R0X	MG RESISTOR				R 423	NRSA63J-472X	MG RESISTOR		
	R 204	NRSA63J-273X	MG RESISTOR				R 424	NRSA63J-472X	MG RESISTOR		
	R 205	NRSA63J-273X	MG RESISTOR				R 427	NRSA63J-0R0X	MG RESISTOR		
	R 206	NRSA63J-303X	MG RESISTOR				R 428	NRSA63J-472X	MG RESISTOR		
	R 207	NRSA63J-473X	MG RESISTOR				R 501	NRSA63J-470X	MG RESISTOR		
	R 208	NRSA63J-223X	MG RESISTOR				R 512	NRSA63J-332X	MG RESISTOR		
	R 209	NRSA63J-223X	MG RESISTOR				R 521	NRSA63J-103X	MG RESISTOR		
	R 210	NRSA63J-242X	MG RESISTOR				R 522	NRSA63J-0R0X	MG RESISTOR		
	R 211	NRSA63J-242X	MG RESISTOR				R 523	NRSA63J-0R0X	MG RESISTOR		
	R 212	NRSA63J-103X	MG RESISTOR				R 524	NRSA63J-0R0X	MG RESISTOR		
	R 213	NRSA63J-103X	MG RESISTOR				R 525	NRSA63J-0R0X	MG RESISTOR		
	R 214	NRSA63J-103X	MG RESISTOR				R 531	NRSA63J-562X	MG RESISTOR		
	R 215	NRSA63J-103X	MG RESISTOR				R 532	NRSA63J-392X	MG RESISTOR		
	R 216	NRSA63J-912X	MG RESISTOR				R 533	NRSA63J-102X	MG RESISTOR		
	R 219	NRSA63J-183X	MG RESISTOR				R 534	NRSA63J-561X	MG RESISTOR		
	R 220	NRSA63J-243X	MG RESISTOR				R 535	NRSA63J-333X	MG RESISTOR		
	R 221	NRSA63J-682X	MG RESISTOR				R 536	NRSA63J-102X	MG RESISTOR		
	R 222	NRSA63J-103X	MG RESISTOR				R 541	NRSA63J-0R0X	MG RESISTOR		
	R 223	NRSA63J-912X	MG RESISTOR				R 543	NRSA63J-0R0X	MG RESISTOR		
	R 224	NRSA63J-103X	MG RESISTOR				R 544	NRSA63J-471X	MG RESISTOR		
	R 251	NRS125J-R47X	MG RESISTOR				R 547	NRSA63J-0R0X	MG RESISTOR		
	R 252	NRSA63J-2R2X	MG RESISTOR				R 548	NRSA63J-471X	MG RESISTOR		
	R 253	NRSA63J-0R0X	MG RESISTOR				R 549	NRSA63J-471X	MG RESISTOR		
	R 254	NRSA63J-203X	MG RESISTOR				R 550	NRSA63J-471X	MG RESISTOR		
	R 255	NRSA63J-103X	MG RESISTOR				R 551	NRSA63J-0R0X	MG RESISTOR		
	R 256	NRSA63J-470X	MG RESISTOR				R 552	NRSA63J-0R0X	MG RESISTOR		
	R 258	NRSA63J-0R0X	MG RESISTOR				R 553	NRSA63J-0R0X	MG RESISTOR		
	R 259	NRSA63J-103X	MG RESISTOR				R 565	NRVA63D-103X	MF RESISTER		
	R 301	NRSA63J-473X	MG RESISTOR				R 566	NRVA63D-122X	MG RESISTOR		
	R 302	NRSA63J-473X	MG RESISTOR				R 567	NRVA63D-750X	RES. C.M		
	R 303	NRSA63J-473X	MG RESISTOR				R 568	NRVA63D-680X	RES. C.M		
	R 304	NRSA63J-473X	MG RESISTOR				R 569	NRVA63D-680X	RES. C.M		
	R 305	NRSA63J-473X	MG RESISTOR				R 570	NRSA63J-100X	MG RESISTOR		
	R 306	NRSA63J-473X	MG RESISTOR				R 572	NRVA63D-680X	RES. C.M		
	R 307	NRSA63J-473X	MG RESISTOR				R 573	NRSA63J-162X	MG RESISTOR		
	R 308	NRSA63J-0R0X	MG RESISTOR				R 574	NRSA63J-162X	MG RESISTOR		
	R 309	NRSA63J-473X	MG RESISTOR				R 575	NRSA63J-471X	MG RESISTOR		
	R 313	NRSA63J-473X	MG RESISTOR				R 576	NRSA63J-471X	MG RESISTOR		
	R 317	NRSA63J-473X	MG RESISTOR				R 578	NRSA63J-471X	MG RESISTOR		
	R 319	NRSA63J-473X	MG RESISTOR				R 579	NRSA63J-471X	MG RESISTOR		
	R 320	NRSA63J-105X	MG RESISTOR				R 580	NRSA63J-471X	MG RESISTOR		
	R 321	NRSA63J-473X	MG RESISTOR				R 583	NRSA63J-471X	MG RESISTOR		
	R 323	NRSA63J-473X	MG RESISTOR				R 584	NRSA63J-332X	MG RESISTOR		
	R 324	NRSA63J-473X	MG RESISTOR				R 608	NRSA63J-103X	MG RESISTOR		
	R 325	NRSA63J-123X	MG RESISTOR				R 655	NRSA63J-0R0X	MG RESISTOR		
	R 326	NRSA63J-473X	MG RESISTOR				R 738	NRSA63J-152X	MG RESISTOR		
	R 327	NRSA63J-105X	MG RESISTOR				R 739	NRSA63J-0R0X	MG RESISTOR		
	R 328	NRSA63J-183X	MG RESISTOR				R 740	NRSA63J-0R0X	MG RESISTOR		

■ Electrical parts list (Servo control board) Block No. 01

△	Item	Parts number	Parts name	Remarks	Area
	R 801	NRSA63J-123X	MG RESISTOR		
	R 802	NRSA63J-223X	MG RESISTOR		
	R 803	NRSA63J-122X	MG RESISTOR		
	R 804	NRSA63J-821X	MG RESISTOR		
	R 805	NRSA63J-242X	MG RESISTOR		
	R 806	NRSA63J-821X	MG RESISTOR		
	R 807	NRSA63J-222X	MG RESISTOR		
	R 808	NRSA63J-102X	MG RESISTOR		
	R 809	NRSA63J-223X	MG RESISTOR		
	R 810	NRSA63J-222X	MG RESISTOR		
	R 811	NRSA63J-103X	MG RESISTOR		
	R 812	NRSA63J-103X	MG RESISTOR		
	R 813	NRSA63J-103X	MG RESISTOR		
	R 814	NRSA63J-103X	MG RESISTOR		
	R 815	NRSA63J-821X	MG RESISTOR		
	R 816	NRSA63J-820X	MG RESISTOR		
	R 817	NRSA63J-102X	MG RESISTOR		
	R 818	NRSA63J-102X	MG RESISTOR		
	R 991	NRSA63J-220X	MG RESISTOR		
	X 301	NAX0542-001X	C RESONATOR		
	X 401	NAX0543-001X	C RESONATOR		
	X 571	NAX0513-001X	CRYSTAL		

■ Electrical parts list (Main board)

Block No. 02

Item	Parts number	Parts name	Remarks	Area	Item	Parts number	Parts name	Remarks	Area
BK 1	LE20539-001A	FL HOLDER			C 837	NCS31HJ-101X	C.CAPA. C.M		
C 1	QEKC1HM-475Z	E CAPACITOR	4.7MF 20% 50V		C 838	NCS31HJ-101X	C.CAPA. C.M		
C 2	QEKC1HM-475Z	E CAPACITOR	4.7MF 20% 50V		C 839	NCS31HJ-101X	C.CAPA. C.M		
C 3	NCB21CK-105X	C CAPACITOR			C 840	NCS31HJ-101X	C.CAPA. C.M		
C 4	QEKC1AM-476Z	E CAPACITOR	47MF 20% 10V		△ C 902	QFZ9075-683	M CAPACITOR	.068MF	
C 5	QETN0JM-227Z	E CAPACITOR	220MF 20% 6.3V		△ C 903	QFZ9075-683	M CAPACITOR	.068MF	
C 6	NCB31CK-104X	C CAPACITOR			△ C 905	QCZ9079-102	C CAPACITOR	1000PF	
C 7	NCB31CK-103X	C CAPACITOR			△ C 906	QCZ9079-102	C CAPACITOR	1000PF	
C 8	NCB31CK-104X	C CAPACITOR			△ C 907	QETM2DM-157	E CAPACITOR	J/C/DOM	
C 9	NCS31HJ-331X	C.CAPA. C.M			C 908	QCZ0136-332Z	C CAPACITOR	3300PF	
C 10	NCB21CK-105X	C CAPACITOR			C 913	QCZ0136-101Z	C CAPACITOR	100PF	
C 11	NCB21CK-105X	C CAPACITOR			C 914	QEZO532-396Z	E CAPACITOR	39MF	
C 12	NCB21CK-105X	C CAPACITOR			C 915	NCB31HK-471X	C CAPACITOR		
C 700	QTE0J28-227Z	E CAPACITOR			C 917	NCB31CK-104X	C CAPACITOR		
C 701	NCB31HK-152X	C CAPACITOR			C 921	NCS31HJ-101X	C.CAPA. C.M		
C 704	NCS31HJ-101X	C.CAPA. C.M			C 922	NCS31HJ-101X	C.CAPA. C.M		
C 707	QETN1AM-107Z	E CAPACITOR	100MF 20% 10V		C 923	NCS31HJ-101X	C.CAPA. C.M		
C 711	QCZ0202-155Z	ML C CAPA I/M	1.5MF		C 924	NCS31HJ-101X	C.CAPA. C.M		
C 713	NCS31HJ-101X	C.CAPA. C.M			C 926	NCS31HJ-101X	C.CAPA. C.M		
C 714	QTE0J28-477Z	E CAPACITOR			C 927	NCS31HJ-101X	C.CAPA. C.M		
C 716	QTE0J28-477Z	E CAPACITOR			C 928	NCS31HJ-101X	C.CAPA. C.M		
C 717	QCZ0202-155Z	ML C CAPA I/M	1.5MF		C 960	QEZO529-826Z	E CAPACITOR	82MF	
C 724	NCB31HK-102X	C CAPACITOR			C 961	NCB31CK-104X	C CAPACITOR		
C 730	QFV21HJ-224Z	MF CAPACITOR	.22MF 5% 50V		C 962	QETN1HM-226Z	E CAPACITOR	22MF 20% 50V	
C 731	QFN31HJ-103Z	M CAPACITOR	.010MF 5% 50V		C 963	QEZO533-396Z	E CAPACITOR	39MF	
C 735	NCB31CK-104X	C CAPACITOR			C 964	NCB31CK-104X	C CAPACITOR		
C 740	QFLC1HJ-561Z	M CAPACITOR	560PF 5% 50V		C 965	QEZO586-567	E CAPACITOR	560MF	
C 741	QFP31HJ-121Z	PP CAPACITOR	120PF 5% 50V		C 966	QETN1AM-477Z	E CAPACITOR	470MF 20% 10V	
C 742	QFLC1HJ-182Z	M CAPACITOR	1800PF 5% 50V		C 968	NCB21CK-105X	C CAPACITOR		
C 743	QFN31HJ-272Z	M CAPACITOR	2700PF 5% 50V		C 969	QETN0JM-227Z	E CAPACITOR	220MF 20% 6.3V	
C 744	QFLC1HJ-561Z	M CAPACITOR	560PF 5% 50V		C 971	QETN1HM-107Z	E CAPACITOR	100MF 20% 50V	
C 745	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V		C 972	NCS31HJ-471X	C CAPACITOR		
C 746	QTE1A48-476Z	E.CAPA I/M			C 975	QEZO591-108	E CAPACITOR	1000MF	
C 747	QFLC1HJ-182Z	M CAPACITOR	1800PF 5% 50V		C 976	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
C 748	QFLC1HJ-561Z	M CAPACITOR	560PF 5% 50V		C 978	QETN1AM-107Z	E CAPACITOR	100MF 20% 10V	
C 749	QFLC1HJ-561Z	M CAPACITOR	560PF 5% 50V		C 979	QEZO530-827	E CAPACITOR	820MF	
C 750	QFLC1HJ-561Z	M CAPACITOR	560PF 5% 50V		C 981	NCB31CK-104X	C CAPACITOR		
C 751	QFP31HJ-121Z	PP CAPACITOR	120PF 5% 50V		C 982	QEZO594-187Z	E CAPACITOR	180MF	
C 752	QFLC1HJ-182Z	M CAPACITOR	1800PF 5% 50V		C 984	QETN1CM-227Z	E CAPACITOR	220MF 20% 16V	
C 753	QFN31HJ-272Z	M CAPACITOR	2700PF 5% 50V		C 986	NCB21CK-334X	C.CAPA. C.M		
C 754	QFLC1HJ-561Z	M CAPACITOR	560PF 5% 50V		C 987	QEZO594-187Z	E CAPACITOR	180MF	
C 755	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V		C 989	QETN1CM-227Z	E CAPACITOR	220MF 20% 16V	
C 756	QTE1A48-476Z	E.CAPA I/M			C 990	NCB21CK-334X	C.CAPA. C.M		
C 757	QFLC1HJ-182Z	M CAPACITOR	1800PF 5% 50V		C 991	QETN0JM-227Z	E CAPACITOR	220MF 20% 6.3V	
C 761	QTE1C28-107Z	E CAPACITOR			C 992	QETN0JM-227Z	E CAPACITOR	220MF 20% 6.3V	
C 762	QTE1C28-107Z	E CAPACITOR			C 993	NCS31HJ-101X	C.CAPA. C.M		
C 771	QTE1C28-107Z	E CAPACITOR			C 994	QETN1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
C 772	QTE1C28-107Z	E CAPACITOR			C 995	NCB21CK-105X	C CAPACITOR		
C 797	NCB31HK-152X	C CAPACITOR			C 997	QETN1CM-227Z	E CAPACITOR	220MF 20% 16V	
C 801	QEZO592-107Z	E CAPACITOR	100MF		C1701	QETN1EM-476Z	E CAPACITOR	47MF 20% 25V	
C 802	NCB31CK-104X	C CAPACITOR			C1702	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
C 803	NCB31CK-104X	C CAPACITOR			C1703	NCS31HJ-151X	C CAPACITOR		
C 806	QEZO592-107Z	E CAPACITOR	100MF		C1704	NCS31HJ-331X	C.CAPA. C.M		
C 808	QEZO592-107Z	E CAPACITOR	100MF		C1706	NCB31CK-104X	C CAPACITOR		
C 810	QEZO592-107Z	E CAPACITOR	100MF		CN 4	QGD2501C1-04Z	SOCKET		
C 811	NCB31CK-104X	C CAPACITOR			CN512	QGB2027M8-26	CONNECTOR		
C 812	QEZO598-226Z	E CAPACITOR	22MF		CN513	QGB2027M8-26	CONNECTOR		
C 813	QETN1AM-477Z	E CAPACITOR	470MF 20% 10V		CN701	QGF1205C1-17	CONNECTOR		
C 814	QEZO598-226Z	E CAPACITOR	22MF		△ CP951	ICP-N10-T	ICP		
C 815	QETN1AM-477Z	E CAPACITOR	470MF 20% 10V		CP952	ICP-N5-T	ICP		
C 817	QEKC1EM-226Z	E CAPACITOR	22MF 20% 25V		D 1	SPR-325MVW/L-T	LED	STANDBY	
C 819	QEZO598-226Z	E CAPACITOR	22MF		D 2	SPR-325MVW/L-T	LED	PROGRESSIVE	
C 833	NCB31HK-103X	C CAPACITOR			D 3	SELU2E10C	LED		
C 834	NCB31CK-104X	C CAPACITOR			D 9	1SS355-X	DIODE C.M		
C 835	NCB21CK-105X	C CAPACITOR			△ D 901	S1WB/A/60-4101	BRIDGE DIODE		
C 836	NCB31CK-103X	C CAPACITOR			△ D 903	SARS01-T2	FR DIODE		

■ Electrical parts list (Main board)

Block No. 02

△	Item	Parts number	Parts name	Remarks	Area
△	D 904	F1T4-T2	FR DIODE		
	D 905	F1T4-T2	FR DIODE		
△	D 908	F1T4-T2	FR DIODE		
△	D 951	F1T4-T2	FR DIODE		
△	D 952	F1T4-T2	FR DIODE		
△	D 954	F1T4-T2	FR DIODE		
△	D 956	F1T4-T2	FR DIODE		
△	D 957	F1T4-T2	FR DIODE		
	D 960	MTZJ4.7B-T2	Z DIODE I M		
△	D 981	RK34-LFB2	SB DIODE		
	D 991	HZS3CLL-T2	Z DIODE		
	D 998	F1T4-T2	FR DIODE		
	DI 1	QLF0103-002	FL TUBE		
	EP711	QNZ0136-001Z	EARTH PLATE		
	EP901	QNZ0136-001Z	EARTH PLATE		
	EP951	QNZ0136-001Z	EARTH PLATE		
	FC901	QNG0003-001Z	FUSE CLIP		
	FC902	QNG0003-001Z	FUSE CLIP		
	FW 1	QUM104-12DGZ4	PARA RIBON WIRE		
	FW 2	QUM108-15DGZ4	PARA RIBON WIRE		
	IC 1	GP1UD271XK	RM RECIVER		
	IC 2	MN101C35DLJ	IC	SYSTEM MICOM	
	IC 3	XC61FN2712M-X	IC		
	IC703	MN35505-X	IC C M		
	IC704	TC74HC08AF-X	IC		
	IC741	NJM5532M-XE	IC		
	IC751	NJM5532M-XE	IC		
	IC801	MM1568CJ-X	IC		
△	IC901	STR-G6551R-F8	IC(HYBRID)		
	IC951	MM1565AF-X	IC		
	IC952	PQ3RD23	IC		
	J 700	QNN0461-001	PIN JACK	AUDIO L/R	
	J 701	QNN0458-001	PIN JACK	COAXIAL	
	J 702	QNS0089-001	3.5 JACK	AV COMPULINK	
	J 703	GP1FA351TZ	OPT TRANSMITTER	OPT DIGITAL OUT	
	J 801	QNN0395-001	PIN JACK	COMPONENT	
	J 802	QNN0454-001	PIN JACK	S/COMP.	
	JT102	QGD2501C1-05Z	SOCKET I.M	CN2	
	JT103	QGD2501C1-03Z	SOCKET		
	K 101	NQR0227-004X	FERRITE BEADS		
	K 701	NRSA63J-0R0X	MG RESISTOR		
	K 703	NRSA63J-0R0X	MG RESISTOR		
	K 704	NRSA63J-0R0X	MG RESISTOR		
	K 705	NQR0227-004X	FERRITE BEADS		
	K 706	NQR0227-004X	FERRITE BEADS		
	K 711	QQR1183-001Z	FERRITE BEADS		
	K 721	QQR1183-001Z	FERRITE BEADS		
	K 801	QQR0601-001Z	FERRITE BEADS		
	K 902	QQR1183-001Z	FERRITE BEADS		
	K1701	NQR0227-004X	FERRITE BEADS		
	K1702	NQR0227-004X	FERRITE BEADS		
	L 709	QQL231K-2R2Y	INDUCTOR		
△	L 901	QQR1105-001	LINE FILTER		
	L 952	QQR1291-001Z	CHOKE COIL		
	L 955	QQR1291-001Z	CHOKE COIL		
	L 957	QQL244K-100Z	INDUCTOR		
	L 959	QQL244K-100Z	INDUCTOR		
	L 960	QQR1291-001Z	CHOKE COIL		
	L1701	QQL231K-R68Y	INDUCTOR I.M		
	P 901	QNC0092-001	AC INLET	J/C	
△	PC901	PC123Y02	IC(PHOTO COUPLE		
	Q 1	KRC104S-X	TRANSISTOR		
	Q 2	KRC107S-X	DIGITAL.TR		
	Q 4	KRC109S-X	TRANSISTOR		
	Q 5	KRA102S-X	DIGITAL.TR		
	Q 13	KRC107S-X	DIGITAL.TR		

△	Item	Parts number	Parts name	Remarks	Area
	Q 14	KRA102S-X	DIGITAL.TR		
	Q 15	KRC107S-X	DIGITAL.TR		
	Q 16	KRA102S-X	DIGITAL.TR		
	Q 17	KRC107S-X	DIGITAL.TR		
	Q 18	KRA102S-X	DIGITAL.TR		
	Q 19	KRC107S-X	DIGITAL.TR		
	Q 20	KRA102S-X	DIGITAL.TR		
	Q 25	KRA102S-X	DIGITAL.TR		
	Q 743	2SC3576-JVC-T	TRANSISTOR I/M	AMUTE1	
	Q 753	2SC3576-JVC-T	TRANSISTOR I/M	AMUTE1	
	Q 755	2SC3576-JVC-T	TRANSISTOR I/M	FREQ	
	Q 756	2SC3576-JVC-T	TRANSISTOR I/M	FREQ	
	Q 791	2SC2412K/RS/-X	CHIP TRANSISTOR		
	Q 792	KRA102S-X	DIGITAL.TR		
	Q 951	2SC3576-JVC-T	TRANSISTOR I/M		
	Q 952	KRA104S-X	DIGITAL.TR		
	Q 991	KTC3199/Y/-T	TR I/M		
	R 2	NRSA63J-431X	MG RESISTOR		
	R 3	NRSA63J-681X	MG RESISTOR		
	R 4	NRSA63J-112X	MG RESISTOR		
	R 5	NRSA63J-222X	MG RESISTOR		
	R 6	NRSA63J-681X	MG RESISTOR		
	R 7	NRSA63J-222X	MG RESISTOR		
	R 8	NRSA63J-151X	MG RESISTOR		
	R 10	NRSA63J-820X	MG RESISTOR		
	R 11	NRSA63J-0R0X	MG RESISTOR		
	R 12	NRSA63J-820X	MG RESISTOR		
	R 13	NRSA63J-102X	MG RESISTOR		
	R 14	NRSA63J-820X	MG RESISTOR		
	R 16	NRSA63J-222X	MG RESISTOR		
	R 18	NRSA63J-102X	MG RESISTOR		
	R 19	NRSA63J-472X	MG RESISTOR		
	R 21	NRSA63J-472X	MG RESISTOR		
	R 23	NRSA63J-222X	MG RESISTOR		
	R 31	NRSA63J-103X	MG RESISTOR		
	R 32	NRSA63J-0R0X	MG RESISTOR		
	R 33	NRSA63J-102X	MG RESISTOR		
	R 36	NRSA63J-0R0X	MG RESISTOR		
	R 38	NRSA63J-222X	MG RESISTOR		
	R 39	NRSA63J-222X	MG RESISTOR		
	R 45	NRSA63J-103X	MG RESISTOR		
	R 46	NRSA63J-103X	MG RESISTOR		
	R 56	NRSA63J-152X	MG RESISTOR		
	R 700	NRSA63J-105X	MG RESISTOR		
	R 701	NRSA63J-103X	MG RESISTOR		
	R 702	NRSA63J-105X	MG RESISTOR		
	R 703	NRSA63J-103X	MG RESISTOR		
	R 706	NRSA63J-104X	MG RESISTOR		
	R 708	NRSA63J-101X	MG RESISTOR		
	R 711	QRE141J-100Y	C RESISTOR	10 5% 1/4W	
	R 712	QRE141J-220Y	C RESISTOR	22 5% 1/4W	
	R 713	QRE141J-470Y	C RESISTOR	47 5% 1/4W	
	R 715	QRE141J-470Y	C RESISTOR	47 5% 1/4W	
	R 721	NRSA63J-471X	MG RESISTOR		
	R 723	NRSA63J-471X	MG RESISTOR		
	R 724	NRSA63J-471X	MG RESISTOR		
	R 725	NRSA63J-471X	MG RESISTOR		
	R 726	QRE141J-330Y	C RESISTOR	33 5% 1/4W	
	R 728	NRSA63J-471X	MG RESISTOR		
	R 729	NRSA63J-471X	MG RESISTOR		
	R 731	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 740	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 741	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 742	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 743	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 744	NRSA63J-362X	MG RESISTOR		

■ Electrical parts list (Main board)

Block No. 02

△	Item	Parts number	Parts name	Remarks	Area
	R 746	QRA14CF-3301Y	MF RESISTOR	33 1/4W	
	R 747	NRSA63J-362X	MG RESISTOR		
	R 748	QRA14CF-6800Y	MF RESISTOR	68 1/4W	
	R 750	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 751	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 752	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 753	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 754	NRSA63J-362X	MG RESISTOR		
	R 756	QRA14CF-3301Y	MF RESISTOR	33 1/4W	
	R 757	NRSA63J-362X	MG RESISTOR		
	R 758	QRA14CF-6800Y	MF RESISTOR	68 1/4W	
	R 761	QRA14CF-6200Y	MF RESISTOR	62 1/4W	
	R 762	QRE141J-821Y	C RESISTOR	820 5% 1/4W	
	R 763	NRSA63J-362X	MG RESISTOR		
	R 764	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 765	QRE141J-561Y	C RESISTOR	560 5% 1/4W	
	R 766	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 767	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 768	NRSA63J-103X	MG RESISTOR		
	R 771	QRA14CF-6200Y	MF RESISTOR	62 1/4W	
	R 772	QRE141J-821Y	C RESISTOR	820 5% 1/4W	
	R 773	NRSA63J-362X	MG RESISTOR		
	R 774	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 775	QRE141J-561Y	C RESISTOR	560 5% 1/4W	
	R 776	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 777	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 778	NRSA63J-103X	MG RESISTOR		
	R 782	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 783	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 789	NRSA63J-103X	MG RESISTOR		
	R 792	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 793	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 794	NRSA63J-103X	MG RESISTOR		
	R 795	NRSA63J-103X	MG RESISTOR		
	R 796	NRSA63J-103X	MG RESISTOR		
	R 797	QRE141J-473Y	C RESISTOR	47K 5% 1/4W	
	R 798	NRSA63J-473X	MG RESISTOR		
	R 799	NRSA63J-333X	MG RESISTOR		
	R 801	NRSA63J-750X	MG RESISTOR		
	R 802	NRSA63J-750X	MG RESISTOR		
	R 803	NRSA63J-750X	MG RESISTOR		
	R 804	NRSA63J-750X	MG RESISTOR		
	R 805	NRSA63J-750X	MG RESISTOR		
	R 808	NRSA63J-750X	MG RESISTOR		
	R 831	NRVA63D-750X	RES. C.M		
	R 834	NRVA63D-750X	RES. C.M		
	R 836	NRVA63D-680X	RES. C.M		
	R 838	NRVA63D-680X	RES. C.M		
	R 851	NRSA63J-223X	MG RESISTOR		
	R 852	NRSA63J-223X	MG RESISTOR		
	R 853	NRSA63J-0R0X	MG RESISTOR	COMP	
	R 856	NRSA63J-0R0X	MG RESISTOR	COMP	
	R 863	NRSA63J-102X	MG RESISTOR		
△	R 901	QRL01DJ-683X	OMF RESISTOR	68K 5% 1/1W	
△	R 903	QRE141J-270Y	C RESISTOR	27 5% 1/4W	
	R 905	QRL027J-683	OMF RESISTOR	68K 5% 1/2W	
	R 906	QRE141J-681Y	C RESISTOR	680 5% 1/4W	
△	R 907	QRT022J-R47	OMF RESISTOR	5% 1/2W	
	R 908	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 920	QRZ9037-335	F RESISTOR	3.3M 1/0W	
	R 921	QRL01DJ-470X	OMF RESISTOR	47 5% 1/1W	
	R 952	NRSA63J-103X	MG RESISTOR		
	R 953	NRSA63J-103X	MG RESISTOR		
	R 955	NRSA63J-223X	MG RESISTOR		
	R 956	QRE141J-180Y	C RESISTOR	18 5% 1/4W	
	R 960	NRSA63J-390X	MG RESISTOR		

△	Item	Parts number	Parts name	Remarks	Area
	R 961	NRSA63J-681X	MG RESISTOR		
	R 962	NRSA63J-151X	MG RESISTOR		
	R 965	NRSA63J-104X	MG RESISTOR		
	R 967	NRSA63J-472X	MG RESISTOR		
	R 968	NRSA63J-390X	MG RESISTOR		
	R 969	NRSA63J-271X	MG RESISTOR		
	R 982	NRSA63J-0R0X	MG RESISTOR		
	R 992	QRZ9005-100X	F RESISTOR	10 1/0W	
	R1107	NRSA63J-431X	MG RESISTOR		
	R1500	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R1501	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R1721	QRE141J-100Y	C RESISTOR	10 5% 1/4W	
	R1722	NRSA63J-391X	MG RESISTOR		
	R1724	NRSA63J-101X	MG RESISTOR		
	R1725	NRSA63J-391X	MG RESISTOR		
	R1727	NRSA63J-101X	MG RESISTOR		
	R1728	NRSA63J-100X	MG RESISTOR		
	R8341	NRVA63D-122X	MG RESISTOR		
	S 1	QSW0651-001Z	TACT SWITCH		
	S 2	QSW0651-001Z	TACT SWITCH		
	S 3	QSW0651-001Z	TACT SWITCH		
	S 4	QSW0651-001Z	TACT SWITCH		
	S 5	QSW0651-001Z	TACT SWITCH		
	S 6	QSW0651-001Z	TACT SWITCH		
	S 7	QSW0651-001Z	TACT SWITCH		
	S 802	QSW0986-001	SLIDE SWITCH		
△	T 901	QQS0150-001	SW TRANSF		
	X 1	QAX0667-001Z	RESONATOR I.M		

■ Electrical parts list (Surround audio board) Block No. 03


△	Item	Parts number	Parts name	Remarks	Area
	BK811	E409182-001SM	GRAND TERMINAL		
	C 838	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 839	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 841	QFLC1HJ-222Z	M CAPACITOR	2200PF 5% 50V	
	C 842	QFLC1HJ-222Z	M CAPACITOR	2200PF 5% 50V	
	C 843	QTE1A48-476Z	E.CAPA I/M		
	C 844	QTE1A48-476Z	E.CAPA I/M		
	C 845	QTE1C28-107Z	E CAPACITOR		
	C 846	QTE1C28-107Z	E CAPACITOR		
	C 847	QTE1C28-107Z	E CAPACITOR		
	C 848	QTE1C28-107Z	E CAPACITOR		
	C 849	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 850	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 851	QFLC1HJ-123Z	M CAPACITOR	.012MF 5% 50V	
	C 852	QFLC1HJ-123Z	M CAPACITOR	.012MF 5% 50V	
	C 853	QFLC1HJ-121Z	M CAPACITOR	120PF 5% 50V	
	C 854	QFLC1HJ-121Z	M CAPACITOR	120PF 5% 50V	
	C 855	QFLC1HJ-472Z	M CAPACITOR	4700PF 5% 50V	
	C 856	QFLC1HJ-472Z	M CAPACITOR	4700PF 5% 50V	
	C 857	QFLC1HJ-122Z	M CAPACITOR	1200PF 5% 50V	
	C 858	QFLC1HJ-122Z	M CAPACITOR	1200PF 5% 50V	
	C 859	QTE0J28-477Z	E CAPACITOR		
	C 860	QTE0J28-477Z	E CAPACITOR		
	C 863	QCZ0202-155Z	ML C CAPA I/M	1.5MF	
	C 864	QCZ0202-155Z	ML C CAPA I/M	1.5MF	
	C 866	QFN31HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 867	QFVJ1HJ-224Z	MF CAPACITOR	.22MF 5% 50V	
	C 868	QTE0J28-227Z	E CAPACITOR		
	C 869	QFN31HJ-152Z	M CAPACITOR	1500PF 5% 50V	
	C 871	QFN31HJ-152Z	M CAPACITOR	1500PF 5% 50V	
	C 873	QFLC1HJ-222Z	M CAPACITOR	2200PF 5% 50V	
	C 874	QFLC1HJ-222Z	M CAPACITOR	2200PF 5% 50V	
	C 875	QTE1A48-476Z	E.CAPA I/M		
	C 876	QTE1A48-476Z	E.CAPA I/M		
	C 877	QTE1C28-107Z	E CAPACITOR		
	C 878	QTE1C28-107Z	E CAPACITOR		
	C 879	QTE1C28-107Z	E CAPACITOR		
	C 880	QTE1C28-107Z	E CAPACITOR		
	C 881	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 882	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 883	QFLC1HJ-123Z	M CAPACITOR	.012MF 5% 50V	
	C 884	QFLC1HJ-123Z	M CAPACITOR	.012MF 5% 50V	
	C 885	QFLC1HJ-472Z	M CAPACITOR	4700PF 5% 50V	
	C 886	QFLC1HJ-472Z	M CAPACITOR	4700PF 5% 50V	
	C 887	QFLC1HJ-121Z	M CAPACITOR	120PF 5% 50V	
	C 888	QFLC1HJ-121Z	M CAPACITOR	120PF 5% 50V	
	C 889	QFLC1HJ-122Z	M CAPACITOR	1200PF 5% 50V	
	C 890	QFLC1HJ-122Z	M CAPACITOR	1200PF 5% 50V	
	C 891	QTE0J28-477Z	E CAPACITOR		
	C 892	QTE0J28-477Z	E CAPACITOR		
	C 895	QCZ0202-155Z	ML C CAPA I/M	1.5MF	
	C 897	QTE0J28-227Z	E CAPACITOR		
	C 898	QFVJ1HJ-224Z	MF CAPACITOR	.22MF 5% 50V	
	C 899	QFN31HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 900	QCZ0202-155Z	ML C CAPA I/M	1.5MF	
	C 902	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C 903	QFLC1HJ-102Z	M CAPACITOR	1000PF 5% 50V	
	C1891	QDGB1HK-102Y	C CAPACITOR		
	C1991	QDGB1HK-102Y	C CAPACITOR		
	CN711	QGF1205C1-17	CONNECTOR		
	IC811	NJM4580L	IC		
	IC812	NJM4580L	IC		
	IC813	MN35505-X	IC C M		
	IC821	NJM4580L	IC		
	IC822	NJM4580L	IC		
	IC823	MN35505-X	IC C M		

△	Item	Parts number	Parts name	Remarks	Area
	J 811	QNN0461-001	PIN JACK		
	J 821	QNN0455-001	PIN JACK		
	K 811	QQR0601-001Z	FERRITE BEADS		
	K 812	QQR0601-001Z	FERRITE BEADS		
	K 813	QQR0601-001Z	FERRITE BEADS		
	K 821	QQR0601-001Z	FERRITE BEADS		
	K 822	QQR0601-001Z	FERRITE BEADS		
	K 823	QQR0601-001Z	FERRITE BEADS		
	K 829	QQR0601-001Z	FERRITE BEADS		
	K8291	QQR0601-001Z	FERRITE BEADS		
	Q 811	2SD2144S/VW/-T	TRANSISTOR		
	Q 812	2SD2144S/VW/-T	TRANSISTOR		
	Q 821	2SD2144S/VW/-T	TRANSISTOR		
	Q 822	2SD2144S/VW/-T	TRANSISTOR		
	R 861	QRE141J-103Y	C RESISTOR	10K 5% 1/4W	
	R 862	QRE141J-103Y	C RESISTOR	10K 5% 1/4W	
	R 863	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 864	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 865	QRE141J-561Y	C RESISTOR	560 5% 1/4W	
	R 866	QRE141J-561Y	C RESISTOR	560 5% 1/4W	
	R 867	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 868	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 869	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 870	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 871	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 872	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 873	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 874	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 875	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 876	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 877	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 878	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 881	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 882	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 883	QRE141J-362Y	C RESISTOR	3.6K 5% 1/4W	
	R 884	QRE141J-362Y	C RESISTOR	3.6K 5% 1/4W	
	R 885	QRA14CF-3602Y	MF RESISTOR	36 1/4W	
	R 886	QRA14CF-3602Y	MF RESISTOR	36 1/4W	
	R 887	QRA14CF-1601Y	MF RESISTOR	16 1/4W	
	R 888	QRA14CF-1601Y	MF RESISTOR	16 1/4W	
	R 889	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R 890	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R 891	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 892	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 893	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 894	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 895	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 896	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 897	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 898	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 899	QRE141J-470Y	C RESISTOR	47 5% 1/4W	
	R 909	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 911	QRE141J-100Y	C RESISTOR	10 5% 1/4W	
	R 912	QRE141J-560Y	C RESISTOR	56 5% 1/4W	
	R 913	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 914	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 915	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 916	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 917	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 918	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 919	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 923	QRE141J-103Y	C RESISTOR	10K 5% 1/4W	
	R 924	QRE141J-103Y	C RESISTOR	10K 5% 1/4W	
	R 925	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 926	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 927	QRE141J-561Y	C RESISTOR	560 5% 1/4W	

■ Electrical parts list (Surround audio board) Block No. 03

△	Item	Parts number	Parts name	Remarks	Area
	R 928	QRE141J-561Y	C RESISTOR	560 5% 1/4W	
	R 929	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 930	QRE141J-273Y	C RESISTOR	27K 5% 1/4W	
	R 931	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 932	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 933	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 934	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 935	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 936	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 937	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 938	QRE141J-221Y	C RESISTOR	220 5% 1/4W	
	R 939	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 940	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 943	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 944	QRA14CF-7500Y	MF RESISTOR	75 1/4W	
	R 945	QRE141J-362Y	C RESISTOR	3.6K 5% 1/4W	
	R 946	QRE141J-362Y	C RESISTOR	3.6K 5% 1/4W	
	R 947	QRA14CF-3602Y	MF RESISTOR	36 1/4W	
	R 948	QRA14CF-3602Y	MF RESISTOR	36 1/4W	
	R 949	QRA14CF-1601Y	MF RESISTOR	16 1/4W	
	R 950	QRA14CF-1601Y	MF RESISTOR	16 1/4W	
	R 951	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 954	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 957	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 958	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 959	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 962	QRE141J-470Y	C RESISTOR	47 5% 1/4W	
	R 966	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 967	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 968	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 970	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 971	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 972	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 973	QRE141J-100Y	C RESISTOR	10 5% 1/4W	
	R 974	QRE141J-560Y	C RESISTOR	56 5% 1/4W	
	R 975	QRE141J-470Y	C RESISTOR	47 5% 1/4W	
	R 976	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 977	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 980	QRE141J-470Y	C RESISTOR	47 5% 1/4W	
	R 981	QRE141J-303Y	C RESISTOR	30K 5% 1/4W	
	R 982	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R 983	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R 984	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R 985	QRA14CF-1802Y	MF RESISTOR	18 1/4W	
	R1825	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R1826	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R1845	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	R1846	QRE141J-272Y	C RESISTOR	2.7K 5% 1/4W	
	SP813	VYH7653-001	IC HOLDER		
	SP823	VYH7653-001	IC HOLDER		

Packing materials and accessories parts list



Block No. M4MM
Block No. M5MM

■ Packing parts list

Block No. M4MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
	P 01	LE31017-013A	PACKING CASE	1		60c,60j
		LE31017-014A	PACKING CASE	1		62c,62j
	P 02	GN20021-001A	PACKING PAD(L)	1		
	P 03	GN20022-001A	PACKING PAD(R)	1		
	P 04	QPC06005515P	POLY BAG	1		

■ Accessories parts list

Block No. M5MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
	A 01	LE40892-001A	ERRATA SHEET	1		
	A 02	LET0205-002A	INST BOOK	1	ENG,FRE	60c,62c
		LET0205-001A	INST BOOK	1	ENG	60j,62j
⚠	A 03	QMPE200-183-JC	POWER CORD	1		
	A 04	BT-51028-2	J=REGIST CARD	1		60j,62j
	A 05	YU20333	SAFETY INST.	1		60j,62j
	A 06	QAM0328-001	AV CORD 3P	1		
	A 07	QAM0358-001	COMP.CORD 3P	1		
	A 08	QAM0326-001	1P PLUG CORD(JE	1		
	A 09	EWP302-011W	SIGNAL CORD	2		
	A 10	RM-SXV011J	REMOCON UNIT	1		
	A 11	-----	BATTERY	2		
	A 12	QPC02504015P	POLY BAG	1		
	A 13	BT-52006-1	WARRANTY CARD	1		60c,62c
	A 14	BT-20071B	JVC CENTER LIST	1		

Extention of area column

60j : XV-SA600BK ver.J

60c : XV-SA600BK ver.C

62j : XV-SA602SL ver.J

62c : XV-SA602SL ver.C