

SECTION 5 REPLACEMENT PARTS LIST


SAFETY PRECAUTION

Parts identified by the ⚠ symbol are critical for safety. Replace only with specified part numbers.

5.1 EXPLODED VIEW

5.1.1 PACKING AND ACCESSORY ASSEMBLY <M1>


The instruction manual to be provided with this product will differ according to the destination.




5.1.2 FINAL ASSEMBLY <M2>

BEWARE OF BOGUS PARTS

Parts that do not meet specifications may cause trouble in regard to safety and performance. We recommend that genuine JVC parts be used.



5.1.3 MECHANISM ASSEMBLY <M4>



5.2 REPLACEMENT PARTS LIST

MODEL	MARK	MODEL	MARK	MODEL	MARK
HR-J285EU	A	HR-J595MS	F	HR-J282EU	K
HR-J290EU	B	HR-J295MS	G	HR-J283EU	L
HR-J585EU	C	HR-J595EK	H	HR-J582EU	M
HR-J590EU	D	HR-J295EK	I	HR-J583EU	N
HR-J593EU	E	HR-J293EU	J		

#	REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCEFGHI JKLMN

PACKING AND ACCESSORY ASSEMBLY <M1>					
801	LG-3835RP0075B	INSTRUCTION ASSEMBLY	(EN,GE,FR,IT,DU)	A C	
801	LG-3835RP0075C	INSTRUCTION ASSEMBLY	(PT,GR,SP)	A C	
801	LG-3835RP0075D	INSTRUCTION ASSEMBLY	(SW,DA,FI,NO,GE)	A C	
801	LG-3835RP0075E	INSTRUCTION ASSEMBLY	(EN,GE,FR,IT,DU)	B DE J	
801	LG-3835RP0075F	INSTRUCTION ASSEMBLY	(PT,GR,SP)	B DE J	
801	LG-3835RP0075G	INSTRUCTION ASSEMBLY	(SW,DA,FI,NO,GE)	B DE J	
801	LG-3835RP0075H	INSTRUCTION ASSEMBLY	(FR)	FG	
801	LG-3835RP0075K	INSTRUCTION ASSEMBLY	(EN)	I	
801	LG-3835RP0075L	INSTRUCTION ASSEMBLY	(PO,CZ,HU)	K M	
801	LG-3835RP0075M	INSTRUCTION ASSEMBLY	(EN)	H	
801	LG-3835RP0075N	INSTRUCTION ASSEMBLY	(PO,CZ,HU)	L N	
802	LG-3889R-H768D	BOX	N5 EDJ200P NA3GJX SW3-A 0.858 4	ABCEFGHI JKLMN	
803	LG-3920R-0067A	PACKING	AF999NS 0.02 65 EPS 12 1190 23	ABCEFGHI JKLMN	
804	LG-292-035A	BAG	SOFT(VCP)	ABCD FG K	
804	LG-3889R-H001A	BAG	HDPE 500 500 0.03 VCR MIDI	E HI J LMN	
806	LG-6850R-CAA26	CABLE,COAXIAL	1200MM PAL-PAL DOUBLE SHIELD	ABCEFGHI JKLMN	
808	—	BATTERY,MANGANESE	AAAM(R03) SEOTONG 1-5 V - 1PA	ABCEFGHI JKLMN	
810	LG-6851RP0003A	CABLE ASSY,RF	CABLE ASSY,RF/SCART/RCA USING	ABCEFGHI JKLMN	
821	LG-6850R-SMA21	CABLE,COAXIAL	14PIN 1200MM SCART-SCART DOUB	FG	
900	LG-6711R1P037A	REMOTE CONTROLLER ASSEMBLY	N5 NOR EDJ209P NA3GJX JVC W/S	B D FGHI L N	
900	LG-6711R1P037B	REMOTE CONTROLLER ASSEMBLY	N5 EDJ209P NAE6JX JVC W/O SHO	A C K M	
900	LG-6711R1P037C	REMOTE CONTROLLER ASSEMBLY	N5 EDJ209P NAGNJY JVC W/SHOVV	E J	

FINAL ASSEMBLY <M2>

A00	LG-6721RF0700D	DECK ASSEMBLY,VIDEO	D35(N) DI(2HD, SP ONLY, AHC(X))	AB G JKL	
A00	LG-6721RF0710D	DECK ASSEMBLY,VIDEO	D35(N) DI(2HD, NP, AHC(X), B)	I	
A00	LG-6721RF0750D	DECK ASSEMBLY,VIDEO	D35(N) DI(4HF, PAL, AHC(X), B)	CDEF H MN	
A43	LG-3721R-F253A	PANEL ASSEMBLY,FRONT	EDJ200P (J285EU)	A	
A43	LG-3721R-F253B	PANEL ASSEMBLY,FRONT	EDJ209P (J290EU)	B	
A43	LG-3721R-F253C	PANEL ASSEMBLY,FRONT	EDJ904NS (J595MS)	F	
A43	LG-3721R-F253D	PANEL ASSEMBLY,FRONT	EDJ900NP (J585EU)	C	
A43	LG-3721R-F253E	PANEL ASSEMBLY,FRONT	EDJ209P (J293EU)	J	
A43	LG-3721R-F253F	PANEL ASSEMBLY,FRONT	EDJ900NP (J590EU)	D	
A43	LG-3721R-F253G	PANEL ASSEMBLY,FRONT	EDJ900NP (J593EU)	E	
A43	LG-3721R-F253H	PANEL ASSEMBLY,FRONT	EDJ204S (J295MS)	G	
A43	LG-3721R-F253J	PANEL ASSEMBLY,FRONT	EDJ904NI (J595EK)	H	
A43	LG-3721R-F253K	PANEL ASSEMBLY,FRONT	EDJ200Y (J282EU)	K	
A43	LG-3721R-F253L	PANEL ASSEMBLY,FRONT	EDJ203Y (J283EU)	L	
A43	LG-3721R-F253M	PANEL ASSEMBLY,FRONT	EDJ203NI (J295EK)	I	
A43	LG-3721R-F253N	PANEL ASSEMBLY,FRONT	EDJ903NY (J583EU)	N	
A43	LG-3721R-F253Q	PANEL ASSEMBLY,FRONT	EDJ900NY (J582EU)	M	
A46	LG-3501R-5739A	BOARD ASSEMBLY	JVC DI EC(D) SERIES	B J	
A46	LG-3501R-5739B	BOARD ASSEMBLY	JVC DI EC(D) SERIES	A	
A46	LG-3501R-5739C	BOARD ASSEMBLY	JVC DI EC(D) SERIES	F	
A46	LG-3501R-5739D	BOARD ASSEMBLY	JVC DI EC(D) SERIES	C	
A46	LG-3501R-5739E	BOARD ASSEMBLY	JVC DI EC(D) SERIES	DE	
A46	LG-3501R-5739F	BOARD ASSEMBLY	JVC DI EC(D) SERIES	G	
A46	LG-3501R-5739G	BOARD ASSEMBLY	JVC DI EC(D) SERIES	MN	
A46	LG-3501R-5739H	BOARD ASSEMBLY	JVC DI EC(D) SERIES	H	
A46	LG-3501R-5739J	BOARD ASSEMBLY	JVC DI EC(D) SERIES	KL	
A46	LG-3501R-5739K	BOARD ASSEMBLY	JVC DI EC(D) SERIES	I	
250	LG-3110R-0128C	CASE	TOP(Q280G-B,K),SIDE	E J	
250	LG-3110R-0223G	CASE	TOP(0128 A288G SIDE SCREW 4EA	ABCD FGHI JKLMN	
260	LG-3210R-0023B	FRAME	MAIN (VII-PJT, 60HR)	ABCEFGHI JKLMN	
280	LG-3720R-F193A	PANEL,VIDEO	FRONT(B589G-SILVER)	ABCD FGHI JKLMN	
280	LG-3720R-F193B	PANEL,VIDEO	FRONT(Q280G)	E J	
283	LG-3580R-V031A	DOOR,CASE	CST (VCR) (MONO-B589G-SILVER)	AB G I KL	
283	LG-3580R-V031B	DOOR,CASE	CST (VCR) (MONO-Q280G-B,K)	F	
283	LG-3580R-V031C	DOOR,CASE	CST (VCR) (HIFI-B589G-SILVER)	CD F H MN	
283	LG-3580R-V031D	DOOR,CASE	CST (VCR) (HIFI-Q280G-BK)	E	
284	LG-442-681A	SPRING	DOOR	ABCEFGHI JKLMN	
300	LG-6410RHBV01A	POWER CORD	H03VVH2-F2 X 0.75MM FILTER VOL	HI	
300	LG-6410RCHP03B	POWER CORD	HIT-102/H03VVH2-F (NM) HARNESS	ABCEFGH JKLMN	
320	LG-3720R-D020A	PANEL	DISTRIBUTOR (PAL-1SCART)	A I KL	
320	LG-3720R-D020B	PANEL	DISTRIBUTOR (PAL-SCART MONO)	B G J	
320	LG-3720R-D020C	PANEL	DISTRIBUTOR (PAL-2SCART HI-FI)	DEF H	
320	LG-3720R-D020D	PANEL	DISTRIBUTOR (PAL-1SCART HI-FI)	C	
323	LG-3111R-0089C	CASE ASSEMBLY	PRE-AMP (02-PAL)	ABCEFGHI JKLMN	
330	LG-3550R-Q210A	COVER	BOTTOM(LARGE)	ABCEFGHI JKLMN	
452	LG-353-051A	SCREW	SPECIAL	ABCEFGHI JKLMN	
457	LG-353-051E	SCREW	SPECIAL (3X12)	ABCEFGHI JKLMN	
462	LG-353-136A	SCREW	SPECIAL(FBK) (363S353A)	ABCEFGHI JKLMN	

MECHANISM ASSEMBLY <M4>

A01LG-6723R-0401A DRUM(CIRC) ASSEMBLY D35-2CH SP ONLY (8P2) AB G JKL

#	REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCEFGHI JKLMN
A01	LG-6723R-0401B	DRUM(CIRC) ASSEMBLY	D35-2CH SPIEP (8M2)	I	
A01	LG-6723R-0403C	DRUM(CIRC) ASSEMBLY	D35-6CH PAL (8P6C)	CDEF H MN	
A04	LG-4421R-0008A	BRAKE ASSEMBLY	RS	AB G JKL	
A04	LG-4811RF0038A	BRACKET ASSEMBLY	L/D(S)	ABCEFGHI JKLMN	
A11	LG-4471R-0005A	GEAR ASSY	P3	ABCEFGHI JKLMN	
A12	LG-4471R-0004A	GEAR ASSY	P2	ABCEFGHI JKLMN	
A21	LG-4931R-0047A	HOLDER ASSY	CST	ABCEFGHI JKLMN	
A22	LG-4471R-0006A	GEAR ASSY	RACK FIL	ABCEFGHI JKLMN	
A23	LG-4261R-0023A	ARM ASSY	FIL	ABCEFGHI JKLMN	
A24	LG-4510R-0046A	LEVER	ASSY SWITCH	ABCEFGHI JKLMN	
001	LG-6723R-0304A	DRUM(CIRC) ASSEMBLY	SUB D35-2CH (8P2)	AB G JKL	
001	LG-6723R-0304B	DRUM(CIRC) ASSEMBLY	SUB D35-2CH (8M2)	I	
001	LG-6723R-0306C	DRUM(CIRC) ASSEMBLY	SUB D35-6CH (8P6C)	CDEF H MN	
002	LG-4680R-0005A	MOTOR(MECH)	DRUM I20AL05 SEJIN-SANKYO ICLE	ABCEFGHI JKLMN	
002A	LG-5202R00002C	BRUSH,CARBON	ASSY D33 (TIP+2 SPRING) 1.4,	ABCEFGHI JKLMN	
003	LG-4930R-0284A	HOLDER,SHELF	FP(C)6CH	ABCEFGHI JKLMN	
004	LG-5006R-0034A	CAP	FFC	ABCEFGHI JKLMN	
008	LG-6850R-HG18Z	CABLE,FLAT	P=1.25 FFC UL2896(0.05X0.8) 7	ABCEFGHI JKLMN	
009	LG-4260R-0038A	ARM	TIUP(D35)	ABCEFGHI JKLMN	
010	LG-4810R-0125A	BRACKET	CHASSIS	ABCEFGHI JKLMN	
011	LG-4261R-0022A	ARM ASSY	TENSION(D35)	ABCEFGHI JKLMN	
012	LG-3041R-0037A	BASE ASSY	P2	ABCEFGHI JKLMN	
013	LG-3041R-0038A	BASE ASSY	P3	ABCEFGHI JKLMN	
014	LG-3041R-0039A	BASE ASSY	P4	ABCEFGHI JKLMN	
015	LG-5870R-0005A	OPENER	LID(D35)	ABCEFGHI JKLMN	
016	LG-3041R-0036A	BASE ASSEMBLY	A/C HEAD (ALPS)	ABCEFGHI JKLMN	
017	LG-4408R-0003A	REEL	S	ABCEFGHI JKLMN	
018	LG-4970R-0140A	SPRING	COIL RS D35	ABCEFGHI JKLMN	
019	LG-4421R-0008A	BRAKE ASSEMBLY	RS	CDEF HI MN	
020	LG-4970R-0128A	SPRING	COIL D35 (TB)	ABCEFGHI JKLMN	
021	LG-4421R-0006A	BRAKE ASSY	T	ABCEFGHI JKLMN	
022	LG-6520D000002A	HEAD(CIRC)	D35 FE ST FE HEAD	ABCEFGHI JKLMN	
023	LG-3040R-0057A	BASE	LOADING	ABCEFGHI JKLMN	
024	LG-4261R-0029A	ARM ASSEMBLY	IDLER (N)	ABCEFGHI JKLMN	
025	LG-4810R-0118A	BRACKET	L/D(S)	ABCEFGHI JKLMN	
026	LG-4680R-D002A	MOTOR(MECH)	LOADING MDB2B66 SANKYO D35 ASP	ABCEFGHI JKLMN	
027	LG-4470R-0093A	GEAR	WHEEL	ABCEFGHI JKLMN	
028	LG-4408R-0004A	REEL	T	ABCEFGHI JKLMN	
029	LG-4261R-0019A	ARM ASSY	PINCH	ABCEFGHI JKLMN	
030	LG-4510R-0043A	LEVER	TIUP	ABCEFGHI JKLMN	
031	LG-4970R-0123A	SPRING	COIL TENSION(D35)	ABCEFGHI JKLMN	
032	LG-3141R-0040A	CHASSIS ASSY	D35	ABCEFGHI JKLMN	
051	LG-4400R-0005A	BELT	CAPSTAN	ABCEFGHI JKLMN	
052	LG-4680R-A007A	MOTOR(MECH)	CAPSTAN F2QVB06 SANKYO D35 ASR	ABCEFGHI JKLMN	
052A	LG-4980R-0023A	SUPPORTER	CAPSTAN(D35)	ABCEFGHI JKLMN	
054	LG-4470R-0100A	GEAR	RACK FIL	ABCEFGHI JKLMN	
054A	LG-4970R-0124B	SPRING	COIL D35 (RACK FIL)	ABCEFGHI JKLMN	
055	LG-4470R-0097A	GEAR	DRIVE(D35)	ABCEFGHI JKLMN	
056	LG-4470R-0096A	GEAR	CAM(D35)	ABCEFGHI JKLMN	
058	LG-4421R-0007A	BRAKE ASSY	CAPSTAN	ABCEFGH JKLMN	
060	LG-4510R-0040A	LEVER	F/R(D35)	ABCEFGHI JKLMN	
061	LG-4265R-0006A	CLUTCH ASSEMBLY	D35 (N)	ABCEFGHI JKLMN	
064	LG-4470R-0098A	GEAR	SECTOR(D35)	ABCEFGHI JKLMN	
065	LG-4261R-0021A	ARM ASSY	P3	ABCEFGHI JKLMN	
066	LG-4970R-0122A	SPRING	COIL D35	ABCEFGHI JKLMN	
067	LG-4470R-0095A	GEAR	P3	ABCEFGHI JKLMN	
068	LG-4470R-0094A	GEAR	P2	ABCEFGHI JKLMN	
069	LG-4970R-0122A	SPRING	COIL D35	ABCEFGHI JKLMN	
070	LG-4261R-0020A	ARM ASSY	P2	ABCEFGHI JKLMN	
076	LG-4510R-0047A	LEVER	SPRING	ABCEFGHI JKLMN	
077	LG-3300R-M116A	PLATE	SLIDER	ABCEFGHI JKLMN	
078	LG-4510R-0041A	LEVER	TENSION	ABCEFGHI JKLMN	
079	LG-3040R-0056A	BASE	TENSION(D35)	ABCEFGHI JKLMN	
100	LG-3301R-M022A	PLATE ASSEMBLY	TOP	ABCEFGHI JKLMN	
102	LG-4970R-0130A	SPRING	COIL D35 (STOPPER)	ABCEFGHI JKLMN	
103	LG-4930R-0276A	HOLDER,SHELF	SIDE(L)	ABCEFGHI JKLMN	
105	LG-4930R-0274A	HOLDER,SHELF	CST	ABCEFGHI JKLMN	
106	LG-4930R-0275A	HOLDER,SHELF	SIDE(R)	ABCEFGHI JKLMN	
107	LG-4510R-0044A	LEVER	STOPPER	ABCEFGHI JKLMN	
109	LG-5870R-0004A	OPENER	DOOR	ABCEFGHI JKLMN	
110	LG-4260R-0035A	ARM	FIL(L)	ABCEFGHI JKLMN	
112	LG-3070R-0002A	BODY	FIL	ABCEFGHI JKLMN	
113	LG-4970R-0127A	SPRING	COIL D35 (FIL(R))	ABCEFGHI JKLMN	
114	LG-4260R-0036A	ARM	FIL(R)	ABCEFGHI JKLMN	
115	LG-4510R-0042A	LEVER	SWITCH	ABCEFGHI JKLMN	
116	LG-4970R-0138A	SPRING	COIL D35 SWITCH	ABCEFGHI JKLMN	
117	LG-3300R-M137A	PLATE	SPRING CST	ABCEFGHI JKLMN	
401	LG-1MEC0261518	SCREW MACHINE,PAN HEAD SPR W	D2.6 L4.5 MSWR3/FZY	ABCEFGHI JKLMN	
402	LG-1MP0261418	SCREW MACHINE,PAN HEAD	D2.6 L4.0 MSWR3/FZY	ABCEFGHI JKLMN	
405	LG-1SZ2R-0031B	SCREW,DRAWING	D2.6 L5.8 SWRCH16A/FZY TAP	ABCEFGHI JKLMN	
406	LG-1MEC0302018	PAN HEAD MACHINE SCREW S/W +	D3.0 L6.0 MSWR3/FZY	ABCEFGHI JKLMN	
409	LG-1SZ2R-0032B	SCREW,DRAWING	D2.6 L5.0 SWRCH18A/FZY TAP	ABCEFGHI JKLMN	
410	LG-1APF0262218	SCREW TAP TITE(B),PAN HEAD	D2.6 L6.8 MSWR3/FZY	ABCEFGHI JKLMN	
517	LG-1WZZR-0004D	WASHER	STOPPER	ABCEFGHI JKLMN	
518	LG-1WZZR-0004A	WASHER	STOPPER	ABCEFGHI JKLMN	

MODEL	MARK	MODEL	MARK	MODEL	MARK
HR-J285EU	A	HR-J595MS	F	HR-J282EU	K
HR-J290EU	B	HR-J295MS	G	HR-J283EU	L
HR-J585EU	C	HR-J595EK	H	HR-J582EU	M
HR-J590EU	D	HR-J295EK	I	HR-J583EU	N
HR-J593EU	E	HR-J293EU	J		

Δ REF. No. PART No. PART NAME, DESCRIPTION SPECIFICATION ABCDEFGHI JKLMN

MAIN BOARD ASSEMBLY <03>

PBM00	LG-6871R-5739A	PWB(PCB) ASSEMBLY,TOTAL	EDJ208P (PCB ASSY)	B	J
PBM00	LG-6871R-5739B	PWB(PCB) ASSEMBLY,TOTAL	EDJ200P (PCB ASSY)	A	
PBM00	LG-6871R-5739C	PWB(PCB) ASSEMBLY,TOTAL	EDJ904NS (PCB ASSY)	F	
PBM00	LG-6871R-5739D	PWB(PCB) ASSEMBLY,TOTAL	EDJ900NP (PCB ASSY)	C	
PBM00	LG-6871R-5739E	PWB(PCB) ASSEMBLY,TOTAL	EDJ908NP (PCB ASSY)	DE	
PBM00	LG-6871R-5739F	PWB(PCB) ASSEMBLY,TOTAL	EC(D) SERIES (PCB ASSY)	G	
PBM00	LG-6871R-5739G	PWB(PCB) ASSEMBLY,TOTAL	EDJ SERIES (HIFI)	MN	
PBM00	LG-6871R-5739H	PWB(PCB) ASSEMBLY,TOTAL	EDJ904NI (HIFI)	H	
PBM00	LG-6871R-5739J	PWB(PCB) ASSEMBLY,TOTAL	EDJ SERIES (MONO)	KL	
PBM00	LG-6871R-5739K	PWB(PCB) ASSEMBLY,TOTAL	EDJ203I (MONO)	I	
IC101	STR-A6351	IC,POWER MANAGEMENT	STR-A6351 SANKEN 8 DIP ST SMPS	ABCDEFGHI JKLMN	
Δ IC102	LTV-817B	SENSOR	LTV-817B, PHOTO COUPLER(LITEON)	ABCDEFGHI JKLMN	
IC103	LG-DIKE431000A	IC,KEC	KU431 3 PIN TP	ABCDEFGHI JKLMN	
IC201	LG-0ILNRS4007A	IC,LINEAR	LA70100M SANYO 30 SOP ST SECAM	FG	
IC301	LG-0ILNRS4005A	IC,LINEAR	LA71750AM SANYO 100 QFP TRAY A	ABCDEFGHI JKLMN	
IC501	LG-0IMCRH014B	IC,MICRO CONTROLLER	HD6432197SA06F HITACHI 112 QFP	KL	
IC501	LG-0IMCRH019A	IC,MICRO CONTROLLER	HD6432197SA09F HITACHI 112P QF	KL	
IC503	LG-0IAL241600B	IC,ATMEL	AT24C16 - - -	ABCDEFGHI JKLMN	
IC504	LG-DIKE731010A	IC,KEC	KU47031P 3P 3.1V RESET(TAPING)	ABCDEFGHI JKLMN	
IC505	LG-DIKE704200B	IC,KEC	KU47042P 3P 4.2V RESET(TAPING)	ABCDEFGHI JKLMN	
IC751	LG-0IIT341700B	IC,ITT	MSP3417D-QG QFP44 BK NICAM+2	CDEF H MN	
IC7V1	LG-0ILNRMN001A	IC,LINEAR	SDA5650 MICRONAS 14 DIP ST VPS	B DE J	
IC801	LG-0IPH980500A	IC,PHILIPS	TDAP605H QFP44 BK HIFI AMP+HIF	CDEF H MN	
IC901	MM1443XJ	IC,MITSUMI	MM1443XJ SSOP-34 TP CANAL SW	B G J	
Q151	LG-0TR127309AA	TRANSISTOR	KT41273-TP-Y (KTA966A)KEC	ABCDEFGHI JKLMN	
Q152	LG-0TR127309AA	TRANSISTOR	KT41273-TP-Y (KTA966A)KEC	ABCDEFGHI JKLMN	
Q154	LG-0TR126809BA	TRANSISTOR,BIPOLARS	KT41268-BL TP KEC	ABCDEFGHI JKLMN	
Q155	LG-0TR320509AB	TRANSISTOR	KTC3205-TP-Y (KTC2236A)KEC	ABCDEFGHI JKLMN	
Q157	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q162	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q163	LG-0TR120109AC	TRANSISTOR	SRC1201 TP AUK TQ92 4.7K,4.7K	ABCDEFGHI JKLMN	
Q164	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q165	LG-0TR220309AF	TRANSISTOR	SRA2203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q166	LG-0TR127309AA	TRANSISTOR	KT41273-TP-Y (KTA966A)KEC	ABCDEFGHI JKLMN	
Q301	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q302	LG-0TR198009CA	TRANSISTOR	2SA1980G TP AUK TQ92	ABCDEFGHI JKLMN	
Q303	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q304	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q305	LG-0TR198009CA	TRANSISTOR	2SA1980G TP AUK TQ92	ABCDEFGHI JKLMN	
Q306	LG-0TR534409AA	TRANSISTOR	2SC5344Y TP	ABCDEFGHI JKLMN	
Q307	LG-0TR198009CA	TRANSISTOR	2SA1980G TP AUK TQ92	B DEFGH J	
Q308	LG-0TR198009CA	TRANSISTOR	2SA1980G TP AUK TQ92	ABCDEFGHI JKLMN	
Q309	LG-0TR198009CA	TRANSISTOR	2SA1980G TP AUK TQ92	ABCDEFGHI JKLMN	
Q501	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q502	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q503	LG-0TR127309AA	TRANSISTOR	KT41273-TP-Y (KTA966A)KEC	ABCDEFGHI JKLMN	
Q504	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q514	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q515	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q5P2	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q5P3	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q5P4	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q5P5	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q5S1	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Q751	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	FG	
Q901	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q902	LG-0TR220309AF	TRANSISTOR	SRA2203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q903	LG-0TR120309AE	TRANSISTOR	SRC1203 TP AUK TQ92 22K,22K	ABCDEFGHI JKLMN	
Q906	LG-0TR534309BA	TRANSISTOR	2SC5343-L TP AUK TQ92	ABCDEFGHI JKLMN	
Δ BD101	S1WB460	DIODE	S1WB460(1A 600V) SHIDENKEN	ABCDEFGHI JKLMN	
D102	EG01CW	DIODE,RECTIFIER	EG01CW(R-FORM 5MM) TP SANKEN	ABCDEFGHI JKLMN	
D103	LG-0DR180209AA	DIODE,RECTIFIER	ERA18-02KFRB TP FUJI D0204AL 2	ABCDEFGHI JKLMN	
D104	1SS133DIODE,SWITCHING		1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D105	LG-0DR104009BA	DIODE,RECTIFIER	RL104F TP RECTRON NON 400V 1A	ABCDEFGHI JKLMN	
D106	1N5822DIODE,RECTIFIER		1N5822 BK RECTRON D0201AD 40V	ABCDEFGHI JKLMN	
D109	LG-0DR202000AB	DIODE,RECTIFIER	HER202 BK RECTRON NON 100V 2A	ABCDEFGHI JKLMN	
D155	LG-0DR104009AB	DIODE,RECTIFIER	RL104 R. TP GULF SEMICONDUCTOR	ABCDEFGHI JKLMN	
D156	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D159	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D160	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D301	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D502	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D509	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D901	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D902	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D903	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	ABCDEFGHI JKLMN	
D904	1SS133	DIODE,SWITCHING	1SS133 DETECT,SW TP	H	
ZD151	MTZ13CT-77	DIODE,ZENERS	MTZ13CT TP ROHM-K	ABCDEFGHI JKLMN	

#	REF. No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCDEFGHI JKLMN
	ZD503	LG-0DZ622608CA	DIODE,ZENER	GDZJ6.2C 26MM TP GRANDE D034 0	ABCDEFGHI JKLMN
	ZD801	UZ5.6BSB-T2	DIODE,ZENER	UZ-5.6BSB 26MM TP PYUNG CHANG	CDEF H MN
	ZD802	UZ5.6BSB-T2	DIODE,ZENER	UZ-5.6BSB 26MM TP PYUNG CHANG	CDEF H MN
	ZD803	MTZ13AT-77	DIODE,ZENER	MTZ13A TP ROHM-K	CDEF H MN
	ZD804	MTZ13AT-77	DIODE,ZENER	MTZ13A TP ROHM-K	CDEF H MN
▲	C101	LG-624-088F	CAPACITOR,DRAWING	PCX2 275V 0.1UF,M (PILKO)	ABCDEFGHI J
▲	C101	LG-624-088L	CAPACITOR,DRAWING	436D SUNIL ELECTRONICS 0.1UF/2	KL MN
▲	C102	LG-624-088F	CAPACITOR,DRAWING	PCX2 275V 0.1UF,M (PILKO)	ABCDEFGHI J
▲	C102	LG-624-088L	CAPACITOR,DRAWING	436D SUNIL ELECTRONICS 0.1UF/2	KL MN
	C103	LG-0CE476CU611	CAPACITOR,AL.ELECTROLYTIC	47UF SHL,SD 400V M FL BK7.5	ABCDEFGHI JKLMN
	C105	LG-0CQ1031Y519	CAPACITOR,POLYESTER	0.01UF D 630V K PE NI TP	ABCDEFGHI JKLMN
	C106	LG-624-087B	CAPACITOR	HIGH-VOL 100P/1KV SMPS SAMHWA	ABCDEFGHI JKLMN
	C109	QET41HM-106	CAPACITOR,FIXED ELECTROLYTIC	10M SRA50V M FM5 TP(5)	ABCDEFGHI JKLMN
▲	C112	LG-0CG3320U630	CAPACITOR,SEMI CERAMIC	3300 PF 400V M E R(NK,AD,SD)	ABCDEFGHI JKLMN
▲	C113	LG-0CG1010U510	CAPACITOR,SEMI CERAMIC	100 PF 400V K B R (NK,AD,SD)	ABCDEFGHI JKLMN
	C114	LG-0CQ4732K409	CAPACITOR,FIXED FILM	0.047UF S 50V J PE TP	ABCDEFGHI JKLMN
	C115	LG-624-085D	CAPACITOR	CE 47UF/50V KME (SMPS)	ABCDEFGHI JKLMN
	C116	LG-0CE108BF630	CAPACITOR,FIXED ELECTROLYTIC	1000UF KME 16V M FM5 BULK	ABCDEFGHI JKLMN
	C117	LG-624-082H	CAPACITOR	CE 1000UF/10V SHL(10*12.5)TP	ABCDEFGHI JKLMN
	C120	LG-0CE477BH630	CAPACITOR,AL.ELECTROLYTIC	470UF KME TYPE 25V M FM5 BULK	ABCDEFGHI JKLMN
	C121	LG-0CE227CH618	CAPACITOR,FIXED ELECTROLYTIC	220UF SHL,SD 25V 20% FL TP 5	ABCDEFGHI JKLMN
	C127	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	ABCDEFGHI JKLMN
	C135	LG-0CN4710K518	CAPACITOR TUBULA(HIGH DIELE)	470P 50V K B TA26	ABCDEFGHI JKLMN
	C153	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C190	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C201	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C202	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C203	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	FG
	C204	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	FG
	C205	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	FG
	C206	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C207	QET41HM-474	CAPACITOR,ELECTROLYTIC	0.47M SRA50V M FM5 TP(5)	FG
	C208	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C209	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C210	QET41HM-474	CAPACITOR,ELECTROLYTIC	0.47M SRA50V M FM5 TP(5)	FG
	C211	LG-0CN2220F668	CAPACITOR,TUBULAR(HIGH DIELEC)	2200P 16V M X TA26	FG
	C212	LG-0CN2220F668	CAPACITOR,TUBULAR(HIGH DIELEC)	2200P 16V M X TA26	FG
	C213	QET41HM-225	CAPACITOR,FIXED ELECTROLYTIC	2.2UF SRA,SS 50V 20% FM5 TP 5	FG
	C214	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C215	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	FG
	C216	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	FG
	C301	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	ABCDEFGHI JKLMN
	C302	QET41CM-226	CAPACITOR,ELECTROLYTIC	22M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C303	LG-0CN1220F668	CAPACITOR TUBULA(HIGH DIELE)	1200P 16V M X TA26	ABCDEFGHI JKLMN
	C304	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C305	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCDEFGHI JKLMN
	C306	LG-0CN1220F668	CAPACITOR TUBULA(HIGH DIELE)	1200P 16V M X TA26	ABCDEFGHI JKLMN
	C307	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCDEFGHI JKLMN
	C308	LG-0CQ1532K409	CAPACITOR,FIXED FILM	0.015UF S 50V J PE TP	ABCDEFGHI JKLMN
	C309	LG-0CN1210K518	CAPACITOR TUBULA(HIGH DIELE)	120P 50V K B TA26	ABCDEFGHI JKLMN
	C310	LG-0CQ1032K409	CAPACITOR,POLYESTER(MYLAR)	0.01UF S 50V J PE TP	ABCDEFGHI JKLMN
	C311	LG-0CE4765K618	CAPACITOR,AL.ELECTROLYTIC	47UF SR,SV 50V M FL TP 5	ABCDEFGHI JKLMN
	C312	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCDEFGHI JKLMN
	C313	LG-0CQ2232L559	CAPACITOR,POLYESTER	0.022UF S 63V K PP NI TP5	ABCDEFGHI JKLMN
	C314	QET41CM-226	CAPACITOR,ELECTROLYTIC	22M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C315	LG-0CE2253K636	CAPACITOR,FIXED ELECTROLYTIC	2.2UF SRE,SE 50V 20% FM5 BP(D)	ABCDEFGHI JKLMN
	C316	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C317	LG-0CN8220F668	CAPACITOR,TUBULAR(HIGH DIELEC)	8200P 16V M X TA26	ABCDEFGHI JKLMN
	C318	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCDEFGHI JKLMN
	C319	LG-0CQ1032K409	CAPACITOR,POLYESTER(MYLAR)	0.01UF S 50V J PE TP	ABCDEFGHI JKLMN
	C320	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCDEFGHI JKLMN
	C321	LG-0CX6800K408	CAPACITOR TUBULA(T.C)	68P 50V J SL TA26	ABCDEFGHI JKLMN
	C322	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C323	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C324	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	ABCDEFGHI JKLMN
	C325	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C326	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCDEFGHI JKLMN
	C327	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCDEFGHI JKLMN
	C328	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCDEFGHI JKLMN
	C329	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCDEFGHI JKLMN
	C330	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCDEFGHI JKLMN
	C331	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C333	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C334	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	ABCDEFGHI JKLMN
	C335	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCDEFGHI JKLMN
	C336	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCDEFGHI JKLMN
	C337	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCDEFGHI JKLMN
	C338	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	ABCDEFGHI JKLMN
	C339	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCDEFGHI JKLMN
	C340	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	ABCDEFGHI JKLMN
	C341	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	ABCDEFGHI JKLMN
	C342	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCDEFGHI JKLMN
	C343	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	ABCDEFGHI JKLMN

MODEL	MARK	MODEL	MARK	MODEL	MARK
HR-J285EU	A	HR-J595MS	F	HR-J282EU	K
HR-J290EU	B	HR-J295MS	G	HR-J283EU	L
HR-J585EU	C	HR-J595EK	H	HR-J582EU	M
HR-J590EU	D	HR-J295EK	I	HR-J583EU	N
HR-J593EU	E	HR-J293EU	J		

# Δ REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCEFGHI JKLMN	# Δ REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCEFGHI JKLMN
C344	LG-0CN1010K518	CAPACITOR,TUBULAR(HIGH DIELEC)	100P 50V K B TA26	ABCEDEFGHI JKLMN	C5P2	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN
C345	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	ABCEDEFGHI JKLMN	C5R1	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	ABCEDEFGHI JKLMN
C346	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C5R2	LG-0CN6810K518	CAPACITOR TUBULA(HIGH DIELE)	680P 50V K B TA26	ABCEDEFGHI JKLMN
C347	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCEDEFGHI JKLMN	C5S1	LG-0CX4300K408	CAPACITOR TUBULA(T.C)	43P 50V J SL TA26	ABCEDEFGHI JKLMN
C348	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCEDEFGHI JKLMN	C5S3	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	ABCEDEFGHI JKLMN
C349	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C701	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	ABCEDEFGHI JKLMN
C353	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCEDEFGHI JKLMN	C703	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	FG
C355	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C704	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN
C356	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCEDEFGHI JKLMN	C705	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN
C357	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCEDEFGHI JKLMN	C706	LG-0CE4775C618	CAPACITOR,AL.ELECTROLYTIC	470UF SR,SV 6.3V M FL TP 5	ABCEDEFGHI JKLMN
C358	LG-0CX6800K408	CAPACITOR TUBULA(T.C)	68P 50V J SL TA26	ABCEDEFGHI JKLMN	C707	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN
C359	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	ABCEDEFGHI JKLMN	C710	LG-0CX6800K408	CAPACITOR TUBULA(T.C)	68P 50V J SL TA26	ABCEDEFGHI JKLMN
C360	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C711	LG-0CX3300K408	CAPACITOR TUBULA(T.C)	33P 50V J SL TA26	ABCEDEFGHI JKLMN
C361	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	ABCEDEFGHI JKLMN	C712	LG-0CX5R600K508	CAPACITOR TUBULA(T.C)	5.6PF 50V K SL TA26	ABCEDEFGHI JKLMN
C362	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C713	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN
C363	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN	C714	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN
C364	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C751	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	CDEF H MN
C365	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C752	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	CDEF H MN
C366	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C753	LG-0CX5600K408	CAPACITOR,TUBULAR(T.C)	56P 50V J SL TA26	CDEF H MN
C367	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C754	LG-0CX5600K408	CAPACITOR,TUBULAR(T.C)	56P 50V J SL TA26	CDEF H MN
C368	LG-0CQ8224K409	CAPACITOR,FIXED FILM	0.0082UF TE 50V 5% PE TP5	ABCEDEFGHI JKLMN	C755	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	CDEF H MN
C369	LG-0CN1010K518	CAPACITOR,TUBULAR(HIGH DIELEC)	100P 50V K B TA26	ABCEDEFGHI JKLMN	C756	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	CDEF H MN
C370	LG-0CN8200K419	CAPACITOR,FIXED TUBULAR(High d	82PF D 50V 5% B(Y5P) TA52	ABCEDEFGHI JKLMN	C757	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	CDEF H MN
C371	LG-0CN8200K419	CAPACITOR,FIXED TUBULAR(High d	82PF D 50V 5% B(Y5P) TA52	ABCEDEFGHI JKLMN	C758	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C372	LG-0CN8200K419	CAPACITOR,FIXED TUBULAR(High d	82PF D 50V 5% B(Y5P) TA52	ABCEDEFGHI JKLMN	C759	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C373	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C760	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	CDEF H MN
C375	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C761	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	CDEF H MN
C500	LG-0CE4775C638	CAPACITOR,FIXED ELECTROLYTIC	470UF SR,SV 6.3V 20% FM5 TP 5	B DE J	C764	LG-0CN1520F668	CAPACITOR,TUBULAR(HIGH DIELEC)	1500P 16V M X TA26	CDEF H MN
C500	LG-624-074A	CAPACITOR	SUPER CAP 0.047F/5.5V T/P S/S	A C FGH JKLMN	C765	LG-0CN1520F668	CAPACITOR,TUBULAR(HIGH DIELEC)	1500P 16V M X TA26	CDEF H MN
C501	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C766	QET41HM-335	CAPACITOR,FIXED ELECTROLYTIC	3.3UF SRA,SS 50V 20% FM5 TP 5	CDEF H MN
C502	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C769	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C503	QET40JM-227	CAPACITOR,ELECTROLYTIC	220M SRA 6.3V M FM5 TP(5)	ABCEDEFGHI JKLMN	C770	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN
C504	QET40JM-227	CAPACITOR,ELECTROLYTIC	220M SRA 6.3V M FM5 TP(5)	ABCEDEFGHI JKLMN	C771	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	CDEF H MN
C505	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C772	LG-0CC0500K015	CAPACITOR,CERAMIC(TEMP COMP)	5P 50V C NP0 TR	CDEF H MN
C506	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	ABCEDEFGHI JKLMN	C773	LG-0CC0800K015	CAPACITOR CERAMIC(TEMP COMP)	8P 50V C NP0 TS	CDEF H MN
C508	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN	C790	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN
C509	LG-0CC2200K415	CAPACITOR,CERAMIC(TEMP COMP)	22P 50V J NP0 TS	ABCEDEFGHI JKLMN	C7M2	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	ABCEDEFGHI JKLMN
C510	QET40JM-227	CAPACITOR,ELECTROLYTIC	220M SRA 6.3V M FM5 TP(5)	ABCEDEFGHI JKLMN	C7M3	LG-0CX2700K408	CAPACITOR TUBULA(T.C)	27P 50V J SL TA26	ABCEDEFGHI JKLMN
C511	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C7M6	LG-0CX2700K408	CAPACITOR TUBULA(T.C)	27P 50V J SL TA26	ABCEDEFGHI JKLMN
C512	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C7S1	QET41CM-336	CAPACITOR,ELECTROLYTIC	33M SRA 16V M FM5 TP(5)	FG
C513	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C7V1	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	B DE J
C514	LG-0CC1200K415	CAPACITOR,CERAMIC(TEMP COMP)	12P 50V J NP0 TS	ABCEDEFGHI JKLMN	C7V2	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	B DE J
C515	LG-0CC1500K415	CAPACITOR,CERAMIC(TEMP COMP)	15P 50V J NP0 TS	ABCEDEFGHI JKLMN	C7V3	QET41HM-105	CAPACITOR,ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	B DE J
C516	LG-0CN223AK948	CAPACITOR,TUBULAR(HIGH DIELEC)	0.022UF 50V Z F TA26 S	ABCEDEFGHI JKLMN	C7V4	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	B DE J
C518	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN	C7V5	LG-0CN4730K948	CAPACITOR,FIXED TUBULAR(High d	0.047UF D 50V 80%,-20% F(Y5V)	B DE J
C519	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	ABCEDEFGHI JKLMN	C805	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	CDEF H MN
C520	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C806	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	CDEF H MN
C523	QET41HM-225	CAPACITOR,FIXED ELECTROLYTIC	2.2UF SRA,SS 50V 20% FM5 TP 5	ABCEDEFGHI JKLMN	C807	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	CDEF H MN
C524	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	ABCEDEFGHI JKLMN	C808	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	CDEF H MN
C525	QET40JM-227	CAPACITOR,ELECTROLYTIC	220M SRA 6.3V M FM5 TP(5)	ABCEDEFGHI JKLMN	C809	LG-0CN1040K948	CAPACITOR,FIXED TUBULAR(High d	0.1UF D 50V 80%,-20% F(Y5V) TA	CDEF H MN
C526	LG-0CE4764J638	CAPACITOR,AL.ELECTROLYTIC	47UF SRA,SS 35V M FM5 TP 5	ABCEDEFGHI JKLMN	C810	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C527	LG-0CN2210K518	CAPACITOR TUBULA(HIGH DIELE)	220P 50V K B TA26	ABCEDEFGHI JKLMN	C811	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C533	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C813	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C534	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	ABCEDEFGHI JKLMN	C814	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C535	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	ABCEDEFGHI JKLMN	C817	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C543	LG-0CN2220F668	CAPACITOR,TUBULAR(HIGH DIELEC)	2200P 16V M X TA26	ABCEDEFGHI JKLMN	C818	QET41HM-475	CAPACITOR,FIXED ELECTROLYTIC	4.7UF SRA,SS 50V 20% FM5 TP 5	CDEF H MN
C544	LG-0CQ4732K409	CAPACITOR,FIXED FILM	0.047UF S 50V J PE TP	ABCEDEFGHI JKLMN	C819	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C545	LG-0CN3330K518	CAPACITOR,FIXED TUBULAR(High d	0.033UF 50V K B TA26	ABCEDEFGHI JKLMN	C820	LG-0CQ6822K409	CAPACITOR,POLYESTER(MYLAR)	6800PF S 50V J PE TP	CDEF H MN
C546	LG-0CE4764J638	CAPACITOR,AL.ELECTROLYTIC	47UF SRA,SS 35V M FM5 TP 5	ABCEDEFGHI JKLMN	C821	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	CDEF H MN
C547	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN	C822	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C551	LG-0CQ3332K409	CAPACITOR,FIXED FILM	0.033UF S 50V J PE TP	ABCEDEFGHI JKLMN	C823	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C552	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y TA26	ABCEDEFGHI JKLMN	C824	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C561	QET40JM-227	CAPACITOR,ELECTROLYTIC	220M SRA 6.3V M FM5 TP(5)	ABCEDEFGHI JKLMN	C825	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	CDEF H MN
C564	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C826	LG-0CQ6822K409	CAPACITOR,POLYESTER(MYLAR)	6800PF S 50V J PE TP	CDEF H MN
C567	LG-0CN1020K518	CAPACITOR TUBULA(HIGH DIELE)	1000P 50V K B TA26	ABCEDEFGHI JKLMN	C827	QET41CM-106	CAPACITOR,ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	CDEF H MN
C570	LG-0CC1500K415	CAPACITOR,CERAMIC(TEMP COMP)	15P 50V J NP0 TS	ABCEDEFGHI JKLMN	C828	QET41CM-476	CAPACITOR,ELECTROLYTIC	47M SRA/SS 16V M FM5 TP(5)	CDEF H MN
C571	LG-0CC1500K415	CAPACITOR,CERAMIC(TEMP COMP)	15P 50V J NP0 TS	ABCEDEFGHI JKLMN	C829	LG-0CN1030F678	CAPACITOR TUBULA(HIGH DIELE)	0.01M 16V M Y	

MODEL	MARK	MODEL	MARK	MODEL	MARK
HR-J285EU	A	HR-J595MS	F	HR-J282EU	K
HR-J290EU	B	HR-J295MS	G	HR-J283EU	L
HR-J585EU	C	HR-J595EK	H	HR-J582EU	M
HR-J590EU	D	HR-J295EK	I	HR-J583EU	N
HR-J593EU	E	HR-J293EU	J		

#	REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	AB	C	D	E	F	G	H	I	J	K	L	M	N
C917		LG-0CX2700K408	CAPACITOR TUBULA(T.C)	27P 50V JSL TA26	B	DE	F	G	H	J							
C920		LG-0CN1040K948	CAPACITOR, FIXED TUBULAR(High d	0.1UF D 50V 80%, -20% F(Y5V) TA	AB	C	D	E	F	G	H	I	J	K	L	M	N
C921		LG-0CN1040K948	CAPACITOR, FIXED TUBULAR(High d	0.1UF D 50V 80%, -20% F(Y5V) TA	AB	C	D	E	F	G	H	I	J	K	L	M	N
C952		LG-0CN1040K948	CAPACITOR, FIXED TUBULAR(High d	0.1UF D 50V 80%, -20% F(Y5V) TA	B	G	J										
C956		QET41HM-105	CAPACITOR, ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	AB	C	D	E	F	G	H	I	J	K	L	M	N
C957		LG-0CX2700K408	CAPACITOR TUBULA(T.C)	27P 50V JSL TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
C960		LG-0CN1040K948	CAPACITOR, FIXED TUBULAR(High d	0.1UF D 50V 80%, -20% F(Y5V) TA	AB	C	D	E	F	G	H	I	J	K	L	M	N
C961		LG-0CN1040K948	CAPACITOR, FIXED TUBULAR(High d	0.1UF D 50V 80%, -20% F(Y5V) TA	AB	C	D	E	F	G	H	I	J	K	L	M	N
C962		QET41CM-106	CAPACITOR, ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	DEF												
C963		QET41CM-106	CAPACITOR, ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	DEF												
C9A1		QET41HM-105	CAPACITOR, ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	B	G	J										
C9A2		QET41HM-105	CAPACITOR, ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	B	G	J										
C9A3		QET41HM-105	CAPACITOR, ELECTROLYTIC	1.0M SRA/SS50V M FM5 TP(5)	B	G	J										
C9A4		LG-0CN1040K948	CAPACITOR, FIXED TUBULAR(High d	0.1UF D 50V 80%, -20% F(Y5V) TA	B	G	J										
C9A5		QET41CM-106	CAPACITOR, ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	B	G	J										
C9A6		QET41CM-106	CAPACITOR, ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	B	G	J										
C9A7		QET41CM-106	CAPACITOR, ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	B	G	J										
C9A8		QET41CM-106	CAPACITOR, ELECTROLYTIC	10M SRA 16V M FM5 TP(5)	B	G	J										
R101		LG-614-007A	RESISTOR	2.7/2W CEMENT Smps V	AB	C	D	E	F	G	H	I	J	K	L	M	N
R102		QRD161J-184Y	RESISTOR, FIXED CARBON FILM	180K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R103		QRD161J-680Y	RESISTOR, FIXED CARBON FILM	68 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R104		LG-0RS5602K619	RESISTOR, FIXED METAL OXIDE FIL	56K OHM 2 W 5.00% TR	AB	C	D	E	F	G	H	I	J	K	L	M	N
R105		LG-0RF0101A619	RESISTOR, DRAWING	1 OHM 1/2 W(7.0) 5.00% TR	AB	C	D	E	F	G	H	I	J	K	L	M	N
R106		QRD161J-184Y	RESISTOR, FIXED CARBON FILM	180K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R109		LG-0RS0350K619	RESISTOR, FIXED METAL OXIDE FIL	0.35 OHM 2 W 5.00% TR	AB	C	D	E	F	G	H	I	J	K	L	M	N
R112		QRD161J-104Y	RESISTOR, FIXED CARBON FILM	100K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R116		QRD161J-221Y	RESISTOR, FIXED CARBON FILM	220 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R117		QRD161J-222Y	RESISTOR, FIXED CARBON FILM	2.2K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R118		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R119		LG-0RN3301F408	RESISTOR, FIXED METAL FILM	3.3K OHM 1/6 W 1.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R120		LG-0RN3001F408	RESISTOR, FIXED METAL FILM	3K OHM 1/6 W 1.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R125		QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R126		QRD161J-681Y	RESISTOR, FIXED CARBON FILM	680 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R151		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R152		QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R153		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R154		QRD161J-331Y	RESISTOR, FIXED CARBON FILM	330 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R155		QRD161J-332Y	RESISTOR, FIXED CARBON FILM	3.3K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R157		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R158		QRD161J-183Y	RESISTOR, FIXED CARBON FILM	18K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R159		QRD161J-471Y	RESISTOR, FIXED CARBON FILM	470 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R161		QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R170		QRD161J-562Y	RESISTOR, FIXED CARBON FILM	5.6K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R172		QRD161J-271Y	RESISTOR, FIXED CARBON FILM	270 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R173		QRD161J-271Y	RESISTOR, FIXED CARBON FILM	270 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R201		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	FG												
R202		QRD161J-124Y	RESISTOR, FIXED CARBON FILM	120K OHM 1/6 W 5.00% TA26	FG												
R204		QRD161J-473Y	RESISTOR, FIXED CARBON FILM	47K OHM 1/6 W 5.00% TA26	FG												
R301		QRD161J-563Y	RESISTOR, FIXED CARBON FILM	56K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R303		QRD161J-183Y	RESISTOR, FIXED CARBON FILM	18K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R304		QRD161J-103Y	RESISTOR, FIXED CARBON FILM	10K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R305		QRD161J-103Y	RESISTOR, FIXED CARBON FILM	10K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R306		QRD161J-223Y	RESISTOR, FIXED CARBON FILM	2.2K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R307		QRD161J-222Y	RESISTOR, FIXED CARBON FILM	2.2K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R308		QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R309		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R310		QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R311		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R312		QRD161J-683Y	RESISTOR, FIXED CARBON FILM	68K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R313		QRD161J-2R2	RESISTOR, FIXED CARBON FILM	2.2 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R314		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R315		QRD161J-470Y	RESISTOR, FIXED CARBON FILM	47 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R316		QRD161J-101Y	RESISTOR, FIXED CARBON FILM	100 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R317		QRD161J-562Y	RESISTOR, FIXED CARBON FILM	5.6K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R318		QRD161J-392Y	RESISTOR, FIXED CARBON FILM	3.9K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R319		QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R320		QRD161J-151Y	RESISTOR, FIXED CARBON FILM	150 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R321		QRD161J-122Y	RESISTOR, FIXED CARBON FILM	1.2K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R322		QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R323		QRD161J-103Y	RESISTOR, FIXED CARBON FILM	10K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R324		QRD161J-334Y	RESISTOR, FIXED CARBON FILM	330K OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R325		QRD161J-471Y	RESISTOR, FIXED CARBON FILM	470 OHM 1/6 W 5.00% TA26	AB	C	D	E	F	G	H	I	J	K	L	M	N
R326		QRD161J-123Y	RESISTOR, FIXED CARBON FILM	12K OHM 1/6 W 5.00% TA26	AB	C	D	E									

MODEL	MARK	MODEL	MARK	MODEL	MARK
HR-J285EU	A	HR-J595MS	F	HR-J282EU	K
HR-J290EU	B	HR-J295MS	G	HR-J283EU	L
HR-J585EU	C	HR-J595EK	H	HR-J582EU	M
HR-J590EU	D	HR-J295EK	I	HR-J583EU	N
HR-J593EU	E	HR-J293EU	J		

# Δ REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCEFGHI JKLMN	# Δ REF No.	PART No.	PART NAME, DESCRIPTION	SPECIFICATION	ABCEFGHI JKLMN
R5C5	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	Δ L102	LG-616-145H	FILTER(CIRC)	SHT LFS2020V4-04350	ABCEDEFGHI JKLMN
R5C6	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L103	LG-633-088G	COIL, CHOKE	CHOCK(22MH) 5MM TOKO TP	ABCEDEFGHI JKLMN
R5C7	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L104	LG-633-088G	COIL, CHOKE	CHOCK(22MH) 5MM TOKO TP	ABCEDEFGHI JKLMN
R5C9	QRD161J-103Y	RESISTOR, FIXED CARBON FILM	10K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L106	LG-636-004C	COIL	BEAD CORE BFS3550R2FD8, R T/P	ABCEDEFGHI JKLMN
R5P2	QRD161J-103Y	RESISTOR, FIXED CARBON FILM	10K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L201	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	FG
R5P3	QRD161J-103Y	RESISTOR, FIXED CARBON FILM	10K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L301	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	ABCEDEFGHI JKLMN
R5R2	QRD161J-331Y	RESISTOR, FIXED CARBON FILM	330 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L302	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5R3	QRD161J-331Y	RESISTOR, FIXED CARBON FILM	330 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L303	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	ABCEDEFGHI JKLMN
R5R4	QRD161J-331Y	RESISTOR, FIXED CARBON FILM	330 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L304	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	ABCEDEFGHI JKLMN
R5R5	QRD161J-331Y	RESISTOR, FIXED CARBON FILM	330 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L305	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5R7	QRD161J-331Y	RESISTOR, FIXED CARBON FILM	330 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L307	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	ABCEDEFGHI JKLMN
R5R8	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L501	LG-0LA0122K018	INDUCTOR AXIAL LEAD	12M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R5S1	QRD161J-562Y	RESISTOR, FIXED CARBON FILM	5.6K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L503	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5T1	QRD161J-182Y	RESISTOR, FIXED CARBON FILM	1.8K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L504	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	ABCEDEFGHI JKLMN
R5T2	QRD161J-152Y	RESISTOR, FIXED CARBON FILM	1.5K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L505	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5T3	QRD161J-222Y	RESISTOR, FIXED CARBON FILM	2.2K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L506	LG-635-027C	INDUCTOR, RADIAL LEAD	EL0405RA SKI150G-3-K-TDK 15UH	ABCEDEFGHI JKLMN
R5T4	QRD161J-272Y	RESISTOR, FIXED CARBON FILM	2.7K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L5G2	LG-0LR3300K035	INDUCTOR, RADIAL LEAD	330M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5T5	QRD161J-332Y	RESISTOR, FIXED CARBON FILM	3.3K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L5S1	LG-0LA0332K018	INDUCTOR AXIAL LEAD	33M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R5T9	QRD161J-182Y	RESISTOR, FIXED CARBON FILM	1.8K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L702	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5T10	QRD161J-152Y	RESISTOR, FIXED CARBON FILM	1.5K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L703	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R5T11	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L704	LG-0LA0821K018	INDUCTOR AXIAL LEAD	8.2M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R706	QRD161J-221Y	RESISTOR, FIXED CARBON FILM	220 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L705	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	ABCEDEFGHI JKLMN
R707	QRD161J-221Y	RESISTOR, FIXED CARBON FILM	220 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L751	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	CDEF H MN
R709	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	L753	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	CDEF H MN
R753	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	CDEF H MN	L7V1	LG-0LR1000K035	INDUCTOR, RADIAL LEAD	100M K 6X6 L5 TP	B DE J
R754	QRD161J-332Y	RESISTOR, FIXED CARBON FILM	3.3K OHM 1/6 W 5.00% TA26	CDEF H MN	L801	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	CDEF H MN
R755	QRD161J-332Y	RESISTOR, FIXED CARBON FILM	3.3K OHM 1/6 W 5.00% TA26	CDEF H MN	L802	LG-0LR0102J0N5	INDUCTOR, RADIAL LEAD	10UH 5% TP 3X5 TR5	CDEF H MN
R758	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	CDEF H MN	L8R1	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	CDEF H MN
R759	QRD161J-562Y	RESISTOR, FIXED CARBON FILM	5.6K OHM 1/6 W 5.00% TA26	CDEF H MN	L8R2	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	CDEF H MN
R7M1	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDE HI JKLMN	L901	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R7M2	QRD161J-221Y	RESISTOR, FIXED CARBON FILM	220 OHM 1/6 W 5.00% TA26	ABCEDE HI JKLMN	L902	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R7M3	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	ABCEDE HI JKLMN	L904	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R7M5	QRD161J-221Y	RESISTOR, FIXED CARBON FILM	220 OHM 1/6 W 5.00% TA26	ABCEDE HI JKLMN	L905	LG-636-004C	COIL	BEAD CORE BFS3550R2FD8, R T/P	ABCEDEFGHI JKLMN
R7S1	QRD161J-223Y	RESISTOR, FIXED CARBON FILM	22K OHM 1/6 W 5.00% TA26	FG	L906	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	ABCEDEFGHI JKLMN
R7V1	QRD161J-105Y	RESISTOR, FIXED CARBON FILM	1M OHM 1/6 W 5.00% TA26	B DE J	L907	LG-636-004C	COIL	BEAD CORE BFS3550R2FD8, R T/P	ABCEDEFGHI JKLMN
R7V2	QRD161J-104Y	RESISTOR, FIXED CARBON FILM	100K OHM 1/6 W 5.00% TA26	B DE J	L911	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	B DEFGH J
R7V3	QRD161J-682Y	RESISTOR, FIXED CARBON FILM	6.8K OHM 1/6 W 5.00% TA26	B DE J	L912	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	B DEFGH J
R7V4	QRD161J-564Y	RESISTOR, FIXED CARBON FILM	560K OHM 1/6 W 5.00% TA26	B DE J	L914	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	B DEFGH J
R7V5	QRD161J-682Y	RESISTOR, FIXED CARBON FILM	6.8K OHM 1/6 W 5.00% TA26	B DE J	L915	LG-0LA1000K018	INDUCTOR AXIAL LEAD	100M K 2.3X3.4 L5 TP	B DEFGH J
R7V6	QRD161J-564Y	RESISTOR, FIXED CARBON FILM	560K OHM 1/6 W 5.00% TA26	B DE J	CSS01	LG-6600M000002	SWITCH, PUSH	MPU11810MLB0 MIC DC 5V 1MA D-3	ABCEDEFGHI JKLMN
R7V7	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	B DE J	ESS01	LG-4931R-0050C	HOLDER ASSEMBLY	END (DI)	ABCEDEFGHI JKLMN
R7V8	QRD161J-101Y	RESISTOR, FIXED CARBON FILM	100 OHM 1/6 W 5.00% TA26	B DE J	ESS02	LG-4931R-0050C	HOLDER ASSEMBLY	END (DI)	ABCEDEFGHI JKLMN
R7V9	QRD161J-101Y	RESISTOR, FIXED CARBON FILM	100 OHM 1/6 W 5.00% TA26	B DE J	Δ F101	LG-585-011T	FUSE, SLOW BLOW	1600MA 250 V 5.2X20 CY/GL SEMK	ABCEDEFGHI JKLMN
R801	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	CDEF H MN	Δ FH01	LG-586-008B	HOLDER	FUSE CLIP TP SINSUNG	ABCEDEFGHI JKLMN
R802	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	CDEF H MN	Δ FH02	LG-586-008B	HOLDER	FUSE CLIP TP SINSUNG	ABCEDEFGHI JKLMN
R817	QRD161J-335Y	RESISTOR, FIXED CARBON FILM	33M OHM 1/6 W 5.00% TA26	CDEF H MN	JK801	LG-6612R-C002C	JACK, RCA	RCA-208C-06 YUQIU WH-RD	CDEF H MN
R818	QRD161J-333Y	RESISTOR, FIXED CARBON FILM	33K OHM 1/6 W 5.00% TA26	CDEF H MN	JK901	LG-6620RM0002J	JACK, SCART	DSAM-0121 DOOWON 2F-21P(BL-BK)	B DEFG J
R819	QRD161J-272Y	RESISTOR, FIXED CARBON FILM	2.7K OHM 1/6 W 5.00% TA26	CDEF H MN	JK901	LG-6620RM0002K	JACK, SCART	DSAM-0120 DOOWON 1F-21P (BK)	A C I KLMN
R820	QRD161J-393Y	RESISTOR, FIXED CARBON FILM	39K OHM 1/6 W 5.00% TA26	CDEF H MN	JK901	LG-6620RM0002L	JACK, SCART	DSAM-0139 DOOWON 2F-21P(BK-BK)	H
R821	QRD161J-272Y	RESISTOR, FIXED CARBON FILM	2.7K OHM 1/6 W 5.00% TA26	CDEF H MN	LD501	LG-4931R-0017C	HOLDER ASSY	LED(DI-CKD)LOCAL	ABCEDEFGHI JKLMN
R822	QRD161J-333Y	RESISTOR, FIXED CARBON FILM	33K OHM 1/6 W 5.00% TA26	CDEF H MN	LED502	LG-6301R2U001F	LED ASSEMBLY	TOH-30M-G3R1 OASIS UNIVERSAL 4	ABCEDEFGHI JKLMN
R823	QRD161J-471Y	RESISTOR, FIXED CARBON FILM	470 OHM 1/6 W 5.00% TA26	CDEF H MN	MS501	LG-6600JB0005B	SWITCH, MODE	NON 5V 1MA VERTICAL -G	ABCEDEFGHI JKLMN
R824	QRD161J-101Y	RESISTOR, FIXED CARBON FILM	100 OHM 1/6 W 5.00% TA26	CDEF H MN	P3D01	LG-561-234S	CONNECTOR(CIRC), DRAWING	GF120-9S-TS-A LG CABLE 9P 1.25	CDEF H MN
R825	QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560 OHM 1/6 W 5.00% TA26	CDEF H MN	P3D01	LG-561-234Z	CONNECTOR(CIRC)	GF120-3S-TS-A LGC 3PIN 1.25MM	AB G IJKL
R826	QRD161J-182Y	RESISTOR, FIXED CARBON FILM	1.8K OHM 1/6 W 5.00% TA26	CDEF H MN	P3D02	LG-6630R5S010A	CONNECTOR(CIRC)	GF105-06S-TS LG CABLE 6PIN 2MM	ABCEDEFGHI JKLMN
R827	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	CDEF H MN	P3D03	LG-561-251B	CONNECTOR(CIRC), DRAWING	GB201-2P-TS-B(LG)	ABCEDEFGHI JKLMN
R828	QRD161J-102Y	RESISTOR, FIXED CARBON FILM	1K OHM 1/6 W 5.00% TA26	CDEF H MN	PMC01	LG-6630R-BE01L	CONNECTOR(CIRC), BOARD TO BOARD	JE612-12 JAE EUN 12P 2.0MM	ABCEDEFGHI JKLMN
R830	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	CDEF H MN	Δ PW101	LG-561-292B	CONNECTOR	GP390 LGC 3P 3.96 STRAIGHT SN	ABCEDEFGHI JKLMN
R831	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	CDEF H MN	RC501	LG-6712R1940GA	REMOTE CONTROLLER RECEIVER	TSOP2840WE1 VISHAY(TEMIC) 40KH	ABCEDEFGHI JKLMN
R8R1	QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560 OHM 1/6 W 5.00% TA26	CDEF H MN	RS501	LG-6500RAB003A	SENSOR	SG-260 KODENSHI D33 REEL SENSO	ABCEDEFGHI JKLMN
R8R2	QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560 OHM 1/6 W 5.00% TA26	CDEF H MN	RS502	LG-6500RAB003A	SENSOR	SG-260 KODENSHI D33 REEL SENSO	ABCEDEFGHI JKLMN
R901	QRD161J-750Y	RESISTOR, FIXED CARBON FILM	75 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	SW5T1	LG-556-213C	SWITCH, DETECTOR	THV951BAA POSTECH DC 12 V 5-0	ABCEDEFGHI JKLMN
R902	QRD161J-750Y	RESISTOR, FIXED CARBON FILM	75 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	SW5T10	LG-556-213C	SWITCH, DETECTOR	THV951BAA POSTECH DC 12 V 5-0	ABCEDEFGHI JKLMN
R903	QRD161J-392Y	RESISTOR, FIXED CARBON FILM	3.9K OHM 1/6 W 5.00% TA26	A I KL	SW5T11	LG-556-213C	SWITCH, DETECTOR	THV951BAA POSTECH DC 12 V 5-0	ABCEDEFGHI JKLMN
R903	QRD161J-472Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	BCDEFGH J MN	SW5T12	LG-556-213C	SWITCH, DETECTOR	THV951BAA POSTECH DC 12 V 5-0	ABCEDEFGHI JKLMN
R904	QRD161J-473Y	RESISTOR, FIXED CARBON FILM	4.7K OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	SW5T13	LG-556-213C	SWITCH, DETECTOR	THV951BAA POSTECH DC 12 V 5-0	ABCEDEFGHI JKLMN
R905	QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560 OHM 1/6 W 5.00% TA26	ABCEDEFGHI JKLMN	SW5T3	LG-556-213C	SWITCH, DETECTOR	THV951BAA POSTECH DC 12 V 5-0	ABCEDEFGHI JKLMN
R906	QRD161J-561Y	RESISTOR, FIXED CARBON FILM	560						